

Title: Additional draft repertoire for ISO/IEC 10646 6th edition Amendment 2 (CDAM2)

Date: 2022-08-26

WG2 N5196 L2/22-194

Source: Michel Suignard (Code Chart editor)

Status: Summary of character repertoire addition for ISO/IEC 10646 6th edition Amendment 2 (CDAM2)

Action: For review by UTC, WG2 experts

Distribution: UTC and ISO

Replaces:

Status

In addition to be a summary of character repertoire addition for ISO/IEC 10646 6th edition Amendment 2 (CDAM2), this document also presents all characters that constitute tentative new repertoire for future versions of the Unicode Standard after version 15.0 with code positions, representative glyphs and character names.

The intent is to be synchronized with the table of 'Characters Accepted or in Ballot for Future Versions' published in the Unicode pipeline at <https://www.unicode.org/alloc/Pipeline.html>.

Feedback is welcome regarding all aspects of these characters, including whether they are acceptable for eventual encoding and publication.

Manner of Presentation

The character names and code points shown are in the same format used for official Unicode code charts. The new characters are shown in the context of the existing characters, using a yellow highlight to distinguish them.

Note to Reviewers

Please use this document as a summary of UTC review of pending proposals.

Contents

This document lists 1130 characters.

The following list shows all 18 blocks (existing or new) to which characters are proposed to be added, or which have been affected by other changes documented here.

0870-089F Arabic Extended-B

see document L2/22-116

0C00-0C7F Telugu

See document: L2/22-006

0C80-0CFF Kannada

See document: L2/21-006

1B00-1B7F Balinese

See document: L2/22-059

1C80-1C8F Cyrillic Extended-C

See document: L2/22-119

2400-243F Control Pictures

See document: L2/21-235

A720-A7FF Latin Extended-D

See document: L2/22-045 L2/22-113R

105C0-105FF Toghri

See document: L2/20-188r2 22-068

10D40-10D8F Garay

See document: L2/22-048

10EC0-10EFF Arabic Extended-C

See document: L2/22-047

11380-113FF Tulu-Tigalari

See document: L2/22-031

116D0-116FF Myanmar Extended-C

See document: L2/22-046

11BC0-11BFF Sunuwar

See document: L2/21-157R

16100-1613F Gurung Khema

See document: L2/22-157

16D40-16D7F Kirat Rai

See document: L2/22-043R

1CC00-1CEBF Symbols for Legacy Computing Supplement

See document: L2/21-234 L2/21-235

1F800-1F8FF Supplemental Arrows-C

See document: L2/21-234 L2/21-235

1FB00-1FBFF Symbols for Legacy Computing

See document L2/21-235

	087	088	089
0	 0870	 0880	 0890
1	 0871	 0881	 0891
2	 0872	 0882	
3	 0873	 0883	
4	 0874	 0884	
5	 0875	 0885	
6	 0876	 0886	
7	 0877	 0887	 0897
8	 0878	 0888	 0898
9	 0879	 0889	 0899
A	 087A	 088A	 089A
B	 087B	 088B	 089B
C	 087C	 088C	 089C
D	 087D	 088D	 089D
E	 087E	 088E	 089E
F	 087F		 089F

Additions for Quranic orthographies

- 0870 ﺀ ARABIC LETTER ALEF WITH ATTACHED FATHA
 0871 ﺀ ARABIC LETTER ALEF WITH ATTACHED TOP RIGHT FATHA
 0872 ﺀ ARABIC LETTER ALEF WITH RIGHT MIDDLE STROKE
 0873 ﺀ ARABIC LETTER ALEF WITH LEFT MIDDLE STROKE
 0874 ﺀ ARABIC LETTER ALEF WITH ATTACHED KASRA
 0875 ﺀ ARABIC LETTER ALEF WITH ATTACHED BOTTOM RIGHT KASRA
 0876 ﺀ ARABIC LETTER ALEF WITH ATTACHED ROUND DOT ABOVE
 0877 ﺀ ARABIC LETTER ALEF WITH ATTACHED RIGHT ROUND DOT
 0878 ﺀ ARABIC LETTER ALEF WITH ATTACHED LEFT ROUND DOT
 0879 ﺀ ARABIC LETTER ALEF WITH ATTACHED ROUND DOT BELOW
 087A ﺀ ARABIC LETTER ALEF WITH DOT ABOVE
 087B ﺀ ARABIC LETTER ALEF WITH ATTACHED TOP RIGHT FATHA AND DOT ABOVE
 087C ﺀ ARABIC LETTER ALEF WITH RIGHT MIDDLE STROKE AND DOT ABOVE
 087D ﺀ ARABIC LETTER ALEF WITH ATTACHED BOTTOM RIGHT KASRA AND DOT ABOVE
 087E ﺀ ARABIC LETTER ALEF WITH ATTACHED TOP RIGHT FATHA AND LEFT RING
 087F ﺀ ARABIC LETTER ALEF WITH RIGHT MIDDLE STROKE AND LEFT RING
 0880 ﺀ ARABIC LETTER ALEF WITH ATTACHED BOTTOM RIGHT KASRA AND LEFT RING
 0881 ﺀ ARABIC LETTER ALEF WITH ATTACHED RIGHT HAMZA
 0882 ﺀ ARABIC LETTER ALEF WITH ATTACHED LEFT HAMZA
 0883 ﺀ ARABIC TATWEEL WITH OVERSTRUCK HAMZA
 0884 ﺀ ARABIC TATWEEL WITH OVERSTRUCK WAW
 0885 ﺀ ARABIC TATWEEL WITH TWO DOTS BELOW
 0886 ﺀ ARABIC LETTER THIN YEH
 • no final or isolated forms are attested
 0887 • ARABIC BASELINE ROUND DOT
 0888 • ARABIC RAISED ROUND DOT

Additions for Bosnian orthographies

- 0889 ﺀ ARABIC LETTER NOON WITH INVERTED SMALL V
 088A ﺀ ARABIC LETTER HAH WITH INVERTED SMALL V BELOW

Additions for Pegon orthographies

- 088B ﺀ ARABIC LETTER TAH WITH DOT BELOW
 • Pegon, Malagasy
 088C ﺀ ARABIC LETTER TAH WITH THREE DOTS BELOW
 • Pegon alternative for 088B ﺀ
 088D ﺀ ARABIC LETTER KEHEH WITH TWO DOTS VERTICALLY BELOW
 • Sundanese Pegon

Abbreviation mark

- 088E ﺀ ARABIC VERTICAL TAIL
 • mark used to indicate abbreviations in early movable type texts from Iran
 • only attested in final form

Supertending currency symbols

- 0890 ﺀ ARABIC POUND MARK ABOVE
 • Egyptian pound
 0891 ﺀ ARABIC PIASTRE MARK ABOVE
 • Egyptian piastre

Vowel sign

- 0897 ﺀ ARABIC PEPET
 • represent vowel ə in Pegon script
 → A9BC ﺀ javanese vowel sign pepet

Additions for Quranic orthographies

- 0898 ﺀ ARABIC SMALL HIGH WORD AL-JUZ
 0899 ﺀ ARABIC SMALL LOW WORD ISHMAAM
 089A ﺀ ARABIC SMALL LOW WORD IMAALA
 089B ﺀ ARABIC SMALL LOW WORD TASHEEL
 089C ﺀ ARABIC MADDA WAAJIB
 → 0653 ﺀ arabic maddah above
 089D ﺀ ARABIC SUPERSCRIPT ALEF MOKHASSAS
 089E ﺀ ARABIC DOUBLED MADDA
 089F ﺀ ARABIC HALF MADDA OVER MADDA

	0C0	0C1	0C2	0C3	0C4	0C5	0C6	0C7
0	౱ 0C00	ఐ 0C10	త 0C20	ర 0C30	్రి 0C40		ఋ 0C60	
1	ృ 0C01		డ 0C21	ఱ 0C31	ృ 0C41		ౠ 0C61	
2	ౄ 0C02	ఓ 0C12	ఢ 0C22	ల 0C32	్రి 0C42		ౡ 0C62	
3	౅ 0C03	ఓ 0C13	ణ 0C23	ళ 0C33	్రి 0C43		ౢ 0C63	
4	ె 0C04	ఔ 0C14	త 0C24	ఱ 0C34	్రి 0C44			
5	అ 0C05	క 0C15	థ 0C25	వ 0C35		్రి 0C55		
6	ఆ 0C06	ఖ 0C16	ద 0C26	శ 0C36	్రి 0C46	్రి 0C56	ం 0C66	
7	ఇ 0C07	గ 0C17	ధ 0C27	ష 0C37	్రి 0C47		ం 0C67	ం 0C77
8	ఈ 0C08	ఘ 0C18	న 0C28	స 0C38	్రి 0C48	్రి 0C58	ం 0C68	ం 0C78
9	ఉ 0C09	జ 0C19		హ 0C39		్రి 0C59	ం 0C69	ం 0C79
A	ఊ 0C0A	చ 0C1A	ప 0C2A		్రి 0C4A	్రి 0C5A	ం 0C6A	ం 0C7A
B	ఋ 0C0B	భ 0C1B	ఫ 0C2B		్రి 0C4B		ం 0C6B	ం 0C7B
C	ౠ 0C0C	జ 0C1C	బ 0C2C	్రి 0C3C	్రి 0C4C	ౠ 0C5C	ం 0C6C	ం 0C7C
D		ఝ 0C1D	భ 0C2D	్రి 0C3D	్రి 0C4D	్రి 0C5D	ం 0C6D	ం 0C7D
E	ఎ 0C0E	ఞ 0C1E	మ 0C2E	్రి 0C3E			ం 0C6E	ం 0C7E
F	ఏ 0C0F	ట 0C1F	య 0C2F	్రి 0C3F			ం 0C6F	ం 0C7F

Various signs

0C00	𑑖	TELUGU SIGN COMBINING CANDRABINDU ABOVE
0C01	𑑗	TELUGU SIGN CANDRABINDU = arasunna • indicates a contextually elided nasal
0C02	𑑘	TELUGU SIGN ANUSVARA = sunna • used in Prakrit language texts to indicate gemination of the following consonant
0C03	𑑙	TELUGU SIGN VISARGA
0C04	𑑚	TELUGU SIGN COMBINING ANUSVARA ABOVE • used in Prakrit language texts for the linguistic anusvara

Independent vowels

0C05	అ	TELUGU LETTER A
0C06	ఆ	TELUGU LETTER AA
0C07	ఇ	TELUGU LETTER I
0C08	ఈ	TELUGU LETTER II
0C09	ఉ	TELUGU LETTER U
0C0A	ఊ	TELUGU LETTER UU
0C0B	ఋ	TELUGU LETTER VOCALIC R
0C0C	ౠ	TELUGU LETTER VOCALIC L
0C0D	☐	<reserved>
0C0E	ఎ	TELUGU LETTER E
0C0F	ఏ	TELUGU LETTER EE
0C10	ఐ	TELUGU LETTER AI
0C11	☐	<reserved>
0C12	ఒ	TELUGU LETTER O
0C13	ఓ	TELUGU LETTER OO
0C14	ఔ	TELUGU LETTER AU

Consonants

0C15	క	TELUGU LETTER KA
0C16	ఖ	TELUGU LETTER KHA
0C17	గ	TELUGU LETTER GA
0C18	ఘ	TELUGU LETTER GHA
0C19	ఙ	TELUGU LETTER NGA
0C1A	చ	TELUGU LETTER CA
0C1B	ఛ	TELUGU LETTER CHA
0C1C	జ	TELUGU LETTER JA
0C1D	ఝ	TELUGU LETTER JHA
0C1E	ఞ	TELUGU LETTER NYA
0C1F	ట	TELUGU LETTER TTA
0C20	ఠ	TELUGU LETTER TTHA
0C21	డ	TELUGU LETTER DDA
0C22	ఢ	TELUGU LETTER DDHA
0C23	ణ	TELUGU LETTER NNA
0C24	త	TELUGU LETTER TA
0C25	థ	TELUGU LETTER THA
0C26	ద	TELUGU LETTER DA
0C27	ధ	TELUGU LETTER DHA
0C28	న	TELUGU LETTER NA
0C29	☐	<reserved>
0C2A	ప	TELUGU LETTER PA
0C2B	ఫ	TELUGU LETTER PHA
0C2C	బ	TELUGU LETTER BA
0C2D	భ	TELUGU LETTER BHA
0C2E	మ	TELUGU LETTER MA
0C2F	య	TELUGU LETTER YA
0C30	ర	TELUGU LETTER RA
0C31	ఱ	TELUGU LETTER RRA

0C32	ల	TELUGU LETTER LA
0C33	ళ	TELUGU LETTER LLA
0C34	ఱ	TELUGU LETTER LLLA
0C35	వ	TELUGU LETTER VA
0C36	శ	TELUGU LETTER SHA
0C37	ష	TELUGU LETTER SSA
0C38	స	TELUGU LETTER SA
0C39	హ	TELUGU LETTER HA

Sign

0C3C ♀ **TELUGU SIGN NUKTA**

- used for Tamil transliteration and Perso-Arabic phonemes
- can also appear as a large dot, should be placed sufficiently below the baseline of a consonant to avoid confusion/collision with the aspiration marker

Addition for Sanskrit

003D 2 TELUGU SIGN AVAGRAHA

Dependent vowel signs

0C3E	అ	TELUGU VOWEL SIGN AA
0C3F	ఆ	TELUGU VOWEL SIGN I
0C40	ఇ	TELUGU VOWEL SIGN II
0C41	ఉ	TELUGU VOWEL SIGN U
0C42	ఊ	TELUGU VOWEL SIGN UU
0C43	ఋ	TELUGU VOWEL SIGN VOCALIC R
0C44	ౠ	TELUGU VOWEL SIGN VOCALIC RR
0C45	◻	<reserved>
0C46	ఎ	TELUGU VOWEL SIGN E
0C47	ఋ	TELUGU VOWEL SIGN EE
0C48	ఌ	TELUGU VOWEL SIGN AI
	≡ 0C46 ఌ 0C56 ౠ	
0C49	◻	<reserved>
0C4A	ఋ	TELUGU VOWEL SIGN O
0C4B	ౠ	TELUGU VOWEL SIGN OO
0C4C	అ	TELUGU VOWEL SIGN AU

Virama

0C4D ఌ TELUGU SIGN VIRAMA
= halant (the preferred name)

Various signs

0C55	○ ^s	TELUGU LENGTH MARK
0C56	○	TELUGU AI LENGTH MARK

Historic phonetic variants

0C58	తా	TELUGU LETTER TSA
0C59	డా	TELUGU LETTER DZA
0C5A	ధ	TELUGU LETTER RRRA

- letter for an alveolar consonant whose exact phonetic value is not known

Ligature

0C5C శ్రీ TELUGU ARCHAIC SHRII

- auspicious word shrii
- does not combine with other letters

Consonant

0C5D ಀ TELUGU LETTER NAKAARA POLLU

- vowelless form of na
- 0CDD ಀ kannada letter nakaara pollu
- 0D7B ഃ malayalam letter chillu n

Additional vowels for Sanskrit

0C60 ఋ TELUGU LETTER VOCALIC RR

0C61 ం TELUGU LETTER VOCALIC LL

Dependent vowels

0C62 ం TELUGU VOWEL SIGN VOCALIC L

0C63 ం TELUGU VOWEL SIGN VOCALIC LL

Reserved

For viram punctuation, use the generic Indic 0964 and 0965.

0C64 <reserved>

→ 0964 I devanagari danda

0C65 <reserved>

→ 0965 II devanagari double danda

Digits

0C66 ౦ TELUGU DIGIT ZERO

0C67 ౧ TELUGU DIGIT ONE

0C68 ౨ TELUGU DIGIT TWO

0C69 ౩ TELUGU DIGIT THREE

0C6A ౪ TELUGU DIGIT FOUR

0C6B ౫ TELUGU DIGIT FIVE

0C6C ౬ TELUGU DIGIT SIX

0C6D ౭ TELUGU DIGIT SEVEN

0C6E ౮ TELUGU DIGIT EIGHT

0C6F ౯ TELUGU DIGIT NINE

Sign

0C77 ం TELUGU SIGN SIDDHAM

= siddhirastu

• used at the beginning of texts as an invocation

→ A8FC ం devanagari sign siddham

→ 111DB ం sharada sign siddham

Telugu fractions and weights

0C78 ౧౪ TELUGU FRACTION DIGIT ZERO FOR ODD POWERS OF FOUR

0C79 ౧౫ TELUGU FRACTION DIGIT ONE FOR ODD POWERS OF FOUR

0C7A ౧౬ TELUGU FRACTION DIGIT TWO FOR ODD POWERS OF FOUR

0C7B ౧౭ TELUGU FRACTION DIGIT THREE FOR ODD POWERS OF FOUR

0C7C ౧౮ TELUGU FRACTION DIGIT ONE FOR EVEN POWERS OF FOUR

0C7D ౧౯ TELUGU FRACTION DIGIT TWO FOR EVEN POWERS OF FOUR

0C7E ౨౦ TELUGU FRACTION DIGIT THREE FOR EVEN POWERS OF FOUR

0C7F ౨౧ TELUGU SIGN TUUMU

	0C8	0C9	0CA	0CB	0CC	0CD	0CE	0CF
0	ಁ 0C80	ಁ 0C90	ರ 0CA0	ರ 0CB0	ೀ 0CC0		ಮೊ 0CE0	
1	ಃ 0C81		ಡ 0CA1	ಱ 0CB1	ು 0CC1		಼ 0CE1	಼ 0CF1
2	ಂ 0C82	ಁ 0C92	ಡ 0CA2	ಲ 0CB2	ೂ 0CC2		಼ 0CE2	಼ 0CF2
3	ಃ 0C83	ಁ 0C93	ಣ 0CA3	ಳ 0CB3	ೂ 0CC3		಼ 0CE3	಼ 0CF3
4	ಁ 0C84	಼ 0C94	ತ 0CA4		ೂ 0CC4			
5	ಅ 0C85	ಕ 0C95	ಢ 0CA5	ಬ 0CB5		ೇ 0CD5		
6	ಆ 0C86	ಖ 0C96	ದ 0CA6	ಪ 0CB6	ಿ 0CC6	ು 0CD6	೦ 0CE6	
7	ಇ 0C87	ಗ 0C97	ಢ 0CA7	ಪ 0CB7	ೀ 0CC7		೦ 0CE7	
8	ಈ 0C88	ಘ 0C98	ಢ 0CA8	಼ 0CB8	ಿ 0CC8		೦ 0CE8	
9	ಉ 0C89	ಜ 0C99		ಱ 0CB9			೦ 0CE9	
A	ಊ 0C8A	ಚ 0C9A	಼ 0CAA		ಿ 0CCA		೦ 0CEA	
B	ಋ 0C8B	ಛ 0C9B	಼ 0CAB		ಿ 0CCB		೦ 0CEB	
C	ಋ 0C8C	ಞ 0C9C	ಬ 0CAC	ಃ 0CBC	಼ 0CCC	ಠ 0CDC	಼ 0CEC	
D		ಝ 0C9D	ಭ 0CAD	ಃ 0CBD	಼ 0CCD	ಠ 0CDD	಼ 0CED	
E	ಎ 0C8E	ಞ 0C9E	ಮ 0CAE	಼ 0CBE		ಱ 0CDE	಼ 0CEE	
F	ಏ 0C8F	ಱ 0C9F	ಯ 0CAF	ಿ 0CBF			಼ 0CEF	

Various signs

OC80	◌	KANNADA SIGN SPACING CANDRABINDU
OC81	◌	KANNADA SIGN CANDRABINDU
OC82	◌	KANNADA SIGN ANUSVARA used in Konkani, Havyaka Kannada (Havigannada) and Awadhi texts to indicate regular anusvara
OC83	◌	KANNADA SIGN VISARGA
OC84	◌	KANNADA SIGN SIDDHAM = siddhirastu - used at the beginning of texts as an invocation → A8FC ◌ devanagari sign siddham → 111DB ◌ sharada sign siddham

Independent vowels

OC85	ಅ	KANNADA LETTER A
OC86	ಆ	KANNADA LETTER AA
OC87	ಇ	KANNADA LETTER I
OC88	ಈ	KANNADA LETTER II
OC89	ಉ	KANNADA LETTER U
OC8A	ಊ	KANNADA LETTER UU
OC8B	ಋ	KANNADA LETTER VOCALIC R
OC8C	ೠ	KANNADA LETTER VOCALIC L
OC8D	◌	<reserved>
OC8E	ಎ	KANNADA LETTER E
OC8F	ಏ	KANNADA LETTER EE
OC90	ಐ	KANNADA LETTER AI
OC91	◌	<reserved>
OC92	ಒ	KANNADA LETTER O
OC93	ಓ	KANNADA LETTER OO
OC94	ಔ	KANNADA LETTER AU

Consonants

OC95	ಕ	KANNADA LETTER KA
OC96	ಖ	KANNADA LETTER KHA
OC97	ಗ	KANNADA LETTER GA
OC98	ಘ	KANNADA LETTER GHA
OC99	ಜ	KANNADA LETTER NGA
OC9A	ಚ	KANNADA LETTER CA
OC9B	ಛ	KANNADA LETTER CHA
OC9C	ಜ	KANNADA LETTER JA
OC9D	ಝ	KANNADA LETTER JHA
OC9E	ಞ	KANNADA LETTER NYA
OC9F	ಟ	KANNADA LETTER TTA
OCA0	ಠ	KANNADA LETTER TTHA
OCA1	ಡ	KANNADA LETTER DDA
OCA2	ಢ	KANNADA LETTER DDHA
OCA3	ಣ	KANNADA LETTER NNA
OCA4	ತ	KANNADA LETTER TA
OCA5	ಥ	KANNADA LETTER THA
OCA6	ದ	KANNADA LETTER DA
OCA7	ಧ	KANNADA LETTER DHA
OCA8	ನ	KANNADA LETTER NA
OCA9	◌	<reserved>
OCAA	ಪ	KANNADA LETTER PA
OCAb	ಫ	KANNADA LETTER PHA
OCAC	ಬ	KANNADA LETTER BA
OCAD	ಭ	KANNADA LETTER BHA
OCAE	ಮ	KANNADA LETTER MA
OCaf	ಯ	KANNADA LETTER YA
OCB0	ರ	KANNADA LETTER RA
OCB1	ಱ	KANNADA LETTER RRA
OCB2	ಲ	KANNADA LETTER LA

0CB3	ಳ	KANNADA LETTER LLA
0CB4	◌	<reserved>
0CB5	ವ	KANNADA LETTER VA
0CB6	ಶ	KANNADA LETTER SHA
0CB7	ಷ	KANNADA LETTER SSA
0CB8	ಸ	KANNADA LETTER SA
0CB9	ಹ	KANNADA LETTER HA

Various signs

0CBC	◌	KANNADA SIGN NUKTA
0CBD	ಽ	KANNADA SIGN AVAGRAHA

Dependent vowel signs

0CBE	ಾ	KANNADA VOWEL SIGN AA
0CBF	ಿ	KANNADA VOWEL SIGN I
0CC0	ೀ	KANNADA VOWEL SIGN II ≡ 0CBF ಿ 0CD5 ೆ
0CC1	ು	KANNADA VOWEL SIGN U
0CC2	ೂ	KANNADA VOWEL SIGN UU
0CC3	ೃ	KANNADA VOWEL SIGN VOCALIC R
0CC4	ೠ	KANNADA VOWEL SIGN VOCALIC RR
0CC5	◌	<reserved>
0CC6	ೆ	KANNADA VOWEL SIGN E
0CC7	ೇ	KANNADA VOWEL SIGN EE ≡ 0CC6 ೆ 0CD5 ೆ
0CC8	ೈ	KANNADA VOWEL SIGN AI ≡ 0CC6 ೆ 0CD6 ೃ
0CC9	◌	<reserved>
0CCA	ೊ	KANNADA VOWEL SIGN O ≡ 0CC6 ೆ 0CC2 ಳ
0CCB	ೋ	KANNADA VOWEL SIGN OO ≡ 0CCA ೊ 0CD5 ೆ
0CCC	ೌ	KANNADA VOWEL SIGN AU

Virama

0CCD	ಂ	KANNADA SIGN VIRAMA preferred name is halant
------	---	--

Various signs

0CD5	ಂ	KANNADA LENGTH MARK
0CD6	ಂ	KANNADA AI LENGTH MARK

Ligature

0CDC	ಠ	KANNADA ARCHAIC SHRII - auspicious word shrī - does not combine with other letters
------	---	---

Additional consonants

0CDD	ಱ	KANNADA LETTER NAKAARA POLLU - vowelless form of na → 0C5D ಱ telugu letter nakaara pollu → 0D7B ಱ malayalam letter chillu n
0CDE	ಱ	KANNADA LETTER FA × KANNADA LETTER LLLA - obsolete historic letter - name is a mistake for LLLA

Additional vowels for Sanskrit

0CE0	ಋ	KANNADA LETTER VOCALIC RR
0CE1	ೠ	KANNADA LETTER VOCALIC LL

Dependent vowels

0CE2	ೃ	KANNADA VOWEL SIGN VOCALIC L
0CE3	ೠ	KANNADA VOWEL SIGN VOCALIC LL

Reserved

For viram punctuation, use the generic Indic 0964 and 0965.

OCE4  <reserved>

→ 0964 I devanagari danda

OCE5  <reserved>

→ 0965 II devanagari double danda

Digits

OCE6 ೦ KANNADA DIGIT ZERO

OCE7 ೧ KANNADA DIGIT ONE

OCE8 ೨ KANNADA DIGIT TWO

OCE9 ೩ KANNADA DIGIT THREE

OCEA ೪ KANNADA DIGIT FOUR

OCEB ೫ KANNADA DIGIT FIVE

OCEC ೬ KANNADA DIGIT SIX

OCED ೭ KANNADA DIGIT SEVEN

OCEE ೮ KANNADA DIGIT EIGHT

OCEF ೯ KANNADA DIGIT NINE

Signs used in Sanskrit

OCF1  KANNADA SIGN JIHVAMULIYA

→ 1CF5  vedic sign jihvamuliya

OCF2  KANNADA SIGN UPADHMANIYA

→ 1CF6  vedic sign upadhmaniya

OCF3  KANNADA SIGN COMBINING ANUSVARA ABOVE RIGHT

- used in Konkani, Havyaka Kannada (Havigannada) and Awadhi texts to indicate anunāsikā

	1B0	1B1	1B2	1B3	1B4	1B5	1B6	1B7
0	 1B00	 1B10	 1B20	 1B30	 1B40	 1B50	 1B60	 1B70
1	 1B01	 1B11	 1B21	 1B31	 1B41	 1B51	 1B61	 1B71
2	 1B02	 1B12	 1B22	 1B32	 1B42	 1B52	 1B62	 1B72
3	 1B03	 1B13	 1B23	 1B33	 1B43	 1B53	 1B63	 1B73
4	 1B04	 1B14	 1B24	 1B34	 1B44	 1B54	 1B64	 1B74
5	 1B05	 1B15	 1B25	 1B35	 1B45	 1B55	 1B65	 1B75
6	 1B06	 1B16	 1B26	 1B36	 1B46	 1B56	 1B66	 1B76
7	 1B07	 1B17	 1B27	 1B37	 1B47	 1B57	 1B67	 1B77
8	 1B08	 1B18	 1B28	 1B38	 1B48	 1B58	 1B68	 1B78
9	 1B09	 1B19	 1B29	 1B39	 1B49	 1B59	 1B69	 1B79
A	 1B0A	 1B1A	 1B2A	 1B3A	 1B4A	 1B5A	 1B6A	 1B7A
B	 1B0B	 1B1B	 1B2B	 1B3B	 1B4B	 1B5B	 1B6B	 1B7B
C	 1B0C	 1B1C	 1B2C	 1B3C	 1B4C	 1B5C	 1B6C	 1B7C
D	 1B0D	 1B1D	 1B2D	 1B3D		 1B5D	 1B6D	 1B7D
E	 1B0E	 1B1E	 1B2E	 1B3E	 1B4E	 1B5E	 1B6E	 1B7E
F	 1B0F	 1B1F	 1B2F	 1B3F	 1B4F	 1B5F	 1B6F	 1B7F

Various signs

- 1B00 𑀧 BALINESE SIGN ULU RICEM
= ardhacandra
- 1B01 𑀨 BALINESE SIGN ULU CANDRA
= candrabindu
- 1B02 𑀩 BALINESE SIGN CECEK
= anusvara
- 1B03 𑀪 BALINESE SIGN SURANG
= final r
• also used for repha in transliteration of Kawi
→ A982 𑀫 javanese sign layar
- 1B04 𑀬 BALINESE SIGN BISAH
= visarga

Independent vowels

- 1B05 𑀭 BALINESE LETTER AKARA
= a
- 1B06 𑀮 BALINESE LETTER AKARA TEDUNG
= aa
≡ 1B05 𑀭 1B35 𑀯
- 1B07 𑀯 BALINESE LETTER IKARA
= i
- 1B08 𑀰 BALINESE LETTER IKARA TEDUNG
= ii
≡ 1B07 𑀯 1B35 𑀯
- 1B09 𑀱 BALINESE LETTER UKARA
= u
- 1B0A 𑀲 BALINESE LETTER UKARA TEDUNG
= uu
≡ 1B09 𑀱 1B35 𑀯
- 1B0B 𑀳 BALINESE LETTER RA REPA
= vocalic r
- 1B0C 𑀴 BALINESE LETTER RA REPA TEDUNG
= vocalic rr
≡ 1B0B 𑀳 1B35 𑀯
- 1B0D 𑀵 BALINESE LETTER LA LENGHA
= vocalic l
- 1B0E 𑀶 BALINESE LETTER LA LENGHA TEDUNG
= vocalic ll
≡ 1B0D 𑀵 1B35 𑀯
- 1B0F 𑀷 BALINESE LETTER EKARA
= e
- 1B10 𑀸 BALINESE LETTER AIKARA
= ai
- 1B11 𑀹 BALINESE LETTER OKARA
= o
- 1B12 𑀺 BALINESE LETTER OKARA TEDUNG
= au
≡ 1B11 𑀹 1B35 𑀯

Consonants

- 1B13 𑀻 BALINESE LETTER KA
- 1B14 𑀼 BALINESE LETTER KA MAHAPRANA
= kha
- 1B15 𑀽 BALINESE LETTER GA
- 1B16 𑀾 BALINESE LETTER GA GORA
= gha
- 1B17 𑀿 BALINESE LETTER NGA
- 1B18 𑁀 BALINESE LETTER CA
- 1B19 𑁁 BALINESE LETTER CA LACA
= cha
- 1B1A 𑁂 BALINESE LETTER JA
- 1B1B 𑁃 BALINESE LETTER JA JERA
= jha
- 1B1C 𑁄 BALINESE LETTER NYA

- 1B1D 𑁅 BALINESE LETTER TA LATIK
= tta
- 1B1E 𑁆 BALINESE LETTER TA MURDA MAHAPRANA
= ttha
- 1B1F 𑁇 BALINESE LETTER DA MURDA ALPAPRANA
= dda
- 1B20 𑁈 BALINESE LETTER DA MURDA MAHAPRANA
= ddha
- 1B21 𑁉 BALINESE LETTER NA RAMBAT
= nna
- 1B22 𑁊 BALINESE LETTER TA
- 1B23 𑁋 BALINESE LETTER TA TAWA
= tha
- 1B24 𑁌 BALINESE LETTER DA
- 1B25 𑁍 BALINESE LETTER DA MADU
= dha
- 1B26 𑁎 BALINESE LETTER NA
- 1B27 𑁏 BALINESE LETTER PA
- 1B28 𑁐 BALINESE LETTER PA KAPAL
= pha
- 1B29 𑁑 BALINESE LETTER BA
- 1B2A 𑁒 BALINESE LETTER BA KEMBANG
= bha
- 1B2B 𑁓 BALINESE LETTER MA
- 1B2C 𑁔 BALINESE LETTER YA
- 1B2D 𑁕 BALINESE LETTER RA
- 1B2E 𑁖 BALINESE LETTER LA
- 1B2F 𑁗 BALINESE LETTER WA
- 1B30 𑁘 BALINESE LETTER SA SAGA
= sha
- 1B31 𑁙 BALINESE LETTER SA SAPA
= ssa
- 1B32 𑁚 BALINESE LETTER SA
- 1B33 𑁛 BALINESE LETTER HA

Sign

- 1B34 𑁜 BALINESE SIGN REREKAN
= nukta

Dependent vowel signs

- 1B35 𑁝 BALINESE VOWEL SIGN TEDUNG
= aa
- 1B36 𑁞 BALINESE VOWEL SIGN ULU
= i
- 1B37 𑁟 BALINESE VOWEL SIGN ULU SARI
= ii
- 1B38 𑁠 BALINESE VOWEL SIGN SUKU
= u
- 1B39 𑁡 BALINESE VOWEL SIGN SUKU ILUT
= uu
- 1B3A 𑁢 BALINESE VOWEL SIGN RA REPA
= vocalic r
- 1B3B 𑁣 BALINESE VOWEL SIGN RA REPA TEDUNG
= vocalic rr
≡ 1B3A 𑁢 1B35 𑁝
- 1B3C 𑁤 BALINESE VOWEL SIGN LA LENGHA
= vocalic l
- 1B3D 𑁥 BALINESE VOWEL SIGN LA LENGHA TEDUNG
= vocalic ll
≡ 1B3C 𑁤 1B35 𑁝
- 1B3E 𑁦 BALINESE VOWEL SIGN TALING
= e
- 1B3F 𑁧 BALINESE VOWEL SIGN TALING REPA
= ai

- 1B40 𑀓 BALINESE VOWEL SIGN TALING TEDUNG
= o
≡ 1B3E 𑀓 1B35 𑀓
- 1B41 𑀔 BALINESE VOWEL SIGN TALING REPA TEDUNG
= au
≡ 1B3F 𑀔 1B35 𑀓
- 1B42 𑀕 BALINESE VOWEL SIGN PEPET
= ae
- 1B43 𑀖 BALINESE VOWEL SIGN PEPET TEDUNG
= oe
≡ 1B42 𑀕 1B35 𑀓

Sign

- 1B44 𑀗 BALINESE ADEG ADEG
= virama

Additional consonants

- 1B45 𑀘 BALINESE LETTER KAF SASAK
- 1B46 𑀙 BALINESE LETTER KHOT SASAK
- 1B47 𑀚 BALINESE LETTER TZIR SASAK
- 1B48 𑀛 BALINESE LETTER EF SASAK
- 1B49 𑀜 BALINESE LETTER VE SASAK
- 1B4A 𑀝 BALINESE LETTER ZAL SASAK
- 1B4B 𑀞 BALINESE LETTER ASYURA SASAK
- 1B4C 𑀟 BALINESE LETTER ARCHAIC JNYA
- used in older texts in place of the ja + nya conjunct
 - A998 𑀠 javanese letter nya murda

Punctuation

may indicate emphasis or a finer division within text

- 1B4E 𑀡 BALINESE INVERTED CARIK SIKI
- 1B4F 𑀢 BALINESE INVERTED CARIK PAREREN

Digits

- 1B50 𑀣 BALINESE DIGIT ZERO
- 1B51 𑀤 BALINESE DIGIT ONE
- 1B52 𑀥 BALINESE DIGIT TWO
- 1B53 𑀦 BALINESE DIGIT THREE
- 1B54 𑀧 BALINESE DIGIT FOUR
- 1B55 𑀨 BALINESE DIGIT FIVE
- 1B56 𑀩 BALINESE DIGIT SIX
- 1B57 𑀪 BALINESE DIGIT SEVEN
- 1B58 𑀫 BALINESE DIGIT EIGHT
- 1B59 𑀬 BALINESE DIGIT NINE

Punctuation

- 1B5A 𑀭 BALINESE PANTI
= section
- 1B5B 𑀮 BALINESE PAMADA
= honorific section
- 1B5C 𑀯 BALINESE WINDU
= punctuation ring
- 1B5D 𑀰 BALINESE CARIK PAMUNGKAH
= colon
- 1B5E 𑀱 BALINESE CARIK SIKI
= danda
→ 0964 I devanagari danda
- 1B5F 𑀲 BALINESE CARIK PAREREN
= double danda
→ 0965 II devanagari double danda
- 1B60 𑀳 BALINESE PAMENENG
= line-breaking hyphen

Musical symbols for notes

- 1B61 𑀴 BALINESE MUSICAL SYMBOL DONG

- 1B62 𑀵 BALINESE MUSICAL SYMBOL DENG
- 1B63 𑀶 BALINESE MUSICAL SYMBOL DUNG
- 1B64 𑀷 BALINESE MUSICAL SYMBOL DANG
- 1B65 𑀸 BALINESE MUSICAL SYMBOL DANG SURANG
- 1B66 𑀹 BALINESE MUSICAL SYMBOL DING
- 1B67 𑀺 BALINESE MUSICAL SYMBOL DAENG
- 1B68 𑀻 BALINESE MUSICAL SYMBOL DEUNG
- 1B69 𑀼 BALINESE MUSICAL SYMBOL DAING
- 1B6A 𑀽 BALINESE MUSICAL SYMBOL DANG GEDE

Diacritical marks for musical symbols

- 1B6B 𑀾 BALINESE MUSICAL SYMBOL COMBINING TEGEH
- 1B6C 𑀿 BALINESE MUSICAL SYMBOL COMBINING ENDEP
- 1B6D 𑁀 BALINESE MUSICAL SYMBOL COMBINING KEMPUL
- 1B6E 𑁁 BALINESE MUSICAL SYMBOL COMBINING KEMPLI
- 1B6F 𑁂 BALINESE MUSICAL SYMBOL COMBINING JEGOGAN
- 1B70 𑁃 BALINESE MUSICAL SYMBOL COMBINING KEMPUL WITH JEGOGAN
- 1B71 𑁄 BALINESE MUSICAL SYMBOL COMBINING KEMPLI WITH JEGOGAN
- 1B72 𑁅 BALINESE MUSICAL SYMBOL COMBINING BENDE
- 1B73 𑁆 BALINESE MUSICAL SYMBOL COMBINING GONG

Musical symbols

- 1B74 𑁇 BALINESE MUSICAL SYMBOL RIGHT-HAND OPEN DUG
- 1B75 𑁈 BALINESE MUSICAL SYMBOL RIGHT-HAND OPEN DAG
- 1B76 𑁉 BALINESE MUSICAL SYMBOL RIGHT-HAND CLOSED TUK
- 1B77 𑁊 BALINESE MUSICAL SYMBOL RIGHT-HAND CLOSED TAK
- 1B78 𑁋 BALINESE MUSICAL SYMBOL LEFT-HAND OPEN PANG
- 1B79 𑁌 BALINESE MUSICAL SYMBOL LEFT-HAND OPEN PUNG
- 1B7A 𑁍 BALINESE MUSICAL SYMBOL LEFT-HAND CLOSED PLAK
- 1B7B 𑁎 BALINESE MUSICAL SYMBOL LEFT-HAND CLOSED PLUK
- 1B7C 𑁏 BALINESE MUSICAL SYMBOL LEFT-HAND OPEN PING

Punctuation

- 1B7D 𑁐 BALINESE PANTI LANTANG
= end of text
- 1B7E 𑁑 BALINESE PAMADA LANTANG
= end of text
- 1B7F 𑁒 BALINESE PANTI BAWAK
• may indicate a finer division within text

1C8	
0	Ѳ 1C80
1	ѳ 1C81
2	Ѵ 1C82
3	ѵ 1C83
4	Ѷ 1C84
5	ѷ 1C85
6	Ѹ 1C86
7	ѹ 1C87
8	Ѻ 1C88
9	ѻ 1C89
A	Ѽ 1C8A
B	
C	
D	
E	
F	

Historic letter variants

1C80	Ѳ	CYRILLIC SMALL LETTER ROUNDED VE → 0432 Ѳ cyrillic small letter ve
1C81	ѳ	CYRILLIC SMALL LETTER LONG-LEGGED DE → 0434 ѳ cyrillic small letter de
1C82	Ѵ	CYRILLIC SMALL LETTER NARROW O → 043E Ѵ cyrillic small letter o
1C83	ѵ	CYRILLIC SMALL LETTER WIDE ES → 0441 ѵ cyrillic small letter es
1C84	Ѷ	CYRILLIC SMALL LETTER TALL TE → 0442 Ѷ cyrillic small letter te
1C85	ѷ	CYRILLIC SMALL LETTER THREE-LEGGED TE → 0442 ѷ cyrillic small letter te
1C86	Ѹ	CYRILLIC SMALL LETTER TALL HARD SIGN → 044A Ѹ cyrillic small letter hard sign
1C87	ѹ	CYRILLIC SMALL LETTER TALL YAT → 0463 ѹ cyrillic small letter yat
1C88	Ѻ	CYRILLIC SMALL LETTER UNBLENDED UK → 0479 Ѻ cyrillic small letter uk → A64B Ѻ cyrillic small letter monograph uk

Khanty letters

1C89	ѻ	CYRILLIC CAPITAL LETTER TJE
1C8A	Ѽ	CYRILLIC SMALL LETTER TJE

	240	241	242	243
0	N _U _L 2400	D _L _E 2410	S _P 2420	
1	S _O _H 2401	D _C ₁ 2411	D _E _L 2421	
2	S _T _X 2402	D _C ₂ 2412	b 2422	
3	E _T _X 2403	D _C ₃ 2413	L 2423	
4	E _O _T 2404	D _C ₄ 2414	N _L 2424	
5	E _N _Q 2405	N _A _K 2415	/// 2425	
6	A _C _K 2406	S _Y _N 2416	? 2426	
7	B _E _L 2407	E _T _B 2417	 2427	
8	B _S 2408	C _A _N 2418	 2428	
9	H _T 2409	E _M 2419	 2429	
A	L _F 240A	S _U _B 241A		
B	V _T 240B	E _S _C 241B		
C	F _F 240C	F _S 241C		
D	C _R 240D	G _S 241D		
E	S _O 240E	R _S 241E		
F	S _I 240F	U _S 241F		

The diagonal lettering glyphs are only exemplary; alternate representations may be, and often are used in the visible display of control codes.

Graphic pictures for control codes

2400	N_U	SYMBOL FOR NULL
2401	S_{OH}	SYMBOL FOR START OF HEADING
2402	S_{TX}	SYMBOL FOR START OF TEXT
2403	E_{TX}	SYMBOL FOR END OF TEXT
2404	E_{OT}	SYMBOL FOR END OF TRANSMISSION
2405	E_{NQ}	SYMBOL FOR ENQUIRY
2406	A_{CK}	SYMBOL FOR ACKNOWLEDGE
2407	B_{EL}	SYMBOL FOR BELL
2408	B_S	SYMBOL FOR BACKSPACE
2409	H_T	SYMBOL FOR HORIZONTAL TABULATION
240A	L_F	SYMBOL FOR LINE FEED
240B	V_T	SYMBOL FOR VERTICAL TABULATION
240C	F_F	SYMBOL FOR FORM FEED
240D	C_R	SYMBOL FOR CARRIAGE RETURN
240E	S_O	SYMBOL FOR SHIFT OUT
240F	S_I	SYMBOL FOR SHIFT IN
2410	D_{LE}	SYMBOL FOR DATA LINK ESCAPE
2411	D_{C_1}	SYMBOL FOR DEVICE CONTROL ONE
2412	D_{C_2}	SYMBOL FOR DEVICE CONTROL TWO
2413	D_{C_3}	SYMBOL FOR DEVICE CONTROL THREE
2414	D_{C_4}	SYMBOL FOR DEVICE CONTROL FOUR
2415	N_{AK}	SYMBOL FOR NEGATIVE ACKNOWLEDGE
2416	S_{YN}	SYMBOL FOR SYNCHRONOUS IDLE
2417	E_{TB}	SYMBOL FOR END OF TRANSMISSION BLOCK
2418	C_{AN}	SYMBOL FOR CANCEL
2419	E_M	SYMBOL FOR END OF MEDIUM
241A	S_{UB}	SYMBOL FOR SUBSTITUTE
241B	E_{SC}	SYMBOL FOR ESCAPE
241C	F_S	SYMBOL FOR FILE SEPARATOR
241D	G_S	SYMBOL FOR GROUP SEPARATOR
241E	R_S	SYMBOL FOR RECORD SEPARATOR
241F	U_S	SYMBOL FOR UNIT SEPARATOR
2420	S_P	SYMBOL FOR SPACE
2421	D_{EL}	SYMBOL FOR DELETE

Specific symbols for space

2422	b	BLANK SYMBOL • graphic for space → 0180 b latin small letter b with stroke
2423	$\sqcup$	OPEN BOX • graphic for space → 2334 $\sqcup$ counterbore

Graphic picture for control code

2424	N_L	SYMBOL FOR NEWLINE
------	-------	--------------------

Keyboard symbol

2425	⧻	SYMBOL FOR DELETE FORM TWO • from ISO 9995-7 • keyboard symbol for undoable delete
------	------------	---

Specific symbol for control code

2426	؟	SYMBOL FOR SUBSTITUTE FORM TWO • from ISO 2047 → 061F ؟ arabic question mark
------	------------	---

Specific symbols for delete

2427	⧻	SYMBOL FOR DELETE SQUARE CHECKER BOARD FORM • symbol for delete in the Apple II character set • fills the bounding box of 002B $+$
2428	⧻	SYMBOL FOR DELETE RECTANGULAR CHECKER BOARD FORM • symbol for delete in the TRS-80 character set • fills the bounding box of 0048 H
2429	⧻	SYMBOL FOR DELETE MEDIUM SHADE FORM • symbol for delete in the Amstrad CPC character set, which also encodes 2592 ⧻ separately • fills the character cell → 2592 ⧻ medium shade

	A72	A73	A74	A75	A76	A77	A78	A79	A7A	A7B	A7C	A7D	A7E	A7F
0	Ƒ A720	F A730	Ƒ A740	Ƒ A750	Ƒ A760	Ƒ A770	Ƒ A780	Ƒ A790	Ƒ A7A0	Ƒ A7B0	Ƒ A7C0	Ƒ A7D0		
1	Ƒ A721	s A731	Ƒ A741	Ƒ A751	Ƒ A761	Ƒ A771	Ƒ A781	Ƒ A791	Ƒ A7A1	Ƒ A7B1	Ƒ A7C1	Ƒ A7D1		
2	Ƒ A722	AA A732	Ƒ A742	Ƒ A752	Ƒ A762	Ƒ A772	Ƒ A782	Ƒ A792	Ƒ A7A2	Ƒ A7B2	Ƒ A7C2			Ƒ A7F2
3	Ƒ A723	aa A733	Ƒ A743	Ƒ A753	Ƒ A763	Ƒ A773	Ƒ A783	Ƒ A793	Ƒ A7A3	Ƒ A7B3	Ƒ A7C3	Ƒ A7D3		Ƒ A7F3
4	Ƒ A724	AO A734	Ƒ A744	Ƒ A754	Ƒ A764	Ƒ A774	Ƒ A784	Ƒ A794	Ƒ A7A4	Ƒ A7B4	Ƒ A7C4			Ƒ A7F4
5	Ƒ A725	ao A735	Ƒ A745	Ƒ A755	Ƒ A765	Ƒ A775	Ƒ A785	Ƒ A795	Ƒ A7A5	Ƒ A7B5	Ƒ A7C5	Ƒ A7D5		Ƒ A7F5
6	Ƒ A726	AU A736	Ƒ A746	Ƒ A756	Ƒ A766	Ƒ A776	Ƒ A786	Ƒ A796	Ƒ A7A6	Ƒ A7B6	Ƒ A7C6	Ƒ A7D6		Ƒ A7F6
7	Ƒ A727	ai A737	Ƒ A747	Ƒ A757	Ƒ A767	Ƒ A777	Ƒ A787	Ƒ A797	Ƒ A7A7	Ƒ A7B7	Ƒ A7C7	Ƒ A7D7		Ƒ A7F7
8	Ƒ A728	AV A738	Ƒ A748	Ƒ A758	Ƒ A768	Ƒ A778	Ƒ A788	Ƒ A798	Ƒ A7A8	Ƒ A7B8	Ƒ A7C8	Ƒ A7D8		Ƒ A7F8
9	Ƒ A729	av A739	Ƒ A749	Ƒ A759	Ƒ A769	Ƒ A779	Ƒ A789	Ƒ A799	Ƒ A7A9	Ƒ A7B9	Ƒ A7C9	Ƒ A7D9		Ƒ A7F9
A	Ƒ A72A	AV A73A	Ƒ A74A	Ƒ A75A	Ƒ A76A	Ƒ A77A	Ƒ A78A	Ƒ A79A	Ƒ A7AA	Ƒ A7BA	Ƒ A7CA			Ƒ A7FA
B	Ƒ A72B	av A73B	Ƒ A74B	Ƒ A75B	Ƒ A76B	Ƒ A77B	Ƒ A78B	Ƒ A79B	Ƒ A7AB	Ƒ A7BB	Ƒ A7CB			Ƒ A7FB
C	Ƒ A72C	AV A73C	Ƒ A74C	Ƒ A75C	Ƒ A76C	Ƒ A77C	Ƒ A78C	Ƒ A79C	Ƒ A7AC	Ƒ A7BC	Ƒ A7CC			Ƒ A7FC
D	Ƒ A72D	av A73D	Ƒ A74D	Ƒ A75D	Ƒ A76D	Ƒ A77D	Ƒ A78D	Ƒ A79D	Ƒ A7AD	Ƒ A7BD	Ƒ A7CD			Ƒ A7FD
E	Ƒ A72E	AV A73E	Ƒ A74E	Ƒ A75E	Ƒ A76E	Ƒ A77E	Ƒ A78E	Ƒ A79E	Ƒ A7AE	Ƒ A7BE				Ƒ A7FE
F	Ƒ A72F	av A73F	Ƒ A74F	Ƒ A75F	Ƒ A76F	Ƒ A77F	Ƒ A78F	Ƒ A79F	Ƒ A7AF	Ƒ A7BF				Ƒ A7FF

Additions for UPA

A720	™	MODIFIER LETTER STRESS AND HIGH TONE
A721	™	MODIFIER LETTER STRESS AND LOW TONE

Egyptological additions

A722	Ⲁ	LATIN CAPITAL LETTER EGYPTOLOGICAL ALEF
A723	ⲁ	LATIN SMALL LETTER EGYPTOLOGICAL ALEF
A724	Ⲃ	LATIN CAPITAL LETTER EGYPTOLOGICAL AIN
A725	ⲃ	LATIN SMALL LETTER EGYPTOLOGICAL AIN
• this is a case pair		
→ 1D25 Ⲁ latin letter ain		
→ 1D5C Ⲃ modifier letter small ain		
→ A7BD ⲃ latin small letter glottal i		

Mayanist additions

A726	Ɑ	LATIN CAPITAL LETTER HENG
A727	Ɱ	LATIN SMALL LETTER HENG
A728	Ɐ	LATIN CAPITAL LETTER TZ
A729	Ɒ	LATIN SMALL LETTER TZ
A72A	ⱱ	LATIN CAPITAL LETTER TRESILLO
A72B	Ⱳ	LATIN SMALL LETTER TRESILLO
→ 218B ⱱ turned digit three		
A72C	ⱳ	LATIN CAPITAL LETTER CUATRILLO
A72D	ⱴ	LATIN SMALL LETTER CUATRILLO
A72E	Ⱶ	LATIN CAPITAL LETTER CUATRILLO WITH COMMA
A72F	ⱶ	LATIN SMALL LETTER CUATRILLO WITH COMMA

Medievalist additions

A730	ƒ	LATIN LETTER SMALL CAPITAL F
A731	ſ	LATIN LETTER SMALL CAPITAL S
A732	AA	LATIN CAPITAL LETTER AA
→ 10780 ^{aa} modifier letter small capital aa		
A733	aa	LATIN SMALL LETTER AA
A734	AO	LATIN CAPITAL LETTER AO
A735	ao	LATIN SMALL LETTER AO
A736	AJ	LATIN CAPITAL LETTER AU
A737	aj	LATIN SMALL LETTER AU
A738	AV	LATIN CAPITAL LETTER AV
A739	av	LATIN SMALL LETTER AV
A73A	AV̄	LATIN CAPITAL LETTER AV WITH HORIZONTAL BAR
A73B	av̄	LATIN SMALL LETTER AV WITH HORIZONTAL BAR
A73C	AY	LATIN CAPITAL LETTER AY
A73D	ay	LATIN SMALL LETTER AY
A73E	Ɔ	LATIN CAPITAL LETTER REVERSED C WITH DOT
A73F	ɔ̣	LATIN SMALL LETTER REVERSED C WITH DOT
A740	K̄	LATIN CAPITAL LETTER K WITH STROKE
A741	k̄	LATIN SMALL LETTER K WITH STROKE
A742	K̸	LATIN CAPITAL LETTER K WITH DIAGONAL STROKE
A743	k̸	LATIN SMALL LETTER K WITH DIAGONAL STROKE
A744	K̶	LATIN CAPITAL LETTER K WITH STROKE AND DIAGONAL STROKE
A745	k̶	LATIN SMALL LETTER K WITH STROKE AND DIAGONAL STROKE
A746	Ł	LATIN CAPITAL LETTER BROKEN L
A747	ł	LATIN SMALL LETTER BROKEN L
A748	Ḷ	LATIN CAPITAL LETTER L WITH HIGH STROKE
A749	ḷ	LATIN SMALL LETTER L WITH HIGH STROKE

A74A	⓪	LATIN CAPITAL LETTER O WITH LONG STROKE OVERLAY
A74B	⓫	LATIN SMALL LETTER O WITH LONG STROKE OVERLAY
A74C	⓬	LATIN CAPITAL LETTER O WITH LOOP
A74D	⓭	LATIN SMALL LETTER O WITH LOOP
A74E	OO	LATIN CAPITAL LETTER OO
A74F	oo	LATIN SMALL LETTER OO
A750	P̄	LATIN CAPITAL LETTER P WITH STROKE THROUGH DESCENDER
A751	p̄	LATIN SMALL LETTER P WITH STROKE THROUGH DESCENDER
A752	P̆	LATIN CAPITAL LETTER P WITH FLOURISH
A753	p̆	LATIN SMALL LETTER P WITH FLOURISH
A754	Ṗ	LATIN CAPITAL LETTER P WITH SQUIRREL TAIL
A755	ṗ	LATIN SMALL LETTER P WITH SQUIRREL TAIL
A756	Q̄	LATIN CAPITAL LETTER Q WITH STROKE THROUGH DESCENDER
A757	q̄	LATIN SMALL LETTER Q WITH STROKE THROUGH DESCENDER
A758	Q̇	LATIN CAPITAL LETTER Q WITH DIAGONAL STROKE
A759	q̇	LATIN SMALL LETTER Q WITH DIAGONAL STROKE
A75A	Ꝛ	LATIN CAPITAL LETTER R ROTUNDA
A75B	ꝛ	LATIN SMALL LETTER R ROTUNDA
A75C	Ꝝ	LATIN CAPITAL LETTER RUM ROTUNDA
A75D	ꝝ	LATIN SMALL LETTER RUM ROTUNDA
A75E	V̄	LATIN CAPITAL LETTER V WITH DIAGONAL STROKE
A75F	v̄	LATIN SMALL LETTER V WITH DIAGONAL STROKE
A760	V̇	LATIN CAPITAL LETTER VY
A761	v̇	LATIN SMALL LETTER VY
A762	ſ̅	LATIN CAPITAL LETTER VISIGOTHIC Z
A763	ſ̅	LATIN SMALL LETTER VISIGOTHIC Z
A764	Þ̄	LATIN CAPITAL LETTER THORN WITH STROKE
A765	þ̄	LATIN SMALL LETTER THORN WITH STROKE
• Old English, Old Norse		
• representative glyph is preferred in Old English text		
• Old Norse fonts show a more horizontal stroke		
A766	Þ̆	LATIN CAPITAL LETTER THORN WITH STROKE THROUGH DESCENDER
A767	þ̆	LATIN SMALL LETTER THORN WITH STROKE THROUGH DESCENDER
A768	V̆	LATIN CAPITAL LETTER VEND
A769	v̆	LATIN SMALL LETTER VEND
A76A	Ʒ	LATIN CAPITAL LETTER ET
A76B	Ʒ	LATIN SMALL LETTER ET
A76C	Ʒ̄	LATIN CAPITAL LETTER IS
A76D	Ʒ̄	LATIN SMALL LETTER IS
A76E	9	LATIN CAPITAL LETTER CON
A76F	9	LATIN SMALL LETTER CON
A770	9̣	MODIFIER LETTER US
≈ <super> A76F 9		
A771	ɖ̣	LATIN SMALL LETTER DUM
A772	ɭ̣	LATIN SMALL LETTER LUM
A773	ɱ̣	LATIN SMALL LETTER MUM
A774	ɳ̣	LATIN SMALL LETTER NUM
A775	ʀ̣	LATIN SMALL LETTER RUM
A776	ʁ̣	LATIN LETTER SMALL CAPITAL RUM
A777	ʈ̣	LATIN SMALL LETTER TUM

A778 Ȣ LATIN SMALL LETTER UM

Insular and Celtic letters

A779 Ɔ LATIN CAPITAL LETTER INSULAR D
 A77A ɔ LATIN SMALL LETTER INSULAR D
 A77B ƒ LATIN CAPITAL LETTER INSULAR F
 A77C ɣ LATIN SMALL LETTER INSULAR F
 A77D Ɔ LATIN CAPITAL LETTER INSULAR G
 • lowercase is 1D79 ɟ
 A77E Ɔ LATIN CAPITAL LETTER TURNED INSULAR G
 A77F ɣ LATIN SMALL LETTER TURNED INSULAR G
 A780 Ț LATIN CAPITAL LETTER TURNED L
 A781 Ț LATIN SMALL LETTER TURNED L
 A782 Ț LATIN CAPITAL LETTER INSULAR R
 A783 Ț LATIN SMALL LETTER INSULAR R
 A784 Ț LATIN CAPITAL LETTER INSULAR S
 A785 Ț LATIN SMALL LETTER INSULAR S
 A786 Ț LATIN CAPITAL LETTER INSULAR T
 A787 Ț LATIN SMALL LETTER INSULAR T

Modifier letters

A788 ˆ MODIFIER LETTER LOW CIRCUMFLEX ACCENT
 → 02C6 ˆ modifier letter circumflex accent
 → 2038 ˆ caret
 A789 : MODIFIER LETTER COLON
 • used as a tone letter in some orthographies
 • Budu (Congo), Sabaot (Kenya), and several Papua New Guinea languages
 → 003A : colon
 A78A = MODIFIER LETTER SHORT EQUALS SIGN
 • used as a tone letter in some orthographies
 • Budu (Congo)
 → 003D = equals sign

Orthographic letters for glottals

A78B ʔ LATIN CAPITAL LETTER SALTILLO
 • Me'phaa (Mexico)
 A78C ʔ LATIN SMALL LETTER SALTILLO
 • saltillos are used as a casing pair for glottal stop in some orthographies
 • the lowercase is widely used in many languages in Mexico and other regions, including Izere in Nigeria
 → 0027 ʔ apostrophe
 → 0242 ʔ latin small letter glottal stop
 → 0294 ʔ latin letter glottal stop
 → 02BC ʔ modifier letter apostrophe
 → 02C0 ʔ modifier letter glottal stop

Additional letter

A78D Ț LATIN CAPITAL LETTER TURNED H
 • used in the Dan/Gio orthography in Liberia
 • lowercase is 0265 Ț

Phonetic symbol

A78E ɬ LATIN SMALL LETTER L WITH RETROFLEX HOOK AND BELT
 • voiceless lateral retroflex fricative
 • used to transcribe Toda

Transliteration letter

A78F ˙ LATIN LETTER SINOLOGICAL DOT
 • used in transliteration of Phags-Pa and in phonetic transcription of Tangut
 → 00B7 ˙ middle dot

Additional letters

A790 Ț LATIN CAPITAL LETTER N WITH DESCENDER
 A791 Ț LATIN SMALL LETTER N WITH DESCENDER
 • Janalif
 A792 Ɔ LATIN CAPITAL LETTER C WITH BAR
 = Cambrian symbol
 A793 Ɔ LATIN SMALL LETTER C WITH BAR
 • Nanai

Additions for Lithuanian dialectology

A794 Ț LATIN SMALL LETTER C WITH PALATAL HOOK
 • uppercase is A7C4 Ț
 A795 Ț LATIN SMALL LETTER H WITH PALATAL HOOK
 → A727 Ț latin small letter heng

Letters for Middle Vietnamese

A796 Ț LATIN CAPITAL LETTER B WITH FLOURISH
 A797 Ț LATIN SMALL LETTER B WITH FLOURISH

Archaic letters for Ewe

A798 Ț LATIN CAPITAL LETTER F WITH STROKE
 → 0191 Ț latin capital letter f with hook
 A799 Ț LATIN SMALL LETTER F WITH STROKE
 • old Ewe orthography
 • also used in German dialectology

Archaic letters for Volapük

A79A Ț LATIN CAPITAL LETTER VOLAPUK AE
 A79B Ț LATIN SMALL LETTER VOLAPUK AE
 A79C Ț LATIN CAPITAL LETTER VOLAPUK OE
 A79D Ț LATIN SMALL LETTER VOLAPUK OE
 A79E Ț LATIN CAPITAL LETTER VOLAPUK UE
 A79F Ț LATIN SMALL LETTER VOLAPUK UE

Letters for pre-1921 Latvian orthography

A7A0 Ț LATIN CAPITAL LETTER G WITH OBLIQUE STROKE
 A7A1 Ț LATIN SMALL LETTER G WITH OBLIQUE STROKE
 A7A2 Ț LATIN CAPITAL LETTER K WITH OBLIQUE STROKE
 A7A3 Ț LATIN SMALL LETTER K WITH OBLIQUE STROKE
 A7A4 Ț LATIN CAPITAL LETTER N WITH OBLIQUE STROKE
 A7A5 Ț LATIN SMALL LETTER N WITH OBLIQUE STROKE
 A7A6 Ț LATIN CAPITAL LETTER R WITH OBLIQUE STROKE
 A7A7 Ț LATIN SMALL LETTER R WITH OBLIQUE STROKE
 A7A8 Ț LATIN CAPITAL LETTER S WITH OBLIQUE STROKE
 A7A9 Ț LATIN SMALL LETTER S WITH OBLIQUE STROKE
 • also used in pre-1950 Lower Sorbian orthography
 → 1E9C Ț latin small letter long s with diagonal stroke

Additional letters

A7AA Ț LATIN CAPITAL LETTER H WITH HOOK
 • lowercase is 0266 Ț
 • used in Chad
 A7AB Ț LATIN CAPITAL LETTER REVERSED OPEN E
 • lowercase is 025C Ț
 A7AC Ț LATIN CAPITAL LETTER SCRIPT G
 • lowercase is 0261 Ț
 A7AD Ț LATIN CAPITAL LETTER L WITH BELT
 • lowercase is 026C Ț

Letter for West African languages

- A7AE ɹ LATIN CAPITAL LETTER SMALL CAPITAL I
 • lowercase is 026A ɹ
 • also used in Unifon

Letter for Japanese phonemic transcription

- A7AF q LATIN LETTER SMALL CAPITAL Q
 • used to represent gemination
 → A7F4 q̄ modifier letter capital q

Letters for Americanist orthographies

- A7B0 x LATIN CAPITAL LETTER TURNED K
 • lowercase is 029E x̣
 A7B1 ɿ LATIN CAPITAL LETTER TURNED T
 • lowercase is 0287 ɿ
 • also used in Unifon

Letter for African languages

- A7B2 j LATIN CAPITAL LETTER J WITH CROSSED-TAIL
 • lowercase is 029D j̣

Letter for German dialectology

- A7B3 x̣ LATIN CAPITAL LETTER CHI
 • lowercase is AB53 x̣
 → 03A7 X̣ greek capital letter chi

Letters for African languages

- A7B4 β LATIN CAPITAL LETTER BETA
 A7B5 β LATIN SMALL LETTER BETA
 → 03B2 β greek small letter beta
 A7B6 ω LATIN CAPITAL LETTER OMEGA
 A7B7 ω LATIN SMALL LETTER OMEGA
 → 03C9 ω greek small letter omega

Letters for Mazahua (México)

- A7B8 ũ LATIN CAPITAL LETTER U WITH STROKE
 A7B9 u LATIN SMALL LETTER U WITH STROKE

Letters for Ugaritic and Egyptological transliteration

These letters are always shown in italic style in actual use for transliteration.

- A7BA ʾ LATIN CAPITAL LETTER GLOTTAL A
 A7BB ʾ LATIN SMALL LETTER GLOTTAL A
 A7BC ʾ LATIN CAPITAL LETTER GLOTTAL I
 A7BD ʾ LATIN SMALL LETTER GLOTTAL I
 = egyptological yod
 → A723 ʾ latin small letter egyptological alef
 → A725 ʾ latin small letter egyptological ain

- A7BE ʾU LATIN CAPITAL LETTER GLOTTAL U
 A7BF ʾu LATIN SMALL LETTER GLOTTAL U

Additional medieval letters

- A7C0 Ȯ LATIN CAPITAL LETTER OLD POLISH O
 A7C1 ȯ LATIN SMALL LETTER OLD POLISH O
 • used in Old Polish as a nasal vowel
 → 00F8 ȯ latin small letter o with stroke
 A7C2 Ƶ LATIN CAPITAL LETTER ANGLICANA W
 A7C3 ƶ LATIN SMALL LETTER ANGLICANA W
 • used in medieval English and Cornish

Letters used in early Pinyin romanization

- A7C4 Ȼ LATIN CAPITAL LETTER C WITH PALATAL HOOK
 • lowercase is A794 Ȼ
 A7C5 ȼ LATIN CAPITAL LETTER S WITH HOOK
 • lowercase is 0282 ȼ
 A7C6 Ƚ LATIN CAPITAL LETTER Z WITH PALATAL HOOK
 • lowercase is 1D8E Ƚ

Additional letters for Gaulish

- A7C7 Ɔ LATIN CAPITAL LETTER D WITH SHORT STROKE OVERLAY
 A7C8 ɖ LATIN SMALL LETTER D WITH SHORT STROKE OVERLAY
 = tau gallicum
 • indicates a dental affricate
 A7C9 Ɔ LATIN CAPITAL LETTER S WITH SHORT STROKE OVERLAY
 A7CA ɣ LATIN SMALL LETTER S WITH SHORT STROKE OVERLAY

Additional letter for Eastern Dan (Africa)

- A7CB Ɔ LATIN CAPITAL LETTER RAMS HORN
 • lowercase is 0264 Ɔ
 → 0194 Ɔ latin capital letter gamma

Letters used for Luiseño and Cupeño

- A7CC Ɔ LATIN CAPITAL LETTER S WITH DIAGONAL STROKE
 A7CD Ɔ LATIN SMALL LETTER S WITH DIAGONAL STROKE

Letters used in the Middle English Ormulum

- A7D0 Ɔ LATIN CAPITAL LETTER CLOSED INSULAR G
 A7D1 Ɔ LATIN SMALL LETTER CLOSED INSULAR G
 → 1D79 Ɔ latin small letter insular g
 A7D2 Ɔ <reserved>
 A7D3 Ɔ LATIN SMALL LETTER DOUBLE THORN
 → 00FE Ɔ latin small letter thorn
 A7D4 Ɔ <reserved>
 A7D5 Ɔ LATIN SMALL LETTER DOUBLE WYNN
 → 01BF Ɔ latin letter wyynn

Letters used in medieval palaeography

- A7D6 Ɔ LATIN CAPITAL LETTER MIDDLE SCOTS S
 A7D7 Ɔ LATIN SMALL LETTER MIDDLE SCOTS S
 • used in Middle Scots for s, ss, ser, sir, is, sis, etc.
 → 00DF Ɔ latin small letter sharp s
 A7D8 Ɔ LATIN CAPITAL LETTER SIGMOID S
 A7D9 Ɔ LATIN SMALL LETTER SIGMOID S
 • used in Middle Cornish, Middle English, and Middle Scots

Modifier letters for Chatino (México)

- A7F2 ˆ MODIFIER LETTER CAPITAL C
 ≈ <super> 0043 ˆ
 A7F3 ˆ MODIFIER LETTER CAPITAL F
 ≈ <super> 0046 ˆ

Modifier letter for Japanese phonemic transcription

- A7F4 q̄ MODIFIER LETTER CAPITAL Q
 → A7AF q̄ latin letter small capital q
 ≈ <super> 0051 Q̄

Ancient Gaulish and Celtic epigraphic letters

- A7F5 Ɔ LATIN CAPITAL LETTER REVERSED HALF H
 = H dimidié
 • appears in inscriptions from the Roman provinces of Gaul
 → 2C75 Ɔ latin capital letter half h
 A7F6 Ɔ LATIN SMALL LETTER REVERSED HALF H
 A7F7 Ɔ LATIN EPIGRAPHIC LETTER SIDEWAYS I
 • Celtic inscriptions

Additions for Extended IPA

- A7F8 ^ʰ MODIFIER LETTER CAPITAL H WITH STROKE
 ≈ <super> 0126 ^ʰ
 A typographical distinction between a capital form and a small capital form is not distinctive for this character in IPA usage.
 • faucalized
 → 029C ^h latin letter small capital h
- A7F9 ^œ MODIFIER LETTER SMALL LIGATURE OE
 • labialized: open-rounded
 ≈ <super> 0153 ^œ

Addition for UPA

- A7FA ^𐌚 LATIN LETTER SMALL CAPITAL TURNED M

Ancient Roman epigraphic letters

- A7FB ^𐌜 LATIN EPIGRAPHIC LETTER REVERSED F
 A7FC ^𐌝 LATIN EPIGRAPHIC LETTER REVERSED P
 A7FD ^𐌞 LATIN EPIGRAPHIC LETTER INVERTED M
 A7FE ^𐌟 LATIN EPIGRAPHIC LETTER I LONGA
 A7FF ^𐌠 LATIN EPIGRAPHIC LETTER ARCHAIC M

	105C	105D	105E	105F
0	𑖀 105C0	𑖁 105D0	𑖂 105E0	𑖃 105F0
1	𑖄 105C1	𑖅 105D1	𑖆 105E1	𑖇 105F1
2	𑖈 105C2	𑖉 105D2	𑖊 105E2	𑖋 105F2
3	𑖌 105C3	𑖍 105D3	𑖎 105E3	𑖏 105F3
4	𑖐 105C4	𑖑 105D4	𑖒 105E4	
5	𑖓 105C5	𑖔 105D5	𑖕 105E5	
6	𑖖 105C6	𑖗 105D6	𑖘 105E6	
7	𑖙 105C7	𑖚 105D7	𑖛 105E7	
8	𑖜 105C8	𑖝 105D8	𑖞 105E8	
9	𑖟 105C9	𑖠 105D9	𑖡 105E9	
A	𑖣 105CA	𑖤 105DA	𑖥 105EA	
B	𑖧 105CB	𑖨 105DB	𑖩 105EB	
C	𑖬 105CC	𑖭 105DC	𑖮 105EC	
D	𑖱 105CD	𑖲 105DD	𑖳 105ED	
E	𑖶 105CE	𑖷 105DE	𑖸 105EE	
F	𑖻 105CF	𑖼 105DF	𑖽 105EF	

Albanian letters

105C0	ṽ	TODHRI LETTER A
105C1	ṽ̇	TODHRI LETTER AS
105C2	ṽ̈	TODHRI LETTER BA
105C3	ḷ	TODHRI LETTER MBA
105C4	ḷ̇	TODHRI LETTER CA
105C5	ḷ̈	TODHRI LETTER CHA
105C6	ḷ̉	TODHRI LETTER DA
105C7	ḷ̊	TODHRI LETTER NDA
105C8	ḷ̋	TODHRI LETTER DHA
105C9	ḷ̌	TODHRI LETTER EI ≡ 105D2 ḷ̍ 0307 ḷ̎
105CA	ḷ̏	TODHRI LETTER E
105CB	ḷ̐	TODHRI LETTER FA
105CC	ḷ̑	TODHRI LETTER GA
105CD	ḷ̒	TODHRI LETTER NGA
105CE	ḷ̓	TODHRI LETTER GJA
105CF	ḷ̔	TODHRI LETTER NGJA
105D0	ḷ̕	TODHRI LETTER HA
105D1	ḷ̖	TODHRI LETTER HJA
105D2	ḷ̗	TODHRI LETTER I
105D3	ḷ̘	TODHRI LETTER JA
105D4	ḷ̙	TODHRI LETTER KA
105D5	ḷ̚	TODHRI LETTER LA
105D6	ḷ̛	TODHRI LETTER LLA
105D7	ḷ̜	TODHRI LETTER MA
105D8	ḷ̝	TODHRI LETTER NA
105D9	ḷ̞	TODHRI LETTER NJAN
105DA	ḷ̟	TODHRI LETTER O
105DB	ḷ̠	TODHRI LETTER PA
105DC	ḷ̡	TODHRI LETTER QA
105DD	ḷ̢	TODHRI LETTER RA
105DE	ḷ̣	TODHRI LETTER RRA
105DF	ḷ̤	TODHRI LETTER SA
105E0	ḷ̥	TODHRI LETTER SHA
105E1	ḷ̦	TODHRI LETTER SHTA • in origin a ligature of sha and ta
105E2	ļ̣	TODHRI LETTER TA
105E3	ḷ̨	TODHRI LETTER THA
105E4	ḷ̩	TODHRI LETTER U ≡ 105DA ḷ̍ 0307 ḷ̎
105E5	ḷ̪	TODHRI LETTER VA
105E6	ḷ̫	TODHRI LETTER XA
105E7	ḷ̬	TODHRI LETTER NXA
105E8	ḷ̭	TODHRI LETTER XHA
105E9	ḷ̮	TODHRI LETTER NXHA
105EA	ḷ̯	TODHRI LETTER Y
105EB	ḷ̰	TODHRI LETTER JY
105EC	ḷ̱	TODHRI LETTER ZA
105ED	ḷ̲	TODHRI LETTER ZHA

Greek letters

105EE	ḷ̳	TODHRI LETTER GHA → 03B3 γ greek small letter gamma
105EF	ḷ̴	TODHRI LETTER STA → 03DB Ϛ greek small letter stigma
105F0	ḷ̵	TODHRI LETTER SKAN → 03BE ξ greek small letter xi
105F1	ḷ̶	TODHRI LETTER KHA → 03C7 χ greek small letter chi
105F2	ḷ̷	TODHRI LETTER PSA → 03C8 ψ greek small letter psi

105F3 ḷ̸ TODHRI LETTER OO
→ 03C9 ω greek small letter omega

	10D4	10D5	10D6	10D7	10D8
0	 10D40	 10D50	 10D60	 10D70	 10D80
1	 10D41	 10D51	 10D61	 10D71	 10D81
2	 10D42	 10D52	 10D62	 10D72	 10D82
3	 10D43	 10D53	 10D63	 10D73	 10D83
4	 10D44	 10D54	 10D64	 10D74	 10D84
5	 10D45	 10D55	 10D65	 10D75	 10D85
6	 10D46	 10D56		 10D76	
7	 10D47	 10D57		 10D77	
8	 10D48	 10D58		 10D78	
9	 10D49	 10D59	 10D69	 10D79	
A	 10D4A	 10D5A	 10D6A	 10D7A	
B	 10D4B	 10D5B	 10D6B	 10D7B	
C	 10D4C	 10D5C	 10D6C	 10D7C	
D	 10D4D	 10D5D	 10D6D	 10D7D	
E	 10D4E	 10D5E	 10D6E	 10D7E	 10D8E
F	 10D4F	 10D5F	 10D6F	 10D7F	 10D8F

Digits

10D40	○	GARAY DIGIT ZERO
10D41	Ⅰ	GARAY DIGIT ONE
10D42	ℓ	GARAY DIGIT TWO
10D43	ℴ	GARAY DIGIT THREE
10D44	ℴ	GARAY DIGIT FOUR
10D45	ϡ	GARAY DIGIT FIVE
10D46	ϡ	GARAY DIGIT SIX
10D47	Ⓢ	GARAY DIGIT SEVEN
10D48	ϣ	GARAY DIGIT EIGHT
10D49	ρ	GARAY DIGIT NINE

Vowel signs

10D4A	/	GARAY VOWEL SIGN A
10D4B	\	GARAY VOWEL SIGN I
10D4C	,	GARAY VOWEL SIGN O
10D4D	ˆ	GARAY VOWEL SIGN EE
10D4E	—	GARAY VOWEL LENGTH MARK
10D4F	◌	GARAY SUKUN

Capital consonant letters

10D50	ᐃ	GARAY CAPITAL LETTER A
10D51	ᐅ	GARAY CAPITAL LETTER CA
10D52	ᐇ	GARAY CAPITAL LETTER MA
10D53	ᐉ	GARAY CAPITAL LETTER KA
10D54	ᐋ	GARAY CAPITAL LETTER BA
10D55	ᐍ	GARAY CAPITAL LETTER JA
10D56	ᐏ	GARAY CAPITAL LETTER SA
10D57	ᐑ	GARAY CAPITAL LETTER WA
10D58	ᐓ	GARAY CAPITAL LETTER LA
10D59	ᐕ	GARAY CAPITAL LETTER GA
10D5A	ᐗ	GARAY CAPITAL LETTER DA
10D5B	ᐙ	GARAY CAPITAL LETTER XA
10D5C	ᐛ	GARAY CAPITAL LETTER YA
10D5D	ᐝ	GARAY CAPITAL LETTER TA
10D5E	ᐟ	GARAY CAPITAL LETTER RA
10D5F	ᐡ	GARAY CAPITAL LETTER NYA
10D60	ᐣ	GARAY CAPITAL LETTER FA
10D61	ᐤ	GARAY CAPITAL LETTER NA
10D62	ᐦ	GARAY CAPITAL LETTER PA
10D63	ᐨ	GARAY CAPITAL LETTER HA

Obsolete capital letter shapes

10D64	ᐪ	GARAY CAPITAL LETTER OLD KA
10D65	ᐬ	GARAY CAPITAL LETTER OLD NA

Garay diacritical marks

10D69	◌̇	GARAY VOWEL SIGN E
10D6A	◌̈	GARAY CONSONANT GEMINATION MARK
10D6B	◌̇	GARAY COMBINING DOT ABOVE
10D6C	◌̈̈	GARAY COMBINING DOUBLE DOT ABOVE
10D6D	◌̃	GARAY CONSONANT NASALIZATION MARK
10D6E	—	GARAY HYPHEN
10D6F	×	GARAY REDUPLICATION MARK

Small consonant letters

10D70	ˆ	GARAY SMALL LETTER A
10D71	ˆ	GARAY SMALL LETTER CA
10D72	ˆ	GARAY SMALL LETTER MA
10D73	ˆ	GARAY SMALL LETTER KA
10D74	ˆ	GARAY SMALL LETTER BA
10D75	ˆ	GARAY SMALL LETTER JA
10D76	//	GARAY SMALL LETTER SA
10D77	ρ	GARAY SMALL LETTER WA

10D78	✓	GARAY SMALL LETTER LA
10D79	ℋ	GARAY SMALL LETTER GA
10D7A	ᐅ	GARAY SMALL LETTER DA
10D7B	ᐉ	GARAY SMALL LETTER XA
10D7C	ˆ	GARAY SMALL LETTER YA
10D7D	ᐝ	GARAY SMALL LETTER TA
10D7E	ᐟ	GARAY SMALL LETTER RA
10D7F	ᐡ	GARAY SMALL LETTER NYA
10D80	ᐣ	GARAY SMALL LETTER FA
10D81	ᐤ	GARAY SMALL LETTER NA
10D82	ᐦ	GARAY SMALL LETTER PA
10D83	ᐨ	GARAY SMALL LETTER HA

Obsolete small letter shapes

10D84	ᐪ	GARAY SMALL LETTER OLD KA
10D85	ᐬ	GARAY SMALL LETTER OLD NA

Mathematical notation

10D8E	+	GARAY PLUS SIGN
10D8F	-	GARAY MINUS SIGN

	10EC	10ED	10EE	10EF
0				
1				
2	د 10EC2			
3	ط 10EC3			
4	ك 10EC4			
5				
6				
7				
8				
9				
A				
B				
C				◌ 10EFC
D				◌ 10EFD
E				◌ 10EFE
F				◌ 10EFF

Additions for Pegon orthographies

10EC2 د ARABIC LETTER DAL WITH TWO DOTS VERTICALLY BELOW
→ 08AE د arabic letter dal with three dots below

10EC3 ط ARABIC LETTER TAH WITH TWO DOTS VERTICALLY BELOW
→ 088C ط arabic letter tah with three dots below

10EC4 ك ARABIC LETTER KAF WITH TWO DOTS VERTICALLY BELOW
→ 088D ك arabic letter keheh with two dots vertically below

Quranic mark used in Libya

10EFC ◌ ARABIC COMBINING ALEF OVERLAY
• a vowel sign equivalent to 0670 ◌, only used to annotate lam
→ 0670 ◌ arabic letter superscript alef

Quranic marks used in Turkey

10EFD ◌ ARABIC SMALL LOW WORD SAKTA
→ 08DD ◌ arabic small high word sakta

10EFE ◌ ARABIC SMALL LOW WORD QASR

10EFF ◌ ARABIC SMALL LOW WORD MADDA

	1138	1139	113A	113B	113C	113D	113E	113F
0	അ 11380	ഒ 11390	നെ 113A0	ഷ 113B0	ശ്ശ 113C0	ശ്ശ 113D0		
1	ഏ 11381	ഐ 11391	ത 113A1	സ 113B1		ശ്ശ 113D1	ശ്ശ 113E1	
2	ഗ 11382	ക 11392	ല 113A2	ഹ 113B2	ര 113C2		ര 113E2	
3	എ 11383	ഐ 11393	റ 113A3	ഉ 113B3				
4	ഈ 11384	ഗ 11394	ധ 113A4	ല 113B4		ശ്ശ 113D4		
5	ഊ 11385	ഐ 11395	ന 113A5	ല 113B5	ര 113C5	113D5		
6	ഋ 11386	ഐ 11396	വ 113A6					
7	ഋ 11387	ച 11397	വ 113A7	ട 113B7	ര 113C7	ദ 113D7		
8	ഐ 11388	ഐ 11398	ബ 113A8	റ 113B8	ര 113C8	ശ്ശ 113D8		
9	ഐ 11389	ഐ 11399	വ 113A9	റി 113B9	ൗ 113C9			
A		ച 1139A	മ 113AA	റി 113BA	ൗ 113CA			
B	ൗ 1138B	ഐ 1139B	ച 113AB	ര 113BB				
C		റ 1139C	ര 113AC	ര 113BC	ൗ 113CC			
D		ര 1139D	ല 113AD	ൗ 113BD	ൗ 113CD			
E	ര 1138E	വ 1139E	വ 113AE	ൗ 113BE	ൗ 113CE			
F		വ 1139F	ശ 113AF	ര 113BF	ൗ 113CF			

Independent vowels

11380	ಅ	TULU-TIGALARI LETTER A
11381	ಆ	TULU-TIGALARI LETTER AA
11382	ಀ	TULU-TIGALARI LETTER I
11383	ಁ	TULU-TIGALARI LETTER II ≡ 11382 ಀ 113C9 ಁ
11384	ಁ	TULU-TIGALARI LETTER U
11385	ಃ	TULU-TIGALARI LETTER UU ≡ 11384 ಁ 113BB ಃ
11386	ಋ	TULU-TIGALARI LETTER VOCALIC R
11387	ೠ	TULU-TIGALARI LETTER VOCALIC RR
11388	ಌ	TULU-TIGALARI LETTER VOCALIC L
11389	ೡ	TULU-TIGALARI LETTER VOCALIC LL
1138A	☐	<reserved>
1138B	ಋ	TULU-TIGALARI LETTER EE
1138C	☐	<reserved>
1138D	☐	<reserved>
1138E	ಋ	TULU-TIGALARI LETTER AI ≡ 1138B ಋ 113C2 ಁ
1138F	☐	<reserved>
11390	ಋ	TULU-TIGALARI LETTER OO
11391	ಋ	TULU-TIGALARI LETTER AU ≡ 11390 ಋ 113C9 ಁ

Consonants

11392	ಕ	TULU-TIGALARI LETTER KA
11393	ಖ	TULU-TIGALARI LETTER KHA
11394	ಗ	TULU-TIGALARI LETTER GA
11395	ಘ	TULU-TIGALARI LETTER GHA
11396	ಙ	TULU-TIGALARI LETTER NGA
11397	ಚ	TULU-TIGALARI LETTER CA
11398	ಛ	TULU-TIGALARI LETTER CHA
11399	ಜ	TULU-TIGALARI LETTER JA
1139A	ಝ	TULU-TIGALARI LETTER JHA
1139B	ಞ	TULU-TIGALARI LETTER NYA
1139C	ಟ	TULU-TIGALARI LETTER TTA
1139D	ಠ	TULU-TIGALARI LETTER TTHA
1139E	ಡ	TULU-TIGALARI LETTER DDA
1139F	ಢ	TULU-TIGALARI LETTER DDHA
113A0	ತ	TULU-TIGALARI LETTER NNA
113A1	ಥ	TULU-TIGALARI LETTER TA
113A2	ದ	TULU-TIGALARI LETTER THA
113A3	ನ	TULU-TIGALARI LETTER DA
113A4	ಢ	TULU-TIGALARI LETTER DHA
113A5	ಪ	TULU-TIGALARI LETTER NA
113A6	ಫ	TULU-TIGALARI LETTER PA
113A7	ಬ	TULU-TIGALARI LETTER PHA
113A8	ಮ	TULU-TIGALARI LETTER BA
113A9	ಮ	TULU-TIGALARI LETTER BHA
113AA	ಯ	TULU-TIGALARI LETTER MA
113AB	ರ	TULU-TIGALARI LETTER YA
113AC	ರ	TULU-TIGALARI LETTER RA
113AD	ಲ	TULU-TIGALARI LETTER LA
113AE	ವ	TULU-TIGALARI LETTER VA
113AF	ಶ	TULU-TIGALARI LETTER SHA
113B0	ಷ	TULU-TIGALARI LETTER SSA
113B1	ಸ	TULU-TIGALARI LETTER SA
113B2	ಹ	TULU-TIGALARI LETTER HA
113B3	ಱ	TULU-TIGALARI LETTER LLA
113B4	ಱ	TULU-TIGALARI LETTER RRA
113B5	ಱ	TULU-TIGALARI LETTER LLLA

Sign

113B7	ಃ	TULU-TIGALARI SIGN AVAGRAHA
-------	---	-----------------------------

Dependent vowel signs

113B8	ಀ	TULU-TIGALARI VOWEL SIGN AA
113B9	ಁ	TULU-TIGALARI VOWEL SIGN I
113BA	ಂ	TULU-TIGALARI VOWEL SIGN II
113BB	ಃ	TULU-TIGALARI VOWEL SIGN U
113BC	಄	TULU-TIGALARI VOWEL SIGN UU
113BD	ಋ	TULU-TIGALARI VOWEL SIGN VOCALIC R
113BE	ೠ	TULU-TIGALARI VOWEL SIGN VOCALIC RR
113BF	ಌ	TULU-TIGALARI VOWEL SIGN VOCALIC L
113C0	ೡ	TULU-TIGALARI VOWEL SIGN VOCALIC LL
113C1	☐	<reserved>
113C2	ಁ	TULU-TIGALARI VOWEL SIGN EE
113C3	☐	<reserved>
113C4	☐	<reserved>
113C5	ಋ	TULU-TIGALARI VOWEL SIGN AI ≡ 113C2 ಁ 113C2 ಁ
113C6	☐	<reserved>
113C7	ಁ	TULU-TIGALARI VOWEL SIGN OO ≡ 113C2 ಁ 113B8 ಀ
113C8	ಁ	TULU-TIGALARI VOWEL SIGN AU ≡ 113C2 ಁ 113C9 ಁ

Various signs

113C9	ಁ	TULU-TIGALARI AU LENGTH MARK
113CA	ಃ	TULU-TIGALARI SIGN CANDRA ANUNASIKA
113CB	☐	<reserved>
113CC	ಃ	TULU-TIGALARI SIGN ANUSVARA
113CD	ಃ	TULU-TIGALARI SIGN VISARGA
113CE	ಃ	TULU-TIGALARI SIGN VIRAMA
113CF	ಃ	TULU-TIGALARI SIGN LOOPED VIRAMA
113D0	ಃ	TULU-TIGALARI CONJOINER • creates conjuncts
113D1	ಃ	TULU-TIGALARI REPHA

Punctuation

113D4		TULU-TIGALARI DANDA
113D5		TULU-TIGALARI DOUBLE DANDA
113D6	☐	<reserved>
113D7	ಃ	TULU-TIGALARI SIGN OM PUSHPIKA
113D8	ಃ	TULU-TIGALARI SIGN SHRII PUSHPIKA

Vedic tones

113E1	ಃ	TULU-TIGALARI VEDIC TONE SVARITA
113E2	ಃ	TULU-TIGALARI VEDIC TONE ANUDATTA

	116D	116E	116F
0	0 116D0	ꟿ 116E0	
1	၁ 116D1	ꟻ 116E1	
2	၂ 116D2	ꟼ 116E2	
3	၃ 116D3	ꟽ 116E3	
4	၄ 116D4		
5	၅ 116D5		
6	၆ 116D6		
7	၇ 116D7		
8	၈ 116D8		
9	၉ 116D9		
A	၀ 116DA		
B	၁ 116DB		
C	၂ 116DC		
D	၃ 116DD		
E	၄ 116DE		
F	၅ 116DF		

Pa'o digits

116D0	၀	MYANMAR PAO DIGIT ZERO
116D1	၁	MYANMAR PAO DIGIT ONE
116D2	၂	MYANMAR PAO DIGIT TWO
116D3	၃	MYANMAR PAO DIGIT THREE
116D4	၄	MYANMAR PAO DIGIT FOUR
116D5	၅	MYANMAR PAO DIGIT FIVE
116D6	၆	MYANMAR PAO DIGIT SIX
116D7	၇	MYANMAR PAO DIGIT SEVEN
116D8	၈	MYANMAR PAO DIGIT EIGHT
116D9	၉	MYANMAR PAO DIGIT NINE

Eastern Pwo Karen digits

116DA	၀	MYANMAR EASTERN PWO KAREN DIGIT ZERO
116DB	၁	MYANMAR EASTERN PWO KAREN DIGIT ONE
116DC	၂	MYANMAR EASTERN PWO KAREN DIGIT TWO
116DD	၃	MYANMAR EASTERN PWO KAREN DIGIT THREE
116DE	၄	MYANMAR EASTERN PWO KAREN DIGIT FOUR
116DF	၅	MYANMAR EASTERN PWO KAREN DIGIT FIVE
116E0	ꟿ	MYANMAR EASTERN PWO KAREN DIGIT SIX
116E1	ꟻ	MYANMAR EASTERN PWO KAREN DIGIT SEVEN
116E2	ꟼ	MYANMAR EASTERN PWO KAREN DIGIT EIGHT
116E3	ꟽ	MYANMAR EASTERN PWO KAREN DIGIT NINE

	11BC	11BD	11BE	11BF
0	 11BC0	 11BD0	 11BE0	 11BF0
1	 11BC1	 11BD1	 11BE1	 11BF1
2	 11BC2	 11BD2		 11BF2
3	 11BC3	 11BD3		 11BF3
4	 11BC4	 11BD4		 11BF4
5	 11BC5	 11BD5		 11BF5
6	 11BC6	 11BD6		 11BF6
7	 11BC7	 11BD7		 11BF7
8	 11BC8	 11BD8		 11BF8
9	 11BC9	 11BD9		 11BF9
A	 11BCA	 11BDA		
B	 11BCB	 11BDB		
C	 11BCC	 11BDC		
D	 11BCD	 11BDD		
E	 11BCE	 11BDE		
F	 11BCF	 11BDF		

The script is known indigenously as 'Koinch brese'

Letters

11BC0		SUNUWAR LETTER DEVI
11BC1		SUNUWAR LETTER TASLA
11BC2		SUNUWAR LETTER EKO
11BC3		SUNUWAR LETTER IMAR
11BC4		SUNUWAR LETTER REU
11BC5		SUNUWAR LETTER UTTHI
11BC6		SUNUWAR LETTER KIK
11BC7		SUNUWAR LETTER MA
11BC8		SUNUWAR LETTER APPHO
11BC9		SUNUWAR LETTER PIP
11BCA		SUNUWAR LETTER GIL
11BCB		SUNUWAR LETTER HAMSO
11BCC		SUNUWAR LETTER CARMi
11BCD		SUNUWAR LETTER NAH
11BCE		SUNUWAR LETTER BUR
11BCF		SUNUWAR LETTER JYAH
11BD0		SUNUWAR LETTER LOACHA
11BD1		SUNUWAR LETTER OTTHI
11BD2		SUNUWAR LETTER SHYELE
11BD3		SUNUWAR LETTER VARCA
11BD4		SUNUWAR LETTER YAT
11BD5		SUNUWAR LETTER AVA
11BD6		SUNUWAR LETTER AAL
11BD7		SUNUWAR LETTER DONGA
11BD8		SUNUWAR LETTER THARI
11BD9		SUNUWAR LETTER PHAR
11BDA		SUNUWAR LETTER NGAR
11BDB		SUNUWAR LETTER KHA
11BDC		SUNUWAR LETTER SHYER
11BDD		SUNUWAR LETTER CHELAP
11BDE		SUNUWAR LETTER TENTU
11BDF		SUNUWAR LETTER THELE
11BE0		SUNUWAR LETTER KLOKO

Auspicious sign

11BE1		SUNUWAR SIGN PVO
-------	---	------------------

Digits

11BF0		SUNUWAR DIGIT ZERO
11BF1		SUNUWAR DIGIT ONE
11BF2		SUNUWAR DIGIT TWO
11BF3		SUNUWAR DIGIT THREE
11BF4		SUNUWAR DIGIT FOUR
11BF5		SUNUWAR DIGIT FIVE
11BF6		SUNUWAR DIGIT SIX
11BF7		SUNUWAR DIGIT SEVEN
11BF8		SUNUWAR DIGIT EIGHT
11BF9		SUNUWAR DIGIT NINE

	1610	1611	1612	1613
0	ཨ 16100	ཀ 16110	ཁྱ 16120	ཏ 16130
1	ཀ 16101	ཁ 16111	ཁྱ 16121	ཏ 16131
2	ཀ 16102	ཁ 16112	ཁྱ 16122	ཏ 16132
3	ཀ 16103	ཁ 16113	ཁྱ 16123	ཏ 16133
4	ཀ 16104	ཁ 16114	ཁྱ 16124	ཏ 16134
5	ཀ 16105	ཁ 16115	ཁྱ 16125	ཏ 16135
6	ཀ 16106	ཁ 16116	ཁྱ 16126	ཏ 16136
7	ཀ 16107	ཁ 16117	ཁྱ 16127	ཏ 16137
8	ཀ 16108	ཁ 16118	ཁྱ 16128	ཏ 16138
9	ཀ 16109	ཁ 16119	ཁྱ 16129	ཏ 16139
A	ཀ 1610A	ཁ 1611A	ཁྱ 1612A	
B	ཀ 1610B	ཁ 1611B	ཁྱ 1612B	
C	ཀ 1610C	ཁ 1611C	ཁྱ 1612C	
D	ཀ 1610D	ཁ 1611D	ཁྱ 1612D	
E	ཀ 1610E	ཁ 1611E	ཁྱ 1612E	
F	ཀ 1610F	ཁ 1611F	ཁྱ 1612F	

Independent Vowel

16100 ཨ GURUNG KHEMA LETTER A
• also used as a vowel carrier

Consonants

16101 ཀ GURUNG KHEMA LETTER KA
16102 ཁ GURUNG KHEMA LETTER KHA
16103 ག GURUNG KHEMA LETTER GA
16104 གྷ GURUNG KHEMA LETTER GHA
16105 ང GURUNG KHEMA LETTER NGA
16106 ཅ GURUNG KHEMA LETTER CA
16107 ཆ GURUNG KHEMA LETTER CHA
16108 ཇ GURUNG KHEMA LETTER JA
16109 ཉ GURUNG KHEMA LETTER JHA
1610A ཏ GURUNG KHEMA LETTER HA
1610B ཐ GURUNG KHEMA LETTER TTA
1610C ད GURUNG KHEMA LETTER TTHA
1610D དྷ GURUNG KHEMA LETTER DDA
1610E ན GURUNG KHEMA LETTER DDHA
1610F པ GURUNG KHEMA LETTER VA
16110 ཌ GURUNG KHEMA LETTER TA
16111 ཌྷ GURUNG KHEMA LETTER THA
16112 ཐ GURUNG KHEMA LETTER DA
16113 ཏྱ GURUNG KHEMA LETTER DHA
16114 ཎ GURUNG KHEMA LETTER NA
16115 ཏ GURUNG KHEMA LETTER PA
16116 ཏྱ GURUNG KHEMA LETTER PHA
16117 ཐ GURUNG KHEMA LETTER BA
16118 ཏྱ GURUNG KHEMA LETTER BHA
16119 ཎ GURUNG KHEMA LETTER MA
1611A ཏ GURUNG KHEMA LETTER YA
1611B ཏྱ GURUNG KHEMA LETTER RA
1611C ཏྱ GURUNG KHEMA LETTER LA
1611D ཏྱ GURUNG KHEMA LETTER SA

Dependent Vowel Signs

1611E ཏྱ GURUNG KHEMA VOWEL SIGN AA
1611F ཏྱ GURUNG KHEMA VOWEL SIGN I
16120 ཏྱ GURUNG KHEMA VOWEL SIGN II
16121 ཏྱ GURUNG KHEMA VOWEL SIGN U
≡ 1611E ཏྱ 1611E ཏྱ
16122 ཏྱ GURUNG KHEMA VOWEL SIGN UU
≡ 1611E ཏྱ 16129 ཏྱ
16123 ཏྱ GURUNG KHEMA VOWEL SIGN E
≡ 1611E ཏྱ 1611F ཏྱ
16124 ཏྱ GURUNG KHEMA VOWEL SIGN EE
≡ 16129 ཏྱ 1611F ཏྱ
16125 ཏྱ GURUNG KHEMA VOWEL SIGN AI
≡ 1611E ཏྱ 16120 ཏྱ
16126 ཏྱ GURUNG KHEMA VOWEL SIGN O
≡ 16121 ཏྱ 1611F ཏྱ
16127 ཏྱ GURUNG KHEMA VOWEL SIGN OO
≡ 16122 ཏྱ 1611F ཏྱ
16128 ཏྱ GURUNG KHEMA VOWEL SIGN AU
≡ 16121 ཏྱ 16120 ཏྱ
16129 ཏྱ GURUNG KHEMA VOWEL LENGTH MARK

Various Signs

1612A ཏྱ GURUNG KHEMA CONSONANT SIGN MEDIAL YA
1612B ཏྱ GURUNG KHEMA CONSONANT SIGN MEDIAL VA
1612C ཏྱ GURUNG KHEMA CONSONANT SIGN MEDIAL HA

1612D ཏྱ GURUNG KHEMA SIGN ANUSVARA
→ 030C ཏྱ combining caron

1612E ཏྱ GURUNG KHEMA CONSONANT SIGN MEDIAL RA
→ 032D ཏྱ combining circumflex accent below

1612F ཏྱ GURUNG KHEMA SIGN THOLHOMA
• vowel killer, always rendered visibly

Digits

16130 ཏྱ GURUNG KHEMA DIGIT ZERO
16131 ཏྱ GURUNG KHEMA DIGIT ONE
16132 ཏྱ GURUNG KHEMA DIGIT TWO
16133 ཏྱ GURUNG KHEMA DIGIT THREE
16134 ཏྱ GURUNG KHEMA DIGIT FOUR
16135 ཏྱ GURUNG KHEMA DIGIT FIVE
16136 ཏྱ GURUNG KHEMA DIGIT SIX
16137 ཏྱ GURUNG KHEMA DIGIT SEVEN
16138 ཏྱ GURUNG KHEMA DIGIT EIGHT
16139 ཏྱ GURUNG KHEMA DIGIT NINE

	16D4	16D5	16D6	16D7
0	◦ 16D40	उ 16D50	र 16D60	० 16D70
1	◌ 16D41	ऊ 16D51	ॡ 16D61	॑ 16D71
2	◌ 16D42	ॠ 16D52	ॢ 16D62	॒ 16D72
3	ॣ 16D43	। 16D53	॥ 16D63	॥ 16D73
4	० 16D44	० 16D54	ॡ 16D64	३ 16D74
5	॥ 16D45	॥ 16D55	॥ 16D65	॥ 16D75
6	॥ 16D46	॥ 16D56	॥ 16D66	॥ 16D76
7	॥ 16D47	॥ 16D57	॥ 16D67	॥ 16D77
8	॥ 16D48	॥ 16D58	॥ 16D68	॥ 16D78
9	॥ 16D49	॥ 16D59	॥ 16D69	॥ 16D79
A	॥ 16D4A	॥ 16D5A	॥ 16D6A	
B	॥ 16D4B	॥ 16D5B	॥ 16D6B	
C	॥ 16D4C	॥ 16D5C	॥ 16D6C	
D	॥ 16D4D	॥ 16D5D	॥ 16D6D	
E	॥ 16D4E	॥ 16D5E	॥ 16D6E	
F	॥ 16D4F	॥ 16D5F	॥ 16D6F	

Various signs

16D40	◌	KIRAT RAI SIGN ANUSVARA → 02DA ◌ ring above
16D41	◌	KIRAT RAI SIGN TONPI
16D42	◌	KIRAT RAI SIGN VISARGA → A789 : modifier letter colon

Letters

16D43	अ	KIRAT RAI LETTER A • also used as a vowel carrier
16D44	क	KIRAT RAI LETTER KA
16D45	ख	KIRAT RAI LETTER KHA
16D46	ग	KIRAT RAI LETTER GA
16D47	घ	KIRAT RAI LETTER GHA
16D48	ङ	KIRAT RAI LETTER NGA
16D49	च	KIRAT RAI LETTER CA
16D4A	छ	KIRAT RAI LETTER CHA
16D4B	ज	KIRAT RAI LETTER JA
16D4C	झ	KIRAT RAI LETTER JHA
16D4D	ञ	KIRAT RAI LETTER NYA
16D4E	ट	KIRAT RAI LETTER TTA
16D4F	ठ	KIRAT RAI LETTER TTHA
16D50	ड	KIRAT RAI LETTER DDA
16D51	ड्ह	KIRAT RAI LETTER DDHA
16D52	त	KIRAT RAI LETTER TA
16D53	थ	KIRAT RAI LETTER THA
16D54	द	KIRAT RAI LETTER DA
16D55	ध	KIRAT RAI LETTER DHA
16D56	न	KIRAT RAI LETTER NA
16D57	प	KIRAT RAI LETTER PA
16D58	फ	KIRAT RAI LETTER PHA
16D59	ब	KIRAT RAI LETTER BA
16D5A	भ	KIRAT RAI LETTER BHA
16D5B	म	KIRAT RAI LETTER MA
16D5C	य	KIRAT RAI LETTER YA
16D5D	र	KIRAT RAI LETTER RA
16D5E	ल	KIRAT RAI LETTER LA
16D5F	व	KIRAT RAI LETTER VA
16D60	श	KIRAT RAI LETTER SA
16D61	ष	KIRAT RAI LETTER SHA
16D62	ह	KIRAT RAI LETTER HA

Vowel signs

16D63	।	KIRAT RAI VOWEL SIGN AA → 007C vertical line → 0964 । devanagari danda
16D64	ी	KIRAT RAI VOWEL SIGN I
16D65	ु	KIRAT RAI VOWEL SIGN U
16D66	ू	KIRAT RAI VOWEL SIGN UE
16D67	ृ	KIRAT RAI VOWEL SIGN E
16D68	ॄ	KIRAT RAI VOWEL SIGN AI ≡ 16D67 ृ 16D67 ृ
16D69	ॅ	KIRAT RAI VOWEL SIGN O ≡ 16D63 । 16D67 ृ
16D6A	ॆ	KIRAT RAI VOWEL SIGN AU ≡ 16D69 ॅ 16D67 ृ

Various signs

16D6B	_	KIRAT RAI SIGN VIRAMA → 02CD _ modifier letter low macron
16D6C	↱	KIRAT RAI SIGN SAAT → 02F0 ↱ modifier letter low up arrowhead

16D6D	◌	KIRAT RAI SIGN YUPI • intended for Kirat Rai-specific abbreviations → 02F3 ◌ modifier letter low ring → 0970 ◌ devanagari abbreviation sign
-------	---	--

Punctuation

16D6E	/	KIRAT RAI DANDA = danda → 0964 । devanagari danda
16D6F	//	KIRAT RAI DOUBLE DANDA = double danda → 0965 ॥ devanagari double danda

Digits

16D70	०	KIRAT RAI DIGIT ZERO
16D71	१	KIRAT RAI DIGIT ONE
16D72	२	KIRAT RAI DIGIT TWO
16D73	३	KIRAT RAI DIGIT THREE
16D74	४	KIRAT RAI DIGIT FOUR
16D75	५	KIRAT RAI DIGIT FIVE
16D76	६	KIRAT RAI DIGIT SIX
16D77	७	KIRAT RAI DIGIT SEVEN
16D78	८	KIRAT RAI DIGIT EIGHT
16D79	९	KIRAT RAI DIGIT NINE

	1CC0	1CC1	1CC2	1CC3	1CC4	1CC5	1CC6	1CC7	1CC8	1CC9	1CCA	1CCB	1CCC	1CCD	1CCE
0	 1CC00	 1CC10	 1CC20	 1CC30	 1CC40	 1CC50	 1CC60	 1CC70	 1CC80	 1CC90	 1CCA0	 1CCB0	 1CCC0	 1CCD0	 1CCE0
1	 1CC01	 1CC11	 1CC21	 1CC31	 1CC41	 1CC51	 1CC61	 1CC71	 1CC81	 1CC91	 1CCA1	 1CCB1	 1CCC1	 1CCD1	 1CCE1
2	 1CC02	 1CC12	 1CC22	 1CC32	 1CC42	 1CC52	 1CC62	 1CC72	 1CC82	 1CC92	 1CCA2	 1CCB2	 1CCC2	 1CCD2	 1CCE2
3	 1CC03	 1CC13	 1CC23	 1CC33	 1CC43	 1CC53	 1CC63	 1CC73	 1CC83	 1CC93	 1CCA3	 1CCB3	 1CCC3	 1CCD3	 1CCE3
4	 1CC04	 1CC14	 1CC24	 1CC34	 1CC44	 1CC54	 1CC64	 1CC74	 1CC84	 1CC94	 1CCA4	 1CCB4	 1CCC4	 1CCD4	 1CCE4
5	 1CC05	 1CC15	 1CC25	 1CC35	 1CC45	 1CC55	 1CC65	 1CC75	 1CC85	 1CC95	 1CCA5	 1CCB5	 1CCC5	 1CCD5	 1CCE5
6	 1CC06	 1CC16	 1CC26	 1CC36	 1CC46	 1CC56	 1CC66	 1CC76	 1CC86	 1CC96	 1CCA6	 1CCB6	 1CCC6	 1CCD6	 1CCE6
7	 1CC07	 1CC17	 1CC27	 1CC37	 1CC47	 1CC57	 1CC67	 1CC77	 1CC87	 1CC97	 1CCA7	 1CCB7	 1CCC7	 1CCD7	 1CCE7
8	 1CC08	 1CC18	 1CC28	 1CC38	 1CC48	 1CC58	 1CC68	 1CC78	 1CC88	 1CC98	 1CCA8	 1CCB8	 1CCC8	 1CCD8	 1CCE8
9	 1CC09	 1CC19	 1CC29	 1CC39	 1CC49	 1CC59	 1CC69	 1CC79	 1CC89	 1CC99	 1CCA9	 1CCB9	 1CCC9	 1CCD9	 1CCE9
A	 1CC0A	 1CC1A	 1CC2A	 1CC3A	 1CC4A	 1CC5A	 1CC6A	 1CC7A	 1CC8A	 1CC9A	 1CCA A	 1CCB A	 1CCC A	 1CCD A	 1CCE A
B	 1CC0B	 1CC1B	 1CC2B	 1CC3B	 1CC4B	 1CC5B	 1CC6B	 1CC7B	 1CC8B	 1CC9B	 1CCA B	 1CCB B	 1CCC B	 1CCD B	 1CCE B
C	 1CC0C	 1CC1C	 1CC2C	 1CC3C	 1CC4C	 1CC5C	 1CC6C	 1CC7C	 1CC8C	 1CC9C	 1CCA C	 1CCB C	 1CCC C	 1CCD C	 1CCE C
D	 1CC0D	 1CC1D	 1CC2D	 1CC3D	 1CC4D	 1CC5D	 1CC6D	 1CC7D	 1CC8D	 1CC9D	 1CCA D	 1CCB D	 1CCC D	 1CCD D	 1CCE D
E	 1CC0E	 1CC1E	 1CC2E	 1CC3E	 1CC4E	 1CC5E	 1CC6E	 1CC7E	 1CC8E	 1CC9E	 1CCA E	 1CCB E	 1CCC E	 1CCD E	 1CCE E
F	 1CC0F	 1CC1F	 1CC2F	 1CC3F	 1CC4F	 1CC5F	 1CC6F	 1CC7F	 1CC8F	 1CC9F	 1CCA F	 1CCB F	 1CCC F	 1CCD F	 1CCE F

1CCF 1CD0 1CD1 1CD2 1CD3 1CD4 1CD5 1CD6 1CD7 1CD8 1CD9 1CDA 1CDB 1CDC 1CDD

0															
1															
2															
3															
4															
5															
6															
7															
8															
9															
A															
B															
C															
D															
E															
F															

	1CDE	1CDF	1CE0	1CE1	1CE2	1CE3	1CE4	1CE5	1CE6	1CE7	1CE8	1CE9	1CEA	1CEB
0	 1CDE0	 1CDF0	 1CE00	 1CE10	 1CE20	 1CE30	 1CE40	 1CE50	 1CE60	 1CE70	 1CE80	 1CE90	 1CEA0	 1CEB0
1	 1CDE1	 1CDF1	 1CE01	 1CE11	 1CE21	 1CE31	 1CE41	 1CE51	 1CE61	 1CE71	 1CE81	 1CE91	 1CEA1	 1CEB1
2	 1CDE2	 1CDF2	 1CE02	 1CE12	 1CE22	 1CE32	 1CE42	 1CE52	 1CE62	 1CE72	 1CE82	 1CE92	 1CEA2	 1CEB2
3	 1CDE3	 1CDF3	 1CE03	 1CE13	 1CE23	 1CE33	 1CE43	 1CE53	 1CE63	 1CE73	 1CE83	 1CE93	 1CEA3	 1CEB3
4	 1CDE4	 1CDF4	 1CE04	 1CE14	 1CE24	 1CE34	 1CE44	 1CE54	 1CE64	 1CE74	 1CE84	 1CE94	 1CEA4	 1CEB4
5	 1CDE5	 1CDF5	 1CE05	 1CE15	 1CE25	 1CE35	 1CE45	 1CE55	 1CE65	 1CE75	 1CE85	 1CE95	 1CEA5	 1CEB5
6	 1CDE6	 1CDF6	 1CE06	 1CE16	 1CE26	 1CE36	 1CE46	 1CE56	 1CE66	 1CE76	 1CE86	 1CE96	 1CEA6	 1CEB6
7	 1CDE7	 1CDF7	 1CE07	 1CE17	 1CE27	 1CE37	 1CE47	 1CE57	 1CE67	 1CE77	 1CE87	 1CE97	 1CEA7	 1CEB7
8	 1CDE8	 1CDF8	 1CE08	 1CE18	 1CE28	 1CE38	 1CE48	 1CE58	 1CE68	 1CE78	 1CE88	 1CE98	 1CEA8	 1CEB8
9	 1CDE9	 1CDF9	 1CE09	 1CE19	 1CE29	 1CE39	 1CE49	 1CE59	 1CE69	 1CE79	 1CE89	 1CE99	 1CEA9	 1CEB9
A	 1CDEA	 1CDFA	 1CE0A	 1CE1A	 1CE2A	 1CE3A	 1CE4A	 1CE5A	 1CE6A	 1CE7A	 1CE8A	 1CE9A	 1CEAA	 1CEBA
B	 1CDEB	 1CDFB	 1CE0B	 1CE1B	 1CE2B	 1CE3B	 1CE4B	 1CE5B	 1CE6B	 1CE7B	 1CE8B	 1CE9B	 1CEAB	 1CEBB
C	 1CDEC	 1CDFC	 1CE0C	 1CE1C	 1CE2C	 1CE3C	 1CE4C	 1CE5C	 1CE6C	 1CE7C	 1CE8C	 1CE9C	 1CEAC	 1CEBC
D	 1CDED	 1CDFD	 1CE0D	 1CE1D	 1CE2D	 1CE3D	 1CE4D	 1CE5D	 1CE6D	 1CE7D	 1CE8D	 1CE9D	 1CEAD	 1CEBD
E	 1CDEE	 1CDFE	 1CE0E	 1CE1E	 1CE2E	 1CE3E	 1CE4E	 1CE5E	 1CE6E	 1CE7E	 1CE8E	 1CE9E	 1CEAE	 1CEBE
F	 1CDEF	 1CDFF	 1CE0F	 1CE1F	 1CE2F	 1CE3F	 1CE4F	 1CE5F	 1CE6F	 1CE7F				

Game sprites1CC00  UP-POINTING GO-KART1CC01  RIGHT-POINTING GO-KART1CC02  LEFT-POINTING STICK FIGURE
→ 1FBC5  stick figure1CC03  RIGHT-POINTING STICK FIGURE1CC04  DOWN-POINTING STICK FIGURE**Ruler segments**1CC05  LOWER HORIZONTAL RULER SEGMENT1CC06  RIGHT VERTICAL RULER SEGMENT1CC07  LOWER RIGHT RULER SEGMENT**Schematic symbols***Designed to be used with light box drawing characters.*1CC08  ANTENNA1CC09  HORIZONTAL RESISTOR SEGMENT1CC0A  VERTICAL RESISTOR SEGMENT1CC0B  LEFT THIRD INDUCTOR1CC0C  MIDDLE THIRD INDUCTOR1CC0D  RIGHT THIRD INDUCTOR1CC0E  LEFT-POINTING DIODE1CC0F  RIGHT-POINTING DIODE1CC10  NPN TRANSISTOR1CC11  PNP TRANSISTOR1CC12  RECEPTACLE1CC13  HORIZONTAL CAPACITOR1CC14  VERTICAL CAPACITOR1CC15  LOGIC GATE OR1CC16  LOGIC GATE AND1CC17  LOGIC GATE INVERTED INPUTS1CC18  LOGIC GATE INVERTED OUTPUT1CC19  LOGIC GATE BUFFER1CC1A  LOGIC GATE BUFFER WITH INVERTED INPUT**Box drawing characters**1CC1B  BOX DRAWINGS LIGHT HORIZONTAL AND UPPER RIGHT1CC1C  BOX DRAWINGS LIGHT HORIZONTAL AND LOWER RIGHT1CC1D  BOX DRAWINGS LIGHT TOP AND UPPER LEFT1CC1E  BOX DRAWINGS LIGHT BOTTOM AND LOWER LEFT1CC1F  BOX DRAWINGS DOUBLE DIAGONAL UPPER RIGHT TO LOWER LEFT1CC20  BOX DRAWINGS DOUBLE DIAGONAL UPPER LEFT TO LOWER RIGHT**Separated mosaic terminal graphic characters***The term "quadrant" refers to block mosaics divided into four parts.*1CC21  SEPARATED BLOCK QUADRANT-1
→ 2598  quadrant upper left1CC22  SEPARATED BLOCK QUADRANT-2
→ 259D  quadrant upper right1CC23  SEPARATED BLOCK QUADRANT-12
→ 2580  upper half block1CC24  SEPARATED BLOCK QUADRANT-3
→ 2596  quadrant lower left1CC25  SEPARATED BLOCK QUADRANT-13
→ 258C  left half block1CC26  SEPARATED BLOCK QUADRANT-23
→ 259E  quadrant upper right and lower left1CC27  SEPARATED BLOCK QUADRANT-123→ 259B  quadrant upper left and upper right and lower left1CC28  SEPARATED BLOCK QUADRANT-4
→ 2597  quadrant lower right1CC29  SEPARATED BLOCK QUADRANT-14
→ 259A  quadrant upper left and lower right1CC2A  SEPARATED BLOCK QUADRANT-24
→ 2590  right half block1CC2B  SEPARATED BLOCK QUADRANT-124
→ 259C  quadrant upper left and upper right and lower right1CC2C  SEPARATED BLOCK QUADRANT-34
→ 2584  lower half block1CC2D  SEPARATED BLOCK QUADRANT-134
→ 2599  quadrant upper left and lower left and lower right1CC2E  SEPARATED BLOCK QUADRANT-234
→ 259F  quadrant upper right and lower left and lower right1CC2F  SEPARATED BLOCK QUADRANT-1234
→ 2588  full block**Circle segments**1CC30  UPPER LEFT TWELFTH CIRCLE1CC31  UPPER CENTRE LEFT TWELFTH CIRCLE1CC32  UPPER CENTRE RIGHT TWELFTH CIRCLE1CC33  UPPER RIGHT TWELFTH CIRCLE1CC34  UPPER MIDDLE LEFT TWELFTH CIRCLE1CC35  UPPER LEFT QUARTER CIRCLE1CC36  UPPER RIGHT QUARTER CIRCLE1CC37  UPPER MIDDLE RIGHT TWELFTH CIRCLE1CC38  LOWER MIDDLE LEFT TWELFTH CIRCLE1CC39  LOWER LEFT QUARTER CIRCLE1CC3A  LOWER RIGHT QUARTER CIRCLE1CC3B  LOWER MIDDLE RIGHT TWELFTH CIRCLE1CC3C  LOWER LEFT TWELFTH CIRCLE1CC3D  LOWER CENTRE LEFT TWELFTH CIRCLE1CC3E  LOWER CENTRE RIGHT TWELFTH CIRCLE1CC3F  LOWER RIGHT TWELFTH CIRCLE**Fill characters**1CC40  SPARSE HORIZONTAL FILL→ 25A4  square with horizontal fill1CC41  SPARSE VERTICAL FILL→ 25A5  square with vertical fill1CC42  ORTHOGONAL CROSSHATCH FILL→ 25A6  square with orthogonal crosshatch fill1CC43  DIAGONAL CROSSHATCH FILL→ 25A9  square with diagonal crosshatch fill1CC44  DENSE VERTICAL FILL1CC45  DENSE HORIZONTAL FILL1CC46  SPECKLE FILL FRAME-11CC47  SPECKLE FILL FRAME-2

• The term "frame" used here refers to frames of an animation

Game sprites1CC48  LEFT-FACING BASSINET1CC49  RIGHT-FACING BASSINET1CC4A  FLYING SAUCER WITH BEAMS

1CC4B		FLYING SAUCER WITHOUT BEAMS • The Sharp MZ-700 character set includes three flying saucer symbols, mapped to 1CC4A  , 1CC4B  , and 1F6F8  . → 1F6F8  flying saucer
1CC4C		ALIEN MONSTER OPEN JAWS
1CC4D		ALIEN MONSTER CLOSED JAWS
1CC4E		ALIEN SQUID OPEN TENTACLES
1CC4F		ALIEN SQUID CLOSED TENTACLES
1CC50		ALIEN CRAB STEPPING RIGHT
1CC51		ALIEN CRAB STEPPING LEFT
1CC52		ALIEN SPIDER CROUCHING
1CC53		ALIEN SPIDER SPREAD
1CC54		ALIEN MONSTER STEP-1
1CC55		ALIEN MONSTER STEP-2
1CC56		LEFT-POINTING ROCKET SHIP → 1F66C  leftwards rocket
1CC57		UP-POINTING ROCKET SHIP → 1F66D  upwards rocket
1CC58		RIGHT-POINTING ROCKET SHIP → 1F66E  rightwards rocket
1CC59		DOWN-POINTING ROCKET SHIP → 1F66F  downwards rocket → 1F680  rocket
1CC5A		TOP HALF LEFT-FACING ROBOT
1CC5B		TOP HALF FORWARD-FACING ROBOT
1CC5C		TOP HALF RIGHT-FACING ROBOT
1CC5D		BOTTOM HALF LEFT-FACING ROBOT
1CC5E		BOTTOM HALF FORWARD-FACING ROBOT
1CC5F		BOTTOM HALF RIGHT-FACING ROBOT
1CC60		LEFT-POINTING ATOMIC BOMB
1CC61		UP-POINTING ATOMIC BOMB
1CC62		RIGHT-POINTING ATOMIC BOMB
1CC63		DOWN-POINTING ATOMIC BOMB
1CC64		MUSHROOM CLOUD
1CC65		LEFT-POINTING RIFLE → 1F946  rifle
1CC66		UP-POINTING RIFLE
1CC67		RIGHT-POINTING RIFLE
1CC68		DOWN-POINTING RIFLE
1CC69		EIGHT RAYS INWARD
1CC6A		EIGHT RAYS OUTWARD
1CC6B		BLACK LARGE CIRCLE MINUS LEFT QUARTER SECTION
1CC6C		BLACK LARGE CIRCLE MINUS UPPER QUARTER SECTION
1CC6D		BLACK LARGE CIRCLE MINUS RIGHT QUARTER SECTION
1CC6E		BLACK LARGE CIRCLE MINUS LOWER QUARTER SECTION

Emoticon

1CC6F		BLACK NEUTRAL FACE → 1F610  neutral face
-------	---	--

Game sprites

1CC70		LEFT-FACING SNAKE HEAD WITH OPEN MOUTH
1CC71		UP-FACING SNAKE HEAD WITH OPEN MOUTH
1CC72		RIGHT-FACING SNAKE HEAD WITH OPEN MOUTH
1CC73		DOWN-FACING SNAKE HEAD WITH OPEN MOUTH

1CC74		LEFT-FACING SNAKE HEAD WITH CLOSED MOUTH
1CC75		UP-FACING SNAKE HEAD WITH CLOSED MOUTH
1CC76		RIGHT-FACING SNAKE HEAD WITH CLOSED MOUTH
1CC77		DOWN-FACING SNAKE HEAD WITH CLOSED MOUTH
1CC78		LEFT-POINTING ENERGY WAVE
1CC79		UP-POINTING ENERGY WAVE
1CC7A		RIGHT-POINTING ENERGY WAVE
1CC7B		DOWN-POINTING ENERGY WAVE
1CC7C		SQUARE SPIRAL FROM TOP LEFT
1CC7D		SQUARE SPIRAL FROM TOP RIGHT
1CC7E		SQUARE SPIRAL FROM BOTTOM RIGHT
1CC7F		SQUARE SPIRAL FROM BOTTOM LEFT
1CC80		STRIPED LEFT-POINTING TRIANGLE → 25C0  black left-pointing triangle
1CC81		STRIPED UP-POINTING TRIANGLE → 25B2  black up-pointing triangle
1CC82		STRIPED RIGHT-POINTING TRIANGLE → 25B6  black right-pointing triangle
1CC83		STRIPED DOWN-POINTING TRIANGLE → 25BC  black down-pointing triangle
1CC84		VERTICAL LADDER → 1FA9C  ladder
1CC85		HORIZONTAL LADDER

Terminal graphic characters

1CC86		WHITE LOWER LEFT POINTER → 25BB  white right-pointing pointer → 25FA  lower left triangle
1CC87		WHITE LOWER RIGHT POINTER → 25C5  white left-pointing pointer → 25FF  lower right triangle
1CC88		TWO RINGS ALIGNED HORIZONTALLY
1CC89		SQUARE FOUR CORNER SALTIRES
1CC8A		SQUARE FOUR CORNER DIAGONALS
1CC8B		SQUARE FOUR CORNER BLACK TRIANGLES
1CC8C		SQUARE APERTURE
1CC8D		INVERSE BLACK DIAMOND → 25C6  black diamond → 1FBBF  negative diagonal diamond
1CC8E		LEFT AND UPPER ONE EIGHTH BLOCK CONTAINING BLACK SMALL SQUARE → 1FB7D  left and upper one eighth block
1CC8F		INVERSE BLACK SMALL SQUARE → 25AA  black small square

Lines with tick marks

1CC90		VERTICAL LINE WITH FOUR TICK MARKS
1CC91		HORIZONTAL LINE WITH FOUR TICK MARKS

Game sprites

1CC92		LEFT-FACING FISH → 1F41F  fish
1CC93		RIGHT-FACING FISH
1CC94		LEFT-FACING FISH WITH OPEN MOUTH
1CC95		RIGHT-FACING FISH WITH OPEN MOUTH
1CC96		FLAPPING BIRD → 1F426  bird
1CC97		LEFT-POINTING RACING CAR
1CC98		UP-POINTING RACING CAR
1CC99		RIGHT-POINTING RACING CAR

1CC9A		DOWN-POINTING RACING CAR
1CC9B		HORIZONTAL RACING CAR
1CC9C		VERTICAL RACING CAR
1CC9D		VERTICAL GO-KART
1CC9E		LEFT-POINTING TANK
1CC9F		RIGHT-POINTING TANK
1CCA0		LEFT-POINTING ROCKET BOOSTER
1CCA1		RIGHT-POINTING ROCKET BOOSTER
1CCA2		LEFT-POINTING ROLLER COASTER CAR → 1F3A2 roller coaster
1CCA3		RIGHT-POINTING ROLLER COASTER CAR
1CCA4		LEFT HALF FLYING SAUCER → 1F6F8 flying saucer
1CCA5		RIGHT HALF FLYING SAUCER

Faces

1CCA6		UPPER LEFT QUADRANT FACE WITH OPEN EYES
1CCA7		UPPER RIGHT QUADRANT FACE WITH OPEN EYES
1CCA8		UPPER LEFT QUADRANT FACE WITH CLOSED EYES
1CCA9		UPPER RIGHT QUADRANT FACE WITH CLOSED EYES
1CCAA		LOWER LEFT QUADRANT SMILING FACE
1CCAB		LOWER RIGHT QUADRANT SMILING FACE
1CCAC		LOWER LEFT QUADRANT NEUTRAL FACE
1CCAD		LOWER RIGHT QUADRANT NEUTRAL FACE
1CCAE		LOWER LEFT QUADRANT FACE WITH OPEN MOUTH
1CCAF		LOWER RIGHT QUADRANT FACE WITH OPEN MOUTH
1CCB0		LOWER LEFT QUADRANT FROWNING FACE
1CCB1		LOWER RIGHT QUADRANT FROWNING FACE

Icons

1CCB2		UPPER LEFT QUADRANT TELEVISION → 1F4FA television
1CCB3		UPPER RIGHT QUADRANT TELEVISION
1CCB4		LOWER LEFT QUADRANT TELEVISION
1CCB5		LOWER RIGHT QUADRANT TELEVISION
1CCB6		UPPER LEFT QUADRANT MICROCOMPUTER
1CCB7		UPPER RIGHT QUADRANT MICROCOMPUTER
1CCB8		LOWER LEFT QUADRANT MICROCOMPUTER
1CCB9		LOWER RIGHT QUADRANT MICROCOMPUTER

Chess symbols

May appear as white or black chess pieces.

1CCBA		UPPER LEFT QUADRANT CHESS KING → 2654 white chess king → 265A black chess king
1CCBB		UPPER RIGHT QUADRANT CHESS KING
1CCBC		LOWER LEFT QUADRANT CHESS KING
1CCBD		LOWER RIGHT QUADRANT CHESS KING
1CCBE		UPPER LEFT QUADRANT CHESS QUEEN → 2655 white chess queen → 265B black chess queen
1CCBF		UPPER RIGHT QUADRANT CHESS QUEEN
1CCC0		LOWER LEFT QUADRANT CHESS QUEEN
1CCC1		LOWER RIGHT QUADRANT CHESS QUEEN
1CCC2		UPPER LEFT QUADRANT CHESS ROOK → 2656 white chess rook → 265C black chess rook
1CCC3		UPPER RIGHT QUADRANT CHESS ROOK

1CCC4		LOWER LEFT QUADRANT CHESS ROOK
1CCC5		LOWER RIGHT QUADRANT CHESS ROOK
1CCC6		UPPER LEFT QUADRANT CHESS BISHOP → 2657 white chess bishop → 265D black chess bishop
1CCC7		UPPER RIGHT QUADRANT CHESS BISHOP
1CCC8		LOWER LEFT QUADRANT CHESS BISHOP
1CCC9		LOWER RIGHT QUADRANT CHESS BISHOP
1CCCA		UPPER LEFT QUADRANT CHESS KNIGHT → 2658 white chess knight → 265E black chess knight
1CCCB		UPPER RIGHT QUADRANT CHESS KNIGHT
1CCCC		LOWER LEFT QUADRANT CHESS KNIGHT
1CCCD		LOWER RIGHT QUADRANT CHESS KNIGHT
1CCCE		UPPER LEFT QUADRANT CHESS PAWN → 2659 white chess pawn → 265F black chess pawn
1CCCF		UPPER RIGHT QUADRANT CHESS PAWN
1CCD0		LOWER LEFT QUADRANT CHESS PAWN
1CCD1		LOWER RIGHT QUADRANT CHESS PAWN

Icons

1CCD2		UPPER LEFT QUADRANT STANDING KNIGHT
1CCD3		UPPER RIGHT QUADRANT STANDING KNIGHT
1CCD4		LOWER LEFT QUADRANT STANDING KNIGHT
1CCD5		LOWER RIGHT QUADRANT STANDING KNIGHT

Outlined uppercase Latin alphabet

1CCD6	A	OUTLINED LATIN CAPITAL LETTER A
1CCD7	B	OUTLINED LATIN CAPITAL LETTER B
1CCD8	C	OUTLINED LATIN CAPITAL LETTER C
1CCD9	D	OUTLINED LATIN CAPITAL LETTER D
1CCDA	E	OUTLINED LATIN CAPITAL LETTER E
1CCDB	F	OUTLINED LATIN CAPITAL LETTER F
1CCDC	G	OUTLINED LATIN CAPITAL LETTER G
1CCDD	H	OUTLINED LATIN CAPITAL LETTER H
1CCDE	I	OUTLINED LATIN CAPITAL LETTER I
1CCDF	J	OUTLINED LATIN CAPITAL LETTER J
1CCE0	K	OUTLINED LATIN CAPITAL LETTER K
1CCE1	L	OUTLINED LATIN CAPITAL LETTER L
1CCE2	M	OUTLINED LATIN CAPITAL LETTER M
1CCE3	N	OUTLINED LATIN CAPITAL LETTER N
1CCE4	O	OUTLINED LATIN CAPITAL LETTER O
1CCE5	P	OUTLINED LATIN CAPITAL LETTER P
1CCE6	Q	OUTLINED LATIN CAPITAL LETTER Q
1CCE7	R	OUTLINED LATIN CAPITAL LETTER R
1CCE8	S	OUTLINED LATIN CAPITAL LETTER S
1CCE9	T	OUTLINED LATIN CAPITAL LETTER T
1CCEA	U	OUTLINED LATIN CAPITAL LETTER U
1CCEB	V	OUTLINED LATIN CAPITAL LETTER V
1CCEC	W	OUTLINED LATIN CAPITAL LETTER W
1CCED	X	OUTLINED LATIN CAPITAL LETTER X
1CCEE	Y	OUTLINED LATIN CAPITAL LETTER Y
1CCEF	Z	OUTLINED LATIN CAPITAL LETTER Z

Outlined ASCII digits

1CCF0	0	OUTLINED DIGIT ZERO
1CCF1	1	OUTLINED DIGIT ONE
1CCF2	2	OUTLINED DIGIT TWO
1CCF3	3	OUTLINED DIGIT THREE
1CCF4	4	OUTLINED DIGIT FOUR
1CCF5	5	OUTLINED DIGIT FIVE
1CCF6	6	OUTLINED DIGIT SIX

1CCF7 7 OUTLINED DIGIT SEVEN
 1CCF8 8 OUTLINED DIGIT EIGHT
 1CCF9 9 OUTLINED DIGIT NINE

Block mosaic terminal graphic characters

The term "octant" refers to block mosaics divided into eight parts.

1CD00  BLOCK OCTANT-3
 1CD01  BLOCK OCTANT-23
 1CD02  BLOCK OCTANT-123
 1CD03  BLOCK OCTANT-4
 1CD04  BLOCK OCTANT-14
 1CD05  BLOCK OCTANT-124
 1CD06  BLOCK OCTANT-34
 1CD07  BLOCK OCTANT-134
 1CD08  BLOCK OCTANT-234
 1CD09  BLOCK OCTANT-5
 1CD0A  BLOCK OCTANT-15
 1CD0B  BLOCK OCTANT-25
 1CD0C  BLOCK OCTANT-125
 1CD0D  BLOCK OCTANT-135
 1CD0E  BLOCK OCTANT-235
 1CD0F  BLOCK OCTANT-1235
 1CD10  BLOCK OCTANT-45
 1CD11  BLOCK OCTANT-145
 1CD12  BLOCK OCTANT-245
 1CD13  BLOCK OCTANT-1245
 1CD14  BLOCK OCTANT-345
 1CD15  BLOCK OCTANT-1345
 1CD16  BLOCK OCTANT-2345
 1CD17  BLOCK OCTANT-12345
 1CD18  BLOCK OCTANT-6
 1CD19  BLOCK OCTANT-16
 1CD1A  BLOCK OCTANT-26
 1CD1B  BLOCK OCTANT-126
 1CD1C  BLOCK OCTANT-36
 1CD1D  BLOCK OCTANT-136
 1CD1E  BLOCK OCTANT-236
 1CD1F  BLOCK OCTANT-1236
 1CD20  BLOCK OCTANT-146
 1CD21  BLOCK OCTANT-246
 1CD22  BLOCK OCTANT-1246
 1CD23  BLOCK OCTANT-346
 1CD24  BLOCK OCTANT-1346
 1CD25  BLOCK OCTANT-2346
 1CD26  BLOCK OCTANT-12346
 1CD27  BLOCK OCTANT-56
 1CD28  BLOCK OCTANT-156
 1CD29  BLOCK OCTANT-256
 1CD2A  BLOCK OCTANT-1256
 1CD2B  BLOCK OCTANT-356
 1CD2C  BLOCK OCTANT-1356
 1CD2D  BLOCK OCTANT-2356
 1CD2E  BLOCK OCTANT-12356
 1CD2F  BLOCK OCTANT-456
 1CD30  BLOCK OCTANT-1456
 1CD31  BLOCK OCTANT-2456
 1CD32  BLOCK OCTANT-12456
 1CD33  BLOCK OCTANT-3456
 1CD34  BLOCK OCTANT-13456
 1CD35  BLOCK OCTANT-23456
 1CD36  BLOCK OCTANT-17

1CD37  BLOCK OCTANT-27
 1CD38  BLOCK OCTANT-127
 1CD39  BLOCK OCTANT-37
 1CD3A  BLOCK OCTANT-137
 1CD3B  BLOCK OCTANT-237
 1CD3C  BLOCK OCTANT-1237
 1CD3D  BLOCK OCTANT-47
 1CD3E  BLOCK OCTANT-147
 1CD3F  BLOCK OCTANT-247
 1CD40  BLOCK OCTANT-1247
 1CD41  BLOCK OCTANT-347
 1CD42  BLOCK OCTANT-1347
 1CD43  BLOCK OCTANT-2347
 1CD44  BLOCK OCTANT-12347
 1CD45  BLOCK OCTANT-157
 1CD46  BLOCK OCTANT-257
 1CD47  BLOCK OCTANT-1257
 1CD48  BLOCK OCTANT-357
 1CD49  BLOCK OCTANT-12357
 1CD4A  BLOCK OCTANT-457
 1CD4B  BLOCK OCTANT-1457
 1CD4C  BLOCK OCTANT-2457
 1CD4D  BLOCK OCTANT-12457
 1CD4E  BLOCK OCTANT-3457
 1CD4F  BLOCK OCTANT-13457
 1CD50  BLOCK OCTANT-23457
 1CD51  BLOCK OCTANT-67
 1CD52  BLOCK OCTANT-167
 1CD53  BLOCK OCTANT-267
 1CD54  BLOCK OCTANT-1267
 1CD55  BLOCK OCTANT-367
 1CD56  BLOCK OCTANT-1367
 1CD57  BLOCK OCTANT-2367
 1CD58  BLOCK OCTANT-12367
 1CD59  BLOCK OCTANT-467
 1CD5A  BLOCK OCTANT-1467
 1CD5B  BLOCK OCTANT-2467
 1CD5C  BLOCK OCTANT-12467
 1CD5D  BLOCK OCTANT-3467
 1CD5E  BLOCK OCTANT-13467
 1CD5F  BLOCK OCTANT-23467
 1CD60  BLOCK OCTANT-123467
 1CD61  BLOCK OCTANT-567
 1CD62  BLOCK OCTANT-1567
 1CD63  BLOCK OCTANT-2567
 1CD64  BLOCK OCTANT-12567
 1CD65  BLOCK OCTANT-3567
 1CD66  BLOCK OCTANT-13567
 1CD67  BLOCK OCTANT-23567
 1CD68  BLOCK OCTANT-123567
 1CD69  BLOCK OCTANT-4567
 1CD6A  BLOCK OCTANT-14567
 1CD6B  BLOCK OCTANT-24567
 1CD6C  BLOCK OCTANT-124567
 1CD6D  BLOCK OCTANT-34567
 1CD6E  BLOCK OCTANT-134567
 1CD6F  BLOCK OCTANT-234567
 1CD70  BLOCK OCTANT-1234567
 1CD71  BLOCK OCTANT-18
 1CD72  BLOCK OCTANT-28
 1CD73  BLOCK OCTANT-128
 1CD74  BLOCK OCTANT-38

1CD75		BLOCK OCTANT-138	1CDB3		BLOCK OCTANT-478
1CD76		BLOCK OCTANT-238	1CDB4		BLOCK OCTANT-1478
1CD77		BLOCK OCTANT-1238	1CDB5		BLOCK OCTANT-2478
1CD78		BLOCK OCTANT-48	1CDB6		BLOCK OCTANT-12478
1CD79		BLOCK OCTANT-148	1CDB7		BLOCK OCTANT-3478
1CD7A		BLOCK OCTANT-248	1CDB8		BLOCK OCTANT-13478
1CD7B		BLOCK OCTANT-1248	1CDB9		BLOCK OCTANT-23478
1CD7C		BLOCK OCTANT-348	1CDBA		BLOCK OCTANT-123478
1CD7D		BLOCK OCTANT-1348	1CDBB		BLOCK OCTANT-578
1CD7E		BLOCK OCTANT-2348	1CDBC		BLOCK OCTANT-1578
1CD7F		BLOCK OCTANT-12348	1CDBD		BLOCK OCTANT-2578
1CD80		BLOCK OCTANT-58	1CDBE		BLOCK OCTANT-12578
1CD81		BLOCK OCTANT-158	1CDBF		BLOCK OCTANT-3578
1CD82		BLOCK OCTANT-258	1CDC0		BLOCK OCTANT-13578
1CD83		BLOCK OCTANT-1258	1CDC1		BLOCK OCTANT-23578
1CD84		BLOCK OCTANT-358	1CDC2		BLOCK OCTANT-123578
1CD85		BLOCK OCTANT-1358	1CDC3		BLOCK OCTANT-4578
1CD86		BLOCK OCTANT-2358	1CDC4		BLOCK OCTANT-14578
1CD87		BLOCK OCTANT-12358	1CDC5		BLOCK OCTANT-24578
1CD88		BLOCK OCTANT-458	1CDC6		BLOCK OCTANT-124578
1CD89		BLOCK OCTANT-1458	1CDC7		BLOCK OCTANT-34578
1CD8A		BLOCK OCTANT-2458	1CDC8		BLOCK OCTANT-134578
1CD8B		BLOCK OCTANT-12458	1CDC9		BLOCK OCTANT-234578
1CD8C		BLOCK OCTANT-3458	1CDCA		BLOCK OCTANT-1234578
1CD8D		BLOCK OCTANT-13458	1CDCB		BLOCK OCTANT-678
1CD8E		BLOCK OCTANT-23458	1CDCC		BLOCK OCTANT-1678
1CD8F		BLOCK OCTANT-123458	1CDCD		BLOCK OCTANT-2678
1CD90		BLOCK OCTANT-168	1CDCE		BLOCK OCTANT-12678
1CD91		BLOCK OCTANT-268	1CDCF		BLOCK OCTANT-3678
1CD92		BLOCK OCTANT-1268	1CDD0		BLOCK OCTANT-13678
1CD93		BLOCK OCTANT-368	1CDD1		BLOCK OCTANT-23678
1CD94		BLOCK OCTANT-2368	1CDD2		BLOCK OCTANT-123678
1CD95		BLOCK OCTANT-12368	1CDD3		BLOCK OCTANT-4678
1CD96		BLOCK OCTANT-468	1CDD4		BLOCK OCTANT-14678
1CD97		BLOCK OCTANT-1468	1CDD5		BLOCK OCTANT-24678
1CD98		BLOCK OCTANT-12468	1CDD6		BLOCK OCTANT-124678
1CD99		BLOCK OCTANT-3468	1CDD7		BLOCK OCTANT-34678
1CD9A		BLOCK OCTANT-13468	1CDD8		BLOCK OCTANT-134678
1CD9B		BLOCK OCTANT-23468	1CDD9		BLOCK OCTANT-234678
1CD9C		BLOCK OCTANT-568	1CDDA		BLOCK OCTANT-1234678
1CD9D		BLOCK OCTANT-1568	1CDDB		BLOCK OCTANT-15678
1CD9E		BLOCK OCTANT-2568	1CDDC		BLOCK OCTANT-25678
1CD9F		BLOCK OCTANT-12568	1CDDD		BLOCK OCTANT-125678
1CDA0		BLOCK OCTANT-3568	1CDDE		BLOCK OCTANT-35678
1CDA1		BLOCK OCTANT-13568	1CDDF		BLOCK OCTANT-235678
1CDA2		BLOCK OCTANT-23568	1CDE0		BLOCK OCTANT-1235678
1CDA3		BLOCK OCTANT-123568	1CDE1		BLOCK OCTANT-45678
1CDA4		BLOCK OCTANT-4568	1CDE2		BLOCK OCTANT-145678
1CDA5		BLOCK OCTANT-14568	1CDE3		BLOCK OCTANT-1245678
1CDA6		BLOCK OCTANT-24568	1CDE4		BLOCK OCTANT-1345678
1CDA7		BLOCK OCTANT-124568	1CDE5		BLOCK OCTANT-2345678
1CDA8		BLOCK OCTANT-34568	Game sprites		
1CDA9		BLOCK OCTANT-134568	<i>The term "frame" used here refers to frames of an animation.</i>		
1CDAA		BLOCK OCTANT-234568	1CDE6		TOP HALF STANDING PERSON
1CDAB		BLOCK OCTANT-1234568	1CDE7		BOTTOM HALF STANDING PERSON
1CDAC		BLOCK OCTANT-178	1CDE8		TOP HALF RIGHT-FACING RUNNER FRAME-1
1CDAD		BLOCK OCTANT-278	1CDE9		BOTTOM HALF RIGHT-FACING RUNNER FRAME-1
1CDAE		BLOCK OCTANT-1278	1CDEA		TOP HALF RIGHT-FACING RUNNER FRAME-2
1CDAF		BLOCK OCTANT-378	1CDEB		BOTTOM HALF RIGHT-FACING RUNNER FRAME-2
1CDB0		BLOCK OCTANT-1378			
1CDB1		BLOCK OCTANT-2378			
1CDB2		BLOCK OCTANT-12378			

1CDEC		TOP HALF LEFT-FACING RUNNER FRAME-1
1CDED		BOTTOM HALF LEFT-FACING RUNNER FRAME-1
1CDEE		TOP HALF LEFT-FACING RUNNER FRAME-2
1CDEF		BOTTOM HALF LEFT-FACING RUNNER FRAME-2
1CDF0		TOP HALF FORWARD-FACING RUNNER
1CDF1		BOTTOM HALF FORWARD-FACING RUNNER FRAME-1
1CDF2		BOTTOM HALF FORWARD-FACING RUNNER FRAME-2
1CDF3		BOTTOM HALF FORWARD-FACING RUNNER FRAME-3
1CDF4		BOTTOM HALF FORWARD-FACING RUNNER FRAME-4
1CDF5		MOON LANDER
1CDF6		TOP HALF FLAILING ROBOT FRAME-1 • bottom half is 1CDF4
1CDF7		TOP HALF FLAILING ROBOT FRAME-2
1CDF8		DOWN-POINTING AIRPLANE → 1F6E7 up-pointing airplane
1CDF9		LEFT-POINTING AIRPLANE → 2708 airplane
1CDFA		SMALL UP-POINTING AIRPLANE
1CDFB		UP-POINTING FROG • represents the frog in the Mattel Aquarius port of Frogger → 1F438 frog face
1CDFC		DOWN-POINTING FROG
1CDFD		EXPLOSION FRAME-1
1CDFE		EXPLOSION FRAME-2
1CDFF		EXPLOSION FRAME-3

Terminal graphic characters

1CE00		RIGHT HALF AND LEFT HALF WHITE CIRCLE
1CE01		LOWER HALF AND UPPER HALF WHITE CIRCLE
1CE02		EXPLOSION AT HORIZON
1CE03		UPPER HALF HEAVY WHITE SQUARE → 23B4 top square bracket
1CE04		LOWER HALF HEAVY WHITE SQUARE → 23B5 bottom square bracket
1CE05		HEAVY WHITE SQUARE CONTAINING BLACK VERY SMALL SQUARE → 2B1D • black very small square → 1F791 heavy white square → 1F794 white square containing black very small square
1CE06		WHITE VERTICAL RECTANGLE WITH HORIZONTAL BAR → 25AF white vertical rectangle
1CE07		TOP RIGHT BLACK LEFT-POINTING SMALL TRIANGLE → 25C2 • black left-pointing small triangle
1CE08		FUNNEL = filter
1CE09		BOX DRAWINGS DOUBLE DIAGONAL LOWER LEFT TO MIDDLE CENTRE TO LOWER RIGHT
1CE0A		BOX DRAWINGS DOUBLE DIAGONAL UPPER LEFT TO MIDDLE CENTRE TO UPPER RIGHT
1CE0B		LEFT HALF WHITE ELLIPSE → 2B2D white horizontal ellipse
1CE0C		RIGHT HALF WHITE ELLIPSE

Dashed lines

1CE0D	--	LEFT HALF TRIPLE DASH HORIZONTAL → 2504 box drawings light triple dash horizontal
-------	----	---

1CE0E	-	RIGHT HALF TRIPLE DASH HORIZONTAL
-------	---	-----------------------------------

Lines with tick marks

1CE0F		HORIZONTAL LINE WITH TICK MARK
1CE10		LEFT HALF HORIZONTAL LINE WITH THREE TICK MARKS
1CE11		RIGHT HALF HORIZONTAL LINE WITH THREE TICK MARKS
1CE12		HORIZONTAL LINE WITH THREE TICK MARKS
1CE13		LOWER HALF VERTICAL LINE WITH THREE TICK MARKS
1CE14		UPPER HALF VERTICAL LINE WITH THREE TICK MARKS
1CE15		VERTICAL LINE WITH THREE TICK MARKS

Box drawing characters

1CE16		BOX DRAWINGS LIGHT VERTICAL AND TOP RIGHT
1CE17		BOX DRAWINGS LIGHT VERTICAL AND BOTTOM RIGHT
1CE18		BOX DRAWINGS LIGHT VERTICAL AND TOP LEFT
1CE19		BOX DRAWINGS LIGHT VERTICAL AND BOTTOM LEFT

Large type pieces

Used to generate large text headlines on HP terminals.

1CE1A		LARGE TYPE PIECE UPPER LEFT ARC
1CE1B		LARGE TYPE PIECE UPPER LEFT CORNER
1CE1C		LARGE TYPE PIECE UPPER TERMINAL
1CE1D		LARGE TYPE PIECE UPPER LEFT CROTCH
1CE1E		LARGE TYPE PIECE LEFT ARM
1CE1F		LARGE TYPE PIECE CROSSBAR
1CE20		LARGE TYPE PIECE CROSSBAR WITH LOWER STEM
1CE21		LARGE TYPE PIECE UPPER HALF VERTEX OF M
1CE22		LARGE TYPE PIECE DIAGONAL LOWER LEFT
1CE23		LARGE TYPE PIECE SHORT UPPER TERMINAL
1CE24		LARGE TYPE PIECE UPPER RIGHT ARC
1CE25		LARGE TYPE PIECE RIGHT ARM
1CE26		LARGE TYPE PIECE UPPER RIGHT CROTCH
1CE27		LARGE TYPE PIECE UPPER RIGHT CORNER
1CE28		LARGE TYPE PIECE STEM WITH RIGHT CROSSBAR
1CE29		LARGE TYPE PIECE STEM
1CE2A		LARGE TYPE PIECE DIAGONAL UPPER RIGHT AND LOWER RIGHT
1CE2B		LARGE TYPE PIECE DIAGONAL UPPER RIGHT
1CE2C		LARGE TYPE PIECE DIAGONAL LOWER RIGHT
1CE2D		LARGE TYPE PIECE SHORT LOWER TERMINAL
1CE2E		LARGE TYPE PIECE LOWER LEFT AND UPPER LEFT ARC
1CE2F		LARGE TYPE PIECE CENTRE OF K
1CE30		LARGE TYPE PIECE LOWER HALF VERTEX OF M
1CE31		LARGE TYPE PIECE UPPER HALF VERTEX OF W
1CE32		LARGE TYPE PIECE CENTRE OF X
1CE33		LARGE TYPE PIECE CENTRE OF Y
1CE34		LARGE TYPE PIECE CENTRE OF Z WITH CROSSBAR
1CE35		LARGE TYPE PIECE RAISED UPPER RIGHT ARC
1CE36		LARGE TYPE PIECE STEM WITH LEFT CROSSBAR
1CE37		LARGE TYPE PIECE LOWER RIGHT AND UPPER RIGHT ARC
1CE38		LARGE TYPE PIECE DIAGONAL UPPER LEFT AND LOWER LEFT

1CE39		LARGE TYPE PIECE STEM WITH LEFT JOINT
1CE3A		LARGE TYPE PIECE STEM WITH CROSSBAR
1CE3B		LARGE TYPE PIECE DIAGONAL UPPER LEFT
1CE3C		LARGE TYPE PIECE LOWER TERMINAL
1CE3D		LARGE TYPE PIECE LOWER LEFT CORNER
1CE3E		LARGE TYPE PIECE LOWER LEFT ARC
1CE3F		LARGE TYPE PIECE LOWER LEFT CROTCH
1CE40		LARGE TYPE PIECE CROSSBAR WITH UPPER STEM
1CE41		LARGE TYPE PIECE VERTEX OF V
1CE42		LARGE TYPE PIECE LOWER HALF VERTEX OF W
1CE43		LARGE TYPE PIECE LOWER RIGHT ARC
1CE44		LARGE TYPE PIECE LOWER RIGHT CORNER
1CE45		LARGE TYPE PIECE LOWER RIGHT ARC WITH TAIL
1CE46		LARGE TYPE PIECE LOWER RIGHT CROTCH
1CE47		LARGE TYPE PIECE STEM-45
1CE48		LARGE TYPE PIECE STEM-2345
1CE49		LARGE TYPE PIECE STEM-4
1CE4A		LARGE TYPE PIECE STEM-34
1CE4B		LARGE TYPE PIECE STEM-234
1CE4C		LARGE TYPE PIECE STEM-1234
1CE4D		LARGE TYPE PIECE STEM-3
1CE4E		LARGE TYPE PIECE STEM-23
1CE4F		LARGE TYPE PIECE STEM-2
1CE50		LARGE TYPE PIECE STEM-12

Separated mosaic terminal graphic characters

The term "sextant" refers to block mosaics divided into six parts.

1CE51		SEPARATED BLOCK SEXTANT-1
1CE52		SEPARATED BLOCK SEXTANT-2
1CE53		SEPARATED BLOCK SEXTANT-12
1CE54		SEPARATED BLOCK SEXTANT-3
1CE55		SEPARATED BLOCK SEXTANT-13
1CE56		SEPARATED BLOCK SEXTANT-23
1CE57		SEPARATED BLOCK SEXTANT-123
1CE58		SEPARATED BLOCK SEXTANT-4
1CE59		SEPARATED BLOCK SEXTANT-14
1CE5A		SEPARATED BLOCK SEXTANT-24
1CE5B		SEPARATED BLOCK SEXTANT-124
1CE5C		SEPARATED BLOCK SEXTANT-34
1CE5D		SEPARATED BLOCK SEXTANT-134
1CE5E		SEPARATED BLOCK SEXTANT-234
1CE5F		SEPARATED BLOCK SEXTANT-1234
1CE60		SEPARATED BLOCK SEXTANT-5
1CE61		SEPARATED BLOCK SEXTANT-15
1CE62		SEPARATED BLOCK SEXTANT-25
1CE63		SEPARATED BLOCK SEXTANT-125
1CE64		SEPARATED BLOCK SEXTANT-35
1CE65		SEPARATED BLOCK SEXTANT-135
1CE66		SEPARATED BLOCK SEXTANT-235
1CE67		SEPARATED BLOCK SEXTANT-1235
1CE68		SEPARATED BLOCK SEXTANT-45
1CE69		SEPARATED BLOCK SEXTANT-145
1CE6A		SEPARATED BLOCK SEXTANT-245
1CE6B		SEPARATED BLOCK SEXTANT-1245
1CE6C		SEPARATED BLOCK SEXTANT-345
1CE6D		SEPARATED BLOCK SEXTANT-1345
1CE6E		SEPARATED BLOCK SEXTANT-2345
1CE6F		SEPARATED BLOCK SEXTANT-12345
1CE70		SEPARATED BLOCK SEXTANT-6

1CE71		SEPARATED BLOCK SEXTANT-16
1CE72		SEPARATED BLOCK SEXTANT-26
1CE73		SEPARATED BLOCK SEXTANT-126
1CE74		SEPARATED BLOCK SEXTANT-36
1CE75		SEPARATED BLOCK SEXTANT-136
1CE76		SEPARATED BLOCK SEXTANT-236
1CE77		SEPARATED BLOCK SEXTANT-1236
1CE78		SEPARATED BLOCK SEXTANT-46
1CE79		SEPARATED BLOCK SEXTANT-146
1CE7A		SEPARATED BLOCK SEXTANT-246
1CE7B		SEPARATED BLOCK SEXTANT-1246
1CE7C		SEPARATED BLOCK SEXTANT-346
1CE7D		SEPARATED BLOCK SEXTANT-1346
1CE7E		SEPARATED BLOCK SEXTANT-2346
1CE7F		SEPARATED BLOCK SEXTANT-12346
1CE80		SEPARATED BLOCK SEXTANT-56
1CE81		SEPARATED BLOCK SEXTANT-156
1CE82		SEPARATED BLOCK SEXTANT-256
1CE83		SEPARATED BLOCK SEXTANT-1256
1CE84		SEPARATED BLOCK SEXTANT-356
1CE85		SEPARATED BLOCK SEXTANT-1356
1CE86		SEPARATED BLOCK SEXTANT-2356
1CE87		SEPARATED BLOCK SEXTANT-12356
1CE88		SEPARATED BLOCK SEXTANT-456
1CE89		SEPARATED BLOCK SEXTANT-1456
1CE8A		SEPARATED BLOCK SEXTANT-2456
1CE8B		SEPARATED BLOCK SEXTANT-12456
1CE8C		SEPARATED BLOCK SEXTANT-3456
1CE8D		SEPARATED BLOCK SEXTANT-13456
1CE8E		SEPARATED BLOCK SEXTANT-23456
1CE8F		SEPARATED BLOCK SEXTANT-123456

Block elements

1CE90		UPPER LEFT ONE SIXTEENTH BLOCK
1CE91		UPPER CENTRE LEFT ONE SIXTEENTH BLOCK
1CE92		UPPER CENTRE RIGHT ONE SIXTEENTH BLOCK
1CE93		UPPER RIGHT ONE SIXTEENTH BLOCK
1CE94		UPPER MIDDLE LEFT ONE SIXTEENTH BLOCK
1CE95		UPPER MIDDLE CENTRE LEFT ONE SIXTEENTH BLOCK
1CE96		UPPER MIDDLE CENTRE RIGHT ONE SIXTEENTH BLOCK
1CE97		UPPER MIDDLE RIGHT ONE SIXTEENTH BLOCK
1CE98		LOWER MIDDLE LEFT ONE SIXTEENTH BLOCK
1CE99		LOWER MIDDLE CENTRE LEFT ONE SIXTEENTH BLOCK
1CE9A		LOWER MIDDLE CENTRE RIGHT ONE SIXTEENTH BLOCK
1CE9B		LOWER MIDDLE RIGHT ONE SIXTEENTH BLOCK
1CE9C		LOWER LEFT ONE SIXTEENTH BLOCK
1CE9D		LOWER CENTRE LEFT ONE SIXTEENTH BLOCK
1CE9E		LOWER CENTRE RIGHT ONE SIXTEENTH BLOCK
1CE9F		LOWER RIGHT ONE SIXTEENTH BLOCK
1CEA0		RIGHT HALF LOWER ONE QUARTER BLOCK
1CEA1		RIGHT THREE QUARTERS LOWER ONE QUARTER BLOCK
1CEA2		LEFT THREE QUARTERS LOWER ONE QUARTER BLOCK
1CEA3		LEFT HALF LOWER ONE QUARTER BLOCK
1CEA4		LOWER HALF LEFT ONE QUARTER BLOCK
1CEA5		LOWER THREE QUARTERS LEFT ONE QUARTER BLOCK

1CEA6	▬	UPPER THREE QUARTERS LEFT ONE QUARTER BLOCK
1CEA7	▬	UPPER HALF LEFT ONE QUARTER BLOCK
1CEA8	▬	LEFT HALF UPPER ONE QUARTER BLOCK
1CEA9	▬	LEFT THREE QUARTERS UPPER ONE QUARTER BLOCK
1CEAA	▬	RIGHT THREE QUARTERS UPPER ONE QUARTER BLOCK
1CEAB	▬	RIGHT HALF UPPER ONE QUARTER BLOCK
1CEAC	▬	UPPER HALF RIGHT ONE QUARTER BLOCK
1CEAD	▬	UPPER THREE QUARTERS RIGHT ONE QUARTER BLOCK
1CEAE	▬	LOWER THREE QUARTERS RIGHT ONE QUARTER BLOCK
1CEAF	▬	LOWER HALF RIGHT ONE QUARTER BLOCK

Smalltalk

1CEB0	⋈	HORIZONTAL ZIGZAG LINE → 299A ⋈ vertical zigzag line
1CEB1	🔑	KEYHOLE = peek → 1F5DD 🔑 old key
1CEB2	🖥	OLD PERSONAL COMPUTER WITH MONITOR IN PORTRAIT ORIENTATION → 1F5B3 🖥 old personal computer
1CEB3	▴	BLACK RIGHT TRIANGLE CARET • zero-advance character pointing between two glyphs → 2038 ▴ caret → 2333 ▴ slope → 1CC86 ▴ white lower left pointer

	1F80	1F81	1F82	1F83	1F84	1F85	1F86	1F87	1F88	1F89	1F8A	1F8B	1F8C	1F8D	1F8E	1F8F
0																
1																
2																
3																
4																
5																
6																
7																
8																
9																
A																
B																
C																
D																
E																
F																

Arrows with triangle arrowheads

- 1F800 ← LEFTWARDS ARROW WITH SMALL TRIANGLE ARROWHEAD
 1F801 ↑ UPWARDS ARROW WITH SMALL TRIANGLE ARROWHEAD
 1F802 → RIGHTWARDS ARROW WITH SMALL TRIANGLE ARROWHEAD
 1F803 ↓ DOWNWARDS ARROW WITH SMALL TRIANGLE ARROWHEAD
 1F804 ← LEFTWARDS ARROW WITH MEDIUM TRIANGLE ARROWHEAD
 1F805 ↑ UPWARDS ARROW WITH MEDIUM TRIANGLE ARROWHEAD
 1F806 → RIGHTWARDS ARROW WITH MEDIUM TRIANGLE ARROWHEAD
 1F807 ↓ DOWNWARDS ARROW WITH MEDIUM TRIANGLE ARROWHEAD
 1F808 ← LEFTWARDS ARROW WITH LARGE TRIANGLE ARROWHEAD
 1F809 ↑ UPWARDS ARROW WITH LARGE TRIANGLE ARROWHEAD
 1F80A → RIGHTWARDS ARROW WITH LARGE TRIANGLE ARROWHEAD
 1F80B ↓ DOWNWARDS ARROW WITH LARGE TRIANGLE ARROWHEAD

Arrows with equilateral triangle arrowheads

- 1F810 ← LEFTWARDS ARROW WITH SMALL EQUILATERAL ARROWHEAD
 1F811 ↑ UPWARDS ARROW WITH SMALL EQUILATERAL ARROWHEAD
 1F812 → RIGHTWARDS ARROW WITH SMALL EQUILATERAL ARROWHEAD
 1F813 ↓ DOWNWARDS ARROW WITH SMALL EQUILATERAL ARROWHEAD
 1F814 ← LEFTWARDS ARROW WITH EQUILATERAL ARROWHEAD
 1F815 ↑ UPWARDS ARROW WITH EQUILATERAL ARROWHEAD
 1F816 → RIGHTWARDS ARROW WITH EQUILATERAL ARROWHEAD
 1F817 ↓ DOWNWARDS ARROW WITH EQUILATERAL ARROWHEAD
 1F818 ← HEAVY LEFTWARDS ARROW WITH EQUILATERAL ARROWHEAD
 1F819 ↑ HEAVY UPWARDS ARROW WITH EQUILATERAL ARROWHEAD
 1F81A → HEAVY RIGHTWARDS ARROW WITH EQUILATERAL ARROWHEAD
 1F81B ↓ HEAVY DOWNWARDS ARROW WITH EQUILATERAL ARROWHEAD
 1F81C ← HEAVY LEFTWARDS ARROW WITH LARGE EQUILATERAL ARROWHEAD
 1F81D ↑ HEAVY UPWARDS ARROW WITH LARGE EQUILATERAL ARROWHEAD
 1F81E → HEAVY RIGHTWARDS ARROW WITH LARGE EQUILATERAL ARROWHEAD
 1F81F ↓ HEAVY DOWNWARDS ARROW WITH LARGE EQUILATERAL ARROWHEAD

Triangle headed arrows with different shaft weights

- 1F820 ← LEFTWARDS TRIANGLE-HEADED ARROW WITH NARROW SHAFT
 1F821 ↑ UPWARDS TRIANGLE-HEADED ARROW WITH NARROW SHAFT
 1F822 → RIGHTWARDS TRIANGLE-HEADED ARROW WITH NARROW SHAFT

- 1F823 ↓ DOWNWARDS TRIANGLE-HEADED ARROW WITH NARROW SHAFT
 1F824 ← LEFTWARDS TRIANGLE-HEADED ARROW WITH MEDIUM SHAFT
 1F825 ↑ UPWARDS TRIANGLE-HEADED ARROW WITH MEDIUM SHAFT
 1F826 → RIGHTWARDS TRIANGLE-HEADED ARROW WITH MEDIUM SHAFT
 1F827 ↓ DOWNWARDS TRIANGLE-HEADED ARROW WITH MEDIUM SHAFT
 1F828 ← LEFTWARDS TRIANGLE-HEADED ARROW WITH BOLD SHAFT
 1F829 ↑ UPWARDS TRIANGLE-HEADED ARROW WITH BOLD SHAFT
 1F82A → RIGHTWARDS TRIANGLE-HEADED ARROW WITH BOLD SHAFT
 1F82B ↓ DOWNWARDS TRIANGLE-HEADED ARROW WITH BOLD SHAFT
 1F82C ← LEFTWARDS TRIANGLE-HEADED ARROW WITH HEAVY SHAFT
 1F82D ↑ UPWARDS TRIANGLE-HEADED ARROW WITH HEAVY SHAFT
 1F82E → RIGHTWARDS TRIANGLE-HEADED ARROW WITH HEAVY SHAFT
 1F82F ↓ DOWNWARDS TRIANGLE-HEADED ARROW WITH HEAVY SHAFT
 1F830 ← LEFTWARDS TRIANGLE-HEADED ARROW WITH VERY HEAVY SHAFT
 1F831 ↑ UPWARDS TRIANGLE-HEADED ARROW WITH VERY HEAVY SHAFT
 1F832 → RIGHTWARDS TRIANGLE-HEADED ARROW WITH VERY HEAVY SHAFT
 1F833 ↓ DOWNWARDS TRIANGLE-HEADED ARROW WITH VERY HEAVY SHAFT

Finger-post arrows

- 1F834 ← LEFTWARDS FINGER-POST ARROW
 1F835 ↑ UPWARDS FINGER-POST ARROW
 1F836 → RIGHTWARDS FINGER-POST ARROW
 1F837 ↓ DOWNWARDS FINGER-POST ARROW

Squared arrows

- 1F838 ← LEFTWARDS SQUARED ARROW
 1F839 ↑ UPWARDS SQUARED ARROW
 1F83A → RIGHTWARDS SQUARED ARROW
 1F83B ↓ DOWNWARDS SQUARED ARROW

Compressed arrows

- 1F83C ← LEFTWARDS COMPRESSED ARROW
 1F83D ↑ UPWARDS COMPRESSED ARROW
 1F83E → RIGHTWARDS COMPRESSED ARROW
 1F83F ↓ DOWNWARDS COMPRESSED ARROW
 1F840 ← LEFTWARDS HEAVY COMPRESSED ARROW
 1F841 ↑ UPWARDS HEAVY COMPRESSED ARROW
 1F842 → RIGHTWARDS HEAVY COMPRESSED ARROW
 → 27A7 ↓ squat black rightwards arrow
 1F843 ↓ DOWNWARDS HEAVY COMPRESSED ARROW

Heavy arrows

- 1F844 ← LEFTWARDS HEAVY ARROW
 1F845 ↑ UPWARDS HEAVY ARROW
 1F846 → RIGHTWARDS HEAVY ARROW
 1F847 ↓ DOWNWARDS HEAVY ARROW

Sans-serif arrows

- 1F850 ← LEFTWARDS SANS-SERIF ARROW
 → 2190 ← leftwards arrow

- 1F851 ↑ UPWARDS SANS-SERIF ARROW
→ 2191 ↑ upwards arrow
- 1F852 → RIGHTWARDS SANS-SERIF ARROW
→ 2192 → rightwards arrow
- 1F853 ↓ DOWNWARDS SANS-SERIF ARROW
→ 2193 ↓ downwards arrow
- 1F854 ↖ NORTH WEST SANS-SERIF ARROW
→ 2196 ↖ north west arrow
- 1F855 ↗ NORTH EAST SANS-SERIF ARROW
→ 2197 ↗ north east arrow
- 1F856 ↘ SOUTH EAST SANS-SERIF ARROW
→ 2198 ↘ south east arrow
- 1F857 ↙ SOUTH WEST SANS-SERIF ARROW
→ 2199 ↙ south west arrow
- 1F858 ↔ LEFT RIGHT SANS-SERIF ARROW
→ 2194 ↔ left right arrow
- 1F859 ⇕ UP DOWN SANS-SERIF ARROW
→ 2195 ⇕ up down arrow

Wide-headed barb arrows

- 1F860 ← WIDE-HEADED LEFTWARDS LIGHT BARB ARROW
- 1F861 ↑ WIDE-HEADED UPWARDS LIGHT BARB ARROW
- 1F862 → WIDE-HEADED RIGHTWARDS LIGHT BARB ARROW
- 1F863 ↓ WIDE-HEADED DOWNWARDS LIGHT BARB ARROW
- 1F864 ↖ WIDE-HEADED NORTH WEST LIGHT BARB ARROW
- 1F865 ↗ WIDE-HEADED NORTH EAST LIGHT BARB ARROW
- 1F866 ↘ WIDE-HEADED SOUTH EAST LIGHT BARB ARROW
- 1F867 ↙ WIDE-HEADED SOUTH WEST LIGHT BARB ARROW
- 1F868 ← WIDE-HEADED LEFTWARDS BARB ARROW
- 1F869 ↑ WIDE-HEADED UPWARDS BARB ARROW
- 1F86A → WIDE-HEADED RIGHTWARDS BARB ARROW
- 1F86B ↓ WIDE-HEADED DOWNWARDS BARB ARROW
- 1F86C ↖ WIDE-HEADED NORTH WEST BARB ARROW
- 1F86D ↗ WIDE-HEADED NORTH EAST BARB ARROW
- 1F86E ↘ WIDE-HEADED SOUTH EAST BARB ARROW
- 1F86F ↙ WIDE-HEADED SOUTH WEST BARB ARROW
- 1F870 ← WIDE-HEADED LEFTWARDS MEDIUM BARB ARROW
- 1F871 ↑ WIDE-HEADED UPWARDS MEDIUM BARB ARROW
- 1F872 → WIDE-HEADED RIGHTWARDS MEDIUM BARB ARROW
→ 2794 → heavy wide-headed rightwards arrow
- 1F873 ↓ WIDE-HEADED DOWNWARDS MEDIUM BARB ARROW
- 1F874 ↖ WIDE-HEADED NORTH WEST MEDIUM BARB ARROW
- 1F875 ↗ WIDE-HEADED NORTH EAST MEDIUM BARB ARROW
- 1F876 ↘ WIDE-HEADED SOUTH EAST MEDIUM BARB ARROW
- 1F877 ↙ WIDE-HEADED SOUTH WEST MEDIUM BARB ARROW
- 1F878 ← WIDE-HEADED LEFTWARDS HEAVY BARB ARROW
- 1F879 ↑ WIDE-HEADED UPWARDS HEAVY BARB ARROW

- 1F87A → WIDE-HEADED RIGHTWARDS HEAVY BARB ARROW
- 1F87B ↓ WIDE-HEADED DOWNWARDS HEAVY BARB ARROW
- 1F87C ↖ WIDE-HEADED NORTH WEST HEAVY BARB ARROW
- 1F87D ↗ WIDE-HEADED NORTH EAST HEAVY BARB ARROW
- 1F87E ↘ WIDE-HEADED SOUTH EAST HEAVY BARB ARROW
- 1F87F ↙ WIDE-HEADED SOUTH WEST HEAVY BARB ARROW
- 1F880 ← WIDE-HEADED LEFTWARDS VERY HEAVY BARB ARROW
- 1F881 ↑ WIDE-HEADED UPWARDS VERY HEAVY BARB ARROW
- 1F882 → WIDE-HEADED RIGHTWARDS VERY HEAVY BARB ARROW
- 1F883 ↓ WIDE-HEADED DOWNWARDS VERY HEAVY BARB ARROW
- 1F884 ↖ WIDE-HEADED NORTH WEST VERY HEAVY BARB ARROW
- 1F885 ↗ WIDE-HEADED NORTH EAST VERY HEAVY BARB ARROW
- 1F886 ↘ WIDE-HEADED SOUTH EAST VERY HEAVY BARB ARROW
- 1F887 ↙ WIDE-HEADED SOUTH WEST VERY HEAVY BARB ARROW

Arrowheads

- 1F890 ◀ LEFTWARDS TRIANGLE ARROWHEAD
- 1F891 ▲ UPWARDS TRIANGLE ARROWHEAD
- 1F892 ▶ RIGHTWARDS TRIANGLE ARROWHEAD
- 1F893 ▼ DOWNWARDS TRIANGLE ARROWHEAD
- 1F894 ◀ LEFTWARDS WHITE ARROW WITHIN TRIANGLE ARROWHEAD
- 1F895 ▲ UPWARDS WHITE ARROW WITHIN TRIANGLE ARROWHEAD
- 1F896 ▶ RIGHTWARDS WHITE ARROW WITHIN TRIANGLE ARROWHEAD
- 1F897 ▼ DOWNWARDS WHITE ARROW WITHIN TRIANGLE ARROWHEAD

Notched arrows

- 1F898 ← LEFTWARDS ARROW WITH NOTCHED TAIL
- 1F899 ↑ UPWARDS ARROW WITH NOTCHED TAIL
- 1F89A → RIGHTWARDS ARROW WITH NOTCHED TAIL
→ 27AF ⇨ notched lower right-shadowed white rightwards arrow
- 1F89B ↓ DOWNWARDS ARROW WITH NOTCHED TAIL

Heavy arrow shafts

The vertical alignment and thickness of this set are compatible with heavy shaft arrows.

- 1F89C ▬ HEAVY ARROW SHAFT WIDTH ONE
- 1F89D ▬ HEAVY ARROW SHAFT WIDTH TWO THIRDS
- 1F89E ▬ HEAVY ARROW SHAFT WIDTH ONE HALF
- 1F89F ▬ HEAVY ARROW SHAFT WIDTH ONE THIRD

Shaded white arrows

- 1F8A0 ⇨ LEFTWARDS BOTTOM-SHADED WHITE ARROW
- 1F8A1 ⇨ RIGHTWARDS BOTTOM SHADED WHITE ARROW
- 1F8A2 ⇨ LEFTWARDS TOP SHADED WHITE ARROW
- 1F8A3 ⇨ RIGHTWARDS TOP SHADED WHITE ARROW
- 1F8A4 ⇨ LEFTWARDS LEFT-SHADED WHITE ARROW

- 1F8A5 ⇨ RIGHTWARDS RIGHT-SHADED WHITE ARROW
 → 27A9 ⇨ right-shaded white rightwards arrow
- 1F8A6 ⇩ LEFTWARDS RIGHT-SHADED WHITE ARROW
- 1F8A7 ⇨ RIGHTWARDS LEFT-SHADED WHITE ARROW
 → 27AA ⇩ left-shaded white rightwards arrow
- 1F8A8 ⇩ LEFTWARDS BACK-TILTED SHADOWED WHITE ARROW
- 1F8A9 ⇨ RIGHTWARDS BACK-TILTED SHADOWED WHITE ARROW
 → 27AB ⇩ back-tilted shadowed white rightwards arrow
- 1F8AA ⇩ LEFTWARDS FRONT-TILTED SHADOWED WHITE ARROW
- 1F8AB ⇨ RIGHTWARDS FRONT-TILTED SHADOWED WHITE ARROW
 → 27AC ⇩ front-tilted shadowed white rightwards arrow

White arrow shafts

The vertical alignment and thickness of this set are compatible with white arrows.

- 1F8AC ▢ WHITE ARROW SHAFT WIDTH ONE
- 1F8AD ▢ WHITE ARROW SHAFT WIDTH TWO THIRDS

Arrows for legacy computing

- 1F8B0 ↗ ARROW POINTING UPWARDS THEN NORTH WEST
- 1F8B1 ↘ ARROW POINTING RIGHTWARDS THEN CURVING SOUTH WEST

Smalltalk

- 1F8B2 ⇨ RIGHTWARDS ARROW WITH LOWER HOOK
 → 21AA ⇨ rightwards arrow with hook

Arrows for legacy computing

- 1F8B3 ↓ DOWNWARDS BLACK ARROW TO BAR
 → 2913 ↓ downwards arrow to bar
 → 2B07 ↓ downwards black arrow
 → 2B73 ↓ downwards triangle-headed arrow to bar
- 1F8B4 ← NEGATIVE SQUARED LEFTWARDS ARROW
 → 2190 ← leftwards arrow
- 1F8B5 ↑ NEGATIVE SQUARED UPWARDS ARROW
 → 2191 ↑ upwards arrow
- 1F8B6 → NEGATIVE SQUARED RIGHTWARDS ARROW
 → 2192 → rightwards arrow
- 1F8B7 ↓ NEGATIVE SQUARED DOWNWARDS ARROW
 → 2193 ↓ downwards arrow

Arrows with bar

These arrows complement the set in the range 21A4-21A7.

- 1F8B8 ↖ NORTH WEST ARROW FROM BAR
- 1F8B9 ↗ NORTH EAST ARROW FROM BAR
- 1F8BA ↘ SOUTH EAST ARROW FROM BAR
- 1F8BB ↙ SOUTH WEST ARROW FROM BAR

	1FB0	1FB1	1FB2	1FB3	1FB4	1FB5	1FB6	1FB7	1FB8	1FB9	1FBA	1FBB	1FBC	1FBD	1FBE	1FBF
0																
1																
2																
3																
4																
5																
6																
7																
8																
9																
A																
B																
C																
D																
E																
F																

Block mosaic terminal graphic characters

The term "sextant" refers to block mosaics divided into six parts.

1FB00		BLOCK SEXTANT-1
1FB01		BLOCK SEXTANT-2
1FB02		BLOCK SEXTANT-12
	• upper one third block	
1FB03		BLOCK SEXTANT-3
1FB04		BLOCK SEXTANT-13
1FB05		BLOCK SEXTANT-23
1FB06		BLOCK SEXTANT-123
1FB07		BLOCK SEXTANT-4
1FB08		BLOCK SEXTANT-14
1FB09		BLOCK SEXTANT-24
1FB0A		BLOCK SEXTANT-124
1FB0B		BLOCK SEXTANT-34
	• middle one third block	
1FB0C		BLOCK SEXTANT-134
1FB0D		BLOCK SEXTANT-234
1FB0E		BLOCK SEXTANT-1234
	• upper two thirds block	
1FB0F		BLOCK SEXTANT-5
1FB10		BLOCK SEXTANT-15
1FB11		BLOCK SEXTANT-25
1FB12		BLOCK SEXTANT-125
1FB13		BLOCK SEXTANT-35
1FB14		BLOCK SEXTANT-235
1FB15		BLOCK SEXTANT-1235
1FB16		BLOCK SEXTANT-45
1FB17		BLOCK SEXTANT-145
1FB18		BLOCK SEXTANT-245
1FB19		BLOCK SEXTANT-1245
1FB1A		BLOCK SEXTANT-345
1FB1B		BLOCK SEXTANT-1345
1FB1C		BLOCK SEXTANT-2345
1FB1D		BLOCK SEXTANT-12345
1FB1E		BLOCK SEXTANT-6
1FB1F		BLOCK SEXTANT-16
1FB20		BLOCK SEXTANT-26
1FB21		BLOCK SEXTANT-126
1FB22		BLOCK SEXTANT-36
1FB23		BLOCK SEXTANT-136
1FB24		BLOCK SEXTANT-236
1FB25		BLOCK SEXTANT-1236
1FB26		BLOCK SEXTANT-46
1FB27		BLOCK SEXTANT-146
1FB28		BLOCK SEXTANT-1246
1FB29		BLOCK SEXTANT-346
1FB2A		BLOCK SEXTANT-1346
1FB2B		BLOCK SEXTANT-2346
1FB2C		BLOCK SEXTANT-12346
1FB2D		BLOCK SEXTANT-56
	• lower one third block	
1FB2E		BLOCK SEXTANT-156
1FB2F		BLOCK SEXTANT-256
1FB30		BLOCK SEXTANT-1256
	• upper and lower one third block	
1FB31		BLOCK SEXTANT-356
1FB32		BLOCK SEXTANT-1356
1FB33		BLOCK SEXTANT-2356
1FB34		BLOCK SEXTANT-12356

1FB35		BLOCK SEXTANT-456
1FB36		BLOCK SEXTANT-1456
1FB37		BLOCK SEXTANT-2456
1FB38		BLOCK SEXTANT-12456
1FB39		BLOCK SEXTANT-3456
	• lower two thirds block	
1FB3A		BLOCK SEXTANT-13456
1FB3B		BLOCK SEXTANT-23456

Smooth mosaic terminal graphic characters

1FB3C		LOWER LEFT BLOCK DIAGONAL LOWER MIDDLE LEFT TO LOWER CENTRE
1FB3D		LOWER LEFT BLOCK DIAGONAL LOWER MIDDLE LEFT TO LOWER RIGHT
1FB3E		LOWER LEFT BLOCK DIAGONAL UPPER MIDDLE LEFT TO LOWER CENTRE
1FB3F		LOWER LEFT BLOCK DIAGONAL UPPER MIDDLE LEFT TO LOWER RIGHT
1FB40		LOWER LEFT BLOCK DIAGONAL UPPER LEFT TO LOWER CENTRE
1FB41		LOWER RIGHT BLOCK DIAGONAL UPPER MIDDLE LEFT TO UPPER CENTRE
1FB42		LOWER RIGHT BLOCK DIAGONAL UPPER MIDDLE LEFT TO UPPER RIGHT
1FB43		LOWER RIGHT BLOCK DIAGONAL LOWER MIDDLE LEFT TO UPPER CENTRE
1FB44		LOWER RIGHT BLOCK DIAGONAL LOWER MIDDLE LEFT TO UPPER RIGHT
1FB45		LOWER RIGHT BLOCK DIAGONAL LOWER LEFT TO UPPER CENTRE
1FB46		LOWER RIGHT BLOCK DIAGONAL LOWER MIDDLE LEFT TO UPPER MIDDLE RIGHT
1FB47		LOWER RIGHT BLOCK DIAGONAL LOWER CENTRE TO LOWER MIDDLE RIGHT
1FB48		LOWER RIGHT BLOCK DIAGONAL LOWER LEFT TO LOWER MIDDLE RIGHT
1FB49		LOWER RIGHT BLOCK DIAGONAL LOWER CENTRE TO UPPER MIDDLE RIGHT
1FB4A		LOWER RIGHT BLOCK DIAGONAL LOWER LEFT TO UPPER MIDDLE RIGHT
1FB4B		LOWER RIGHT BLOCK DIAGONAL LOWER CENTRE TO UPPER RIGHT
1FB4C		LOWER LEFT BLOCK DIAGONAL UPPER CENTRE TO UPPER MIDDLE RIGHT
1FB4D		LOWER LEFT BLOCK DIAGONAL UPPER LEFT TO UPPER MIDDLE RIGHT
1FB4E		LOWER LEFT BLOCK DIAGONAL UPPER CENTRE TO LOWER MIDDLE RIGHT
1FB4F		LOWER LEFT BLOCK DIAGONAL UPPER LEFT TO LOWER MIDDLE RIGHT
1FB50		LOWER LEFT BLOCK DIAGONAL UPPER CENTRE TO LOWER RIGHT
1FB51		LOWER LEFT BLOCK DIAGONAL UPPER MIDDLE LEFT TO LOWER MIDDLE RIGHT
1FB52		UPPER RIGHT BLOCK DIAGONAL LOWER MIDDLE LEFT TO LOWER CENTRE
1FB53		UPPER RIGHT BLOCK DIAGONAL LOWER MIDDLE LEFT TO LOWER RIGHT
1FB54		UPPER RIGHT BLOCK DIAGONAL UPPER MIDDLE LEFT TO LOWER CENTRE
1FB55		UPPER RIGHT BLOCK DIAGONAL UPPER MIDDLE LEFT TO LOWER RIGHT
1FB56		UPPER RIGHT BLOCK DIAGONAL UPPER LEFT TO LOWER CENTRE
1FB57		UPPER LEFT BLOCK DIAGONAL UPPER MIDDLE LEFT TO UPPER CENTRE

1FB58		UPPER LEFT BLOCK DIAGONAL UPPER MIDDLE LEFT TO UPPER RIGHT
1FB59		UPPER LEFT BLOCK DIAGONAL LOWER MIDDLE LEFT TO UPPER CENTRE
1FB5A		UPPER LEFT BLOCK DIAGONAL LOWER MIDDLE LEFT TO UPPER RIGHT
1FB5B		UPPER LEFT BLOCK DIAGONAL LOWER LEFT TO UPPER CENTRE
1FB5C		UPPER LEFT BLOCK DIAGONAL LOWER MIDDLE LEFT TO UPPER MIDDLE RIGHT
1FB5D		UPPER LEFT BLOCK DIAGONAL LOWER CENTRE TO LOWER MIDDLE RIGHT
1FB5E		UPPER LEFT BLOCK DIAGONAL LOWER LEFT TO LOWER MIDDLE RIGHT
1FB5F		UPPER LEFT BLOCK DIAGONAL LOWER CENTRE TO UPPER MIDDLE RIGHT
1FB60		UPPER LEFT BLOCK DIAGONAL LOWER LEFT TO UPPER MIDDLE RIGHT
1FB61		UPPER LEFT BLOCK DIAGONAL LOWER CENTRE TO UPPER RIGHT
1FB62		UPPER RIGHT BLOCK DIAGONAL UPPER CENTRE TO UPPER MIDDLE RIGHT
1FB63		UPPER RIGHT BLOCK DIAGONAL UPPER LEFT TO UPPER MIDDLE RIGHT
1FB64		UPPER RIGHT BLOCK DIAGONAL UPPER CENTRE TO LOWER MIDDLE RIGHT
1FB65		UPPER RIGHT BLOCK DIAGONAL UPPER LEFT TO LOWER MIDDLE RIGHT
1FB66		UPPER RIGHT BLOCK DIAGONAL UPPER CENTRE TO LOWER RIGHT
1FB67		UPPER RIGHT BLOCK DIAGONAL UPPER MIDDLE LEFT TO LOWER MIDDLE RIGHT
1FB68		UPPER AND RIGHT AND LOWER TRIANGULAR THREE QUARTERS BLOCK
1FB69		LEFT AND LOWER AND RIGHT TRIANGULAR THREE QUARTERS BLOCK
1FB6A		UPPER AND LEFT AND LOWER TRIANGULAR THREE QUARTERS BLOCK
1FB6B		LEFT AND UPPER AND RIGHT TRIANGULAR THREE QUARTERS BLOCK
1FB6C		LEFT TRIANGULAR ONE QUARTER BLOCK
1FB6D		UPPER TRIANGULAR ONE QUARTER BLOCK
1FB6E		RIGHT TRIANGULAR ONE QUARTER BLOCK
1FB6F		LOWER TRIANGULAR ONE QUARTER BLOCK

Block elements

1FB70		VERTICAL ONE EIGHTH BLOCK-2 → 258F left one eighth block
1FB71		VERTICAL ONE EIGHTH BLOCK-3
1FB72		VERTICAL ONE EIGHTH BLOCK-4
1FB73		VERTICAL ONE EIGHTH BLOCK-5
1FB74		VERTICAL ONE EIGHTH BLOCK-6
1FB75		VERTICAL ONE EIGHTH BLOCK-7 → 2595 right one eighth block
1FB76		HORIZONTAL ONE EIGHTH BLOCK-2 → 2594 upper one eighth block
1FB77		HORIZONTAL ONE EIGHTH BLOCK-3
1FB78		HORIZONTAL ONE EIGHTH BLOCK-4
1FB79		HORIZONTAL ONE EIGHTH BLOCK-5
1FB7A		HORIZONTAL ONE EIGHTH BLOCK-6
1FB7B		HORIZONTAL ONE EIGHTH BLOCK-7 → 2581 lower one eighth block
1FB7C		LEFT AND LOWER ONE EIGHTH BLOCK
1FB7D		LEFT AND UPPER ONE EIGHTH BLOCK
1FB7E		RIGHT AND UPPER ONE EIGHTH BLOCK

1FB7F		RIGHT AND LOWER ONE EIGHTH BLOCK
1FB80		UPPER AND LOWER ONE EIGHTH BLOCK
1FB81		HORIZONTAL ONE EIGHTH BLOCK-1358
1FB82		UPPER ONE QUARTER BLOCK → 2582 lower one quarter block
1FB83		UPPER THREE EIGHTHS BLOCK → 2583 lower three eighths block
1FB84		UPPER FIVE EIGHTHS BLOCK → 2585 lower five eighths block
1FB85		UPPER THREE QUARTERS BLOCK → 2586 lower three quarters block
1FB86		UPPER SEVEN EIGHTHS BLOCK → 2587 lower seven eighths block
1FB87		RIGHT ONE QUARTER BLOCK → 258E left one quarter block
1FB88		RIGHT THREE EIGHTHS BLOCK → 258D left three eighths block
1FB89		RIGHT FIVE EIGHTHS BLOCK → 258B left five eighths block
1FB8A		RIGHT THREE QUARTERS BLOCK → 258A left three quarters block
1FB8B		RIGHT SEVEN EIGHTHS BLOCK → 2589 left seven eighths block

Rectangular shade characters

1FB8C		LEFT HALF MEDIUM SHADE
1FB8D		RIGHT HALF MEDIUM SHADE
1FB8E		UPPER HALF MEDIUM SHADE
1FB8F		LOWER HALF MEDIUM SHADE
1FB90		INVERSE MEDIUM SHADE → 2592 medium shade
1FB91		UPPER HALF BLOCK AND LOWER HALF INVERSE MEDIUM SHADE
1FB92		UPPER HALF INVERSE MEDIUM SHADE AND LOWER HALF BLOCK
1FB93		<reserved>
1FB94		LEFT HALF INVERSE MEDIUM SHADE AND RIGHT HALF BLOCK

Fill characters

1FB95		CHECKER BOARD FILL → 259A quadrant upper left and lower right → 1F67F reverse checker board
1FB96		INVERSE CHECKER BOARD FILL → 259E quadrant upper right and lower left → 1F67E checker board
1FB97		HEAVY HORIZONTAL FILL • upper middle and lower one quarter block → 3013 geta mark
1FB98		UPPER LEFT TO LOWER RIGHT FILL → 25A7 square with upper left to lower right fill
1FB99		UPPER RIGHT TO LOWER LEFT FILL → 25A8 square with upper right to lower left fill

Smooth mosaic terminal graphic characters

1FB9A		UPPER AND LOWER TRIANGULAR HALF BLOCK → 29D7 black hourglass
1FB9B		LEFT AND RIGHT TRIANGULAR HALF BLOCK → 29D3 black bowtie

Triangular shade characters

1FB9C		UPPER LEFT TRIANGULAR MEDIUM SHADE → 25E4 black upper left triangle
-------	--	---

- 1FB9D  UPPER RIGHT TRIANGULAR MEDIUM SHADE
→ 25E5  black upper right triangle
- 1FB9E  LOWER RIGHT TRIANGULAR MEDIUM SHADE
→ 25E2  black lower right triangle
- 1FB9F  LOWER LEFT TRIANGULAR MEDIUM SHADE
→ 25E3  black lower left triangle

Character cell diagonals

- 1FBA0  BOX DRAWINGS LIGHT DIAGONAL UPPER CENTRE TO MIDDLE LEFT
- 1FBA1  BOX DRAWINGS LIGHT DIAGONAL UPPER CENTRE TO MIDDLE RIGHT
- 1FBA2  BOX DRAWINGS LIGHT DIAGONAL MIDDLE LEFT TO LOWER CENTRE
- 1FBA3  BOX DRAWINGS LIGHT DIAGONAL MIDDLE RIGHT TO LOWER CENTRE
- 1FBA4  BOX DRAWINGS LIGHT DIAGONAL UPPER CENTRE TO MIDDLE LEFT TO LOWER CENTRE
- 1FBA5  BOX DRAWINGS LIGHT DIAGONAL UPPER CENTRE TO MIDDLE RIGHT TO LOWER CENTRE
- 1FBA6  BOX DRAWINGS LIGHT DIAGONAL MIDDLE LEFT TO LOWER CENTRE TO MIDDLE RIGHT
- 1FBA7  BOX DRAWINGS LIGHT DIAGONAL MIDDLE LEFT TO UPPER CENTRE TO MIDDLE RIGHT
- 1FBA8  BOX DRAWINGS LIGHT DIAGONAL UPPER CENTRE TO MIDDLE LEFT AND MIDDLE RIGHT TO LOWER CENTRE
- 1FBA9  BOX DRAWINGS LIGHT DIAGONAL UPPER CENTRE TO MIDDLE RIGHT AND MIDDLE LEFT TO LOWER CENTRE
- 1FBAA  BOX DRAWINGS LIGHT DIAGONAL UPPER CENTRE TO MIDDLE RIGHT TO LOWER CENTRE TO MIDDLE LEFT
- 1FBAB  BOX DRAWINGS LIGHT DIAGONAL UPPER CENTRE TO MIDDLE LEFT TO LOWER CENTRE TO MIDDLE RIGHT
- 1FBAC  BOX DRAWINGS LIGHT DIAGONAL MIDDLE LEFT TO UPPER CENTRE TO MIDDLE RIGHT TO LOWER CENTRE
- 1FBAD  BOX DRAWINGS LIGHT DIAGONAL MIDDLE RIGHT TO UPPER CENTRE TO MIDDLE LEFT TO LOWER CENTRE
- 1FBAE  BOX DRAWINGS LIGHT DIAGONAL DIAMOND
→ 25C7  white diamond

Light solid line with stroke

- 1FBAF  BOX DRAWINGS LIGHT HORIZONTAL WITH VERTICAL STROKE
→ 2500  box drawings light horizontal

Terminal graphic characters

- 1FBB0  ARROWHEAD-SHAPED POINTER
→ 27A4  black rightwards arrowhead
- 1FBB1  INVERSE CHECK MARK
→ 2713  check mark
- 1FBB2  LEFT HALF RUNNING MAN
• paired with 1FBB3  , faces to the right
• the Apple II documentation refers to these characters as "Running Man"
→ 1F3C3  runner
- 1FBB3  RIGHT HALF RUNNING MAN

Arrows

- 1FBB4  INVERSE DOWNWARDS ARROW WITH TIP LEFTWARDS
→ 21B2  downwards arrow with tip leftwards
→ 21B5  downwards arrow with corner leftwards
- 1FBB5  LEFTWARDS ARROW AND UPPER AND LOWER ONE EIGHTH BLOCK
- 1FBB6  RIGHTWARDS ARROW AND UPPER AND LOWER ONE EIGHTH BLOCK
- 1FBB7  DOWNWARDS ARROW AND RIGHT ONE EIGHTH BLOCK
- 1FBB8  UPWARDS ARROW AND RIGHT ONE EIGHTH BLOCK

Terminal graphic characters

- 1FBB9  LEFT HALF FOLDER
• paired with 1FBBA 
→ 1F4C1  file folder
→ 1F5C0  folder
- 1FBBA  RIGHT HALF FOLDER
- 1FBBB  VOIDED GREEK CROSS
→ 0023  number sign
→ 256C  box drawings double vertical and horizontal
→ 2719  outlined greek cross
→ 271A  heavy greek cross
→ 1F7A3  medium greek cross
- 1FBBC  RIGHT OPEN SQUARED DOT
→ 22A1  squared dot operator

Negative terminal graphic characters

The glyphs for these "negative" characters do not necessarily extend to the edges of the character cell.

- 1FBBD  NEGATIVE DIAGONAL CROSS
• diagonals extend past the corners of the box, unlike in 274E 
→ 2573  box drawings light diagonal cross
→ 274E  negative squared cross mark
- 1FBBE  NEGATIVE DIAGONAL MIDDLE RIGHT TO LOWER CENTRE
- 1FBBF  NEGATIVE DIAGONAL DIAMOND

Terminal graphic characters

- 1FBC0  WHITE HEAVY SALTIRE WITH ROUNDED CORNERS
→ 274C  cross mark
→ 1F5D9  cancellation x
→ 1F7AC  heavy saltire
- 1FBC1  LEFT THIRD WHITE RIGHT POINTING INDEX
• glyph part, combined with 1FBC2  and 1FBC3 
→ 261E  white right pointing index
- 1FBC2  MIDDLE THIRD WHITE RIGHT POINTING INDEX
- 1FBC3  RIGHT THIRD WHITE RIGHT POINTING INDEX
- 1FBC4  NEGATIVE SQUARED QUESTION MARK
• glyph does not necessarily extend to the edges of the character cell
→ 003F  question mark
→ 2BD1  uncertainty sign
→ FFFD  replacement character
- 1FBC5  STICK FIGURE
→ 1F6B9  mens symbol
- 1FBC6  STICK FIGURE WITH ARMS RAISED
- 1FBC7  STICK FIGURE LEANING LEFT

1FBC8	👤	STICK FIGURE LEANING RIGHT
1FBC9	👤	STICK FIGURE WITH DRESS → 1F6BA 👤 womens symbol
1FBCA	➦	WHITE UP-POINTING CHEVRON → 21E7 ⬆ upwards white arrow → 2302 🏠 house → 1F835 📌 upwards finger-post arrow
1FBCB	✖	WHITE CROSS MARK → 274C ✖ cross mark
1FBCC	⌜	RAISED SMALL LEFT SQUARE BRACKET
1FBCD	➦	BLACK SMALL UP-POINTING CHEVRON → 1F835 📌 upwards finger-post arrow → 1FBCA ➦ white up-pointing chevron

Block elements

1FBCE	▒	LEFT TWO THIRDS BLOCK
1FBCF	▒	LEFT ONE THIRD BLOCK

Character cell diagonals

1FBD0	↘	BOX DRAWINGS LIGHT DIAGONAL MIDDLE RIGHT TO LOWER LEFT
1FBD1	↗	BOX DRAWINGS LIGHT DIAGONAL UPPER RIGHT TO MIDDLE LEFT
1FBD2	↖	BOX DRAWINGS LIGHT DIAGONAL UPPER LEFT TO MIDDLE RIGHT
1FBD3	↘	BOX DRAWINGS LIGHT DIAGONAL MIDDLE LEFT TO LOWER RIGHT
1FBD4	↖	BOX DRAWINGS LIGHT DIAGONAL UPPER LEFT TO LOWER CENTRE
1FBD5	↘	BOX DRAWINGS LIGHT DIAGONAL UPPER CENTRE TO LOWER RIGHT
1FBD6	↗	BOX DRAWINGS LIGHT DIAGONAL UPPER RIGHT TO LOWER CENTRE
1FBD7	↗	BOX DRAWINGS LIGHT DIAGONAL UPPER CENTRE TO LOWER LEFT
1FBD8	↖	BOX DRAWINGS LIGHT DIAGONAL UPPER LEFT TO MIDDLE CENTRE TO UPPER RIGHT
1FBD9	↖	BOX DRAWINGS LIGHT DIAGONAL UPPER RIGHT TO MIDDLE CENTRE TO LOWER RIGHT
1FBDA	↗	BOX DRAWINGS LIGHT DIAGONAL LOWER LEFT TO MIDDLE CENTRE TO LOWER RIGHT
1FBDB	↗	BOX DRAWINGS LIGHT DIAGONAL UPPER LEFT TO MIDDLE CENTRE TO LOWER LEFT
1FBDC	↖	BOX DRAWINGS LIGHT DIAGONAL UPPER LEFT TO LOWER CENTRE TO UPPER RIGHT
1FBDD	↖	BOX DRAWINGS LIGHT DIAGONAL UPPER RIGHT TO MIDDLE LEFT TO LOWER RIGHT
1FBDE	↗	BOX DRAWINGS LIGHT DIAGONAL LOWER LEFT TO UPPER CENTRE TO LOWER RIGHT
1FBDF	↗	BOX DRAWINGS LIGHT DIAGONAL UPPER LEFT TO MIDDLE RIGHT TO LOWER LEFT

Geometric shapes

1FBE0	◐	OP JUSTIFIED LOWER HALF WHITE CIRCLE → 25E1 ◐ lower half circle
1FBE1	◑	RIGHT JUSTIFIED LEFT HALF WHITE CIRCLE → 1F907 ◑ left half circle
1FBE2	◒	BOTTOM JUSTIFIED UPPER HALF WHITE CIRCLE → 2312 ◒ arc → 25E0 ◒ upper half circle
1FBE3	◓	LEFT JUSTIFIED RIGHT HALF WHITE CIRCLE
1FBE4	■	UPPER CENTRE ONE QUARTER BLOCK
1FBE5	■	LOWER CENTRE ONE QUARTER BLOCK
1FBE6	■	MIDDLE LEFT ONE QUARTER BLOCK
1FBE7	■	MIDDLE RIGHT ONE QUARTER BLOCK

1FBE8	◑	TOP JUSTIFIED LOWER HALF BLACK CIRCLE → 2BCB ◑ bottom half black circle
1FBE9	◒	RIGHT JUSTIFIED LEFT HALF BLACK CIRCLE → 25D6 ◒ left half black circle
1FBEA	◓	BOTTOM JUSTIFIED UPPER HALF BLACK CIRCLE → 2BCA ◓ top half black circle
1FBEB	◔	LEFT JUSTIFIED RIGHT HALF BLACK CIRCLE → 25D7 ◔ right half black circle
1FBEC	◕	TOP RIGHT JUSTIFIED LOWER LEFT QUARTER BLACK CIRCLE
1FBED	◖	BOTTOM LEFT JUSTIFIED UPPER RIGHT QUARTER BLACK CIRCLE
1FBEE	◗	BOTTOM RIGHT JUSTIFIED UPPER LEFT QUARTER BLACK CIRCLE
1FBEF	◘	TOP LEFT JUSTIFIED LOWER RIGHT QUARTER BLACK CIRCLE

Segmented digits

1FBF0	0	SEGMENTED DIGIT ZERO ≈ 0030 0 digit zero
1FBF1	1	SEGMENTED DIGIT ONE ≈ 0031 1 digit one
1FBF2	2	SEGMENTED DIGIT TWO ≈ 0032 2 digit two
1FBF3	3	SEGMENTED DIGIT THREE ≈ 0033 3 digit three
1FBF4	4	SEGMENTED DIGIT FOUR ≈ 0034 4 digit four
1FBF5	5	SEGMENTED DIGIT FIVE ≈ 0035 5 digit five
1FBF6	6	SEGMENTED DIGIT SIX ≈ 0036 6 digit six
1FBF7	7	SEGMENTED DIGIT SEVEN ≈ 0037 7 digit seven
1FBF8	8	SEGMENTED DIGIT EIGHT ≈ 0038 8 digit eight
1FBF9	9	SEGMENTED DIGIT NINE ≈ 0039 9 digit nine