

Representation	Proposed Character Name	Amstrad	Apple	Aquarius	Atari ST	Atari 8-Bit	CoCo	Minitel	MSX	Oric	PET/VIC20	C64/C128	RISC OS	Sinclair	Teletext	TI-99/4a	TRS-80
 1F8B0	ARROW POINTING UPWARDS THEN NORTH WEST					 7D											
 1F8B1	ARROW POINTING RIGHTWARDS THEN CURVING SOUTH WEST																 18 (M4b)
 1FB00	BLOCK SEXTANT-1			 A1			 A0, E0	 21 (G1)		 21 (G1)					 21 (G1)		 81
 1FB01	BLOCK SEXTANT-2			 A2			 90, D0	 22 (G1)		 22 (G1)					 22 (G1)		 82
 1FB02	BLOCK SEXTANT-12			 A3			 B0, F0	 23 (G1)		 23 (G1)					 23 (G1)		 83
 1FB03	BLOCK SEXTANT-3			 A4			 88, C8	 24 (G1)		 24 (G1)					 24 (G1)		 84
 1FB04	BLOCK SEXTANT-13			 A5			 A8, E8	 25 (G1)		 25 (G1)					 25 (G1)		 85
 1FB05	BLOCK SEXTANT-23			 A6			 98, D8	 26 (G1)		 26 (G1)					 26 (G1)		 86
 1FB06	BLOCK SEXTANT-123			 A7			 B8, F8	 27 (G1)		 27 (G1)					 27 (G1)		 87
 1FB07	BLOCK SEXTANT-4			 A8			 84, C4	 28 (G1)		 28 (G1)					 28 (G1)		 88
 1FB08	BLOCK SEXTANT-14			 A9			 A4, E4	 29 (G1)		 29 (G1)					 29 (G1)		 89
 1FB09	BLOCK SEXTANT-24			 AA			 94, D4	 2A (G1)		 2A (G1)					 2A (G1)		 8A
 1FB0A	BLOCK SEXTANT-124			 AB			 B4, F4	 2B (G1)		 2B (G1)					 2B (G1)		 8B
 1FB0B	BLOCK SEXTANT-34			 AC			 8C, CC	 2C (G1)		 2C (G1)					 2C (G1)		 8C
 1FB0C	BLOCK SEXTANT-134			 AD			 AC, EC	 2D (G1)		 2D (G1)					 2D (G1)		 8D
 1FB0D	BLOCK SEXTANT-234			 AE			 9C, DC	 2E (G1)		 2E (G1)					 2E (G1)		 8E
 1FB0E	BLOCK SEXTANT-1234			 AF			 BC, FC	 2F (G1)		 2F (G1)					 2F (G1)		 8F
 1FB0F	BLOCK SEXTANT-5			 B0			 82, C2	 30 (G1)		 30 (G1)					 30 (G1)		 90
 1FB10	BLOCK SEXTANT-15			 B1			 A2, E2	 31 (G1)		 31 (G1)					 31 (G1)		 91
 1FB11	BLOCK SEXTANT-25			 B2			 92, D2	 32 (G1)		 32 (G1)					 32 (G1)		 92
 1FB12	BLOCK SEXTANT-125			 B3			 B2, F2	 33 (G1)		 33 (G1)					 33 (G1)		 93
 1FB13	BLOCK SEXTANT-35			 B4			 8A, CA	 34 (G1)		 34 (G1)					 34 (G1)		 94
 1FB14	BLOCK SEXTANT-235			 B6			 9A, DA	 36 (G1)		 36 (G1)					 36 (G1)		 96
 1FB15	BLOCK SEXTANT-1235			 B7			 BA, FA	 37 (G1)		 37 (G1)					 37 (G1)		 97
 1FB16	BLOCK SEXTANT-45			 B8			 86, C6	 38 (G1)		 38 (G1)					 38 (G1)		 98
 1FB17	BLOCK SEXTANT-145			 B9			 A6, E6	 39 (G1)		 39 (G1)					 39 (G1)		 99
 1FB18	BLOCK SEXTANT-245			 BA			 96, D6	 3A (G1)		 3A (G1)					 3A (G1)		 9A
 1FB19	BLOCK SEXTANT-1245			 BB			 B6, F6	 3B (G1)		 3B (G1)					 3B (G1)		 9B
 1FB1A	BLOCK SEXTANT-345			 BC			 8E, CE	 3C (G1)		 3C (G1)					 3C (G1)		 9C
 1FB1B	BLOCK SEXTANT-1345			 BD			 AE, EE	 3D (G1)		 3D (G1)					 3D (G1)		 9D
 1FB1C	BLOCK SEXTANT-2345			 BE			 9E, DE	 3E (G1)		 3E (G1)					 3E (G1)		 9E
 1FB1D	BLOCK SEXTANT-12345			 BF			 BE, FE	 3F (G1)		 3F (G1)					 3F (G1)		 9F
 1FB1E	BLOCK SEXTANT-6			 E0			 81, C1	 60 (G1)		 40 (G1)					 60 (G1)		 A0
 1FB1F	BLOCK SEXTANT-16			 E1			 A1, E1	 61 (G1)		 41 (G1)					 61 (G1)		 A1
 1FB20	BLOCK SEXTANT-26			 E2			 91, D1	 62 (G1)		 42 (G1)					 62 (G1)		 A2
 1FB21	BLOCK SEXTANT-126			 E3			 B1, F1	 63 (G1)		 43 (G1)					 63 (G1)		 A3
 1FB22	BLOCK SEXTANT-36			 E4			 89, C9	 64 (G1)		 44 (G1)					 64 (G1)		 A4
 1FB23	BLOCK SEXTANT-136																

Representation	Proposed Character Name	Amstrad	Apple	Aquarius	Atari ST	Atari 8-Bit	CoCo	Minitel	MSX	Oric	PET/VIC20	C64/C128	RISC OS	Sinclair	Teletext	TI-99/4a	TRS-80	
	1FB28 BLOCK SEXTANT-1246				EB			B5, F5		6B (G1)			4B (G1)			6B (G1)		AB
	1FB29 BLOCK SEXTANT-346				EC			8D, CD		6C (G1)			4C (G1)			6C (G1)		AC
	1FB2A BLOCK SEXTANT-1346				ED			AD, ED		6D (G1)			4D (G1)			6D (G1)		AD
	1FB2B BLOCK SEXTANT-2346				EE			9D, DD		6E (G1)			4E (G1)			6E (G1)		AE
	1FB2C BLOCK SEXTANT-12346				EF			BD, FD		6F (G1)			4F (G1)			6F (G1)		AF
	1FB2D BLOCK SEXTANT-56				F0			83, C3		70 (G1)			50 (G1)			70 (G1)		B0
	1FB2E BLOCK SEXTANT-156				F1			A3, E3		71 (G1)			51 (G1)			71 (G1)		B1
	1FB2F BLOCK SEXTANT-256				F2			93, D3		72 (G1)			52 (G1)			72 (G1)		B2
	1FB30 BLOCK SEXTANT-1256				F3			B3, F3		73 (G1)			53 (G1)			73 (G1)		B3
	1FB31 BLOCK SEXTANT-356				F4			8B, CB		74 (G1)			54 (G1)			74 (G1)		B4
	1FB32 BLOCK SEXTANT-1356				F5			AB, EB		75 (G1)			55 (G1)			75 (G1)		B5
	1FB33 BLOCK SEXTANT-2356				F6			9B, DB		76 (G1)			56 (G1)			76 (G1)		B6
	1FB34 BLOCK SEXTANT-12356				F7			BB, FB		77 (G1)			57 (G1)			77 (G1)		B7
	1FB35 BLOCK SEXTANT-456				F8			87, C7		78 (G1)			58 (G1)			78 (G1)		B8
	1FB36 BLOCK SEXTANT-1456				F9			A7, E7		79 (G1)			59 (G1)			79 (G1)		B9
	1FB37 BLOCK SEXTANT-2456				FA			97, D7		7A (G1)			5A (G1)			7A (G1)		BA
	1FB38 BLOCK SEXTANT-12456				FB			B7, F7		7B (G1)			5B (G1)			7B (G1)		BB
	1FB39 BLOCK SEXTANT-3456				FC			8F, CF		7C (G1)			5C (G1)			7C (G1)		BC
	1FB3A BLOCK SEXTANT-13456				FD			AF, EF		7D (G1)			5D (G1)			7D (G1)		BD
	1FB3B BLOCK SEXTANT-23456				FE			9F, DF		7E (G1)			5E (G1)			7E (G1)		BE
	1FB3C LOWER LEFT BLOCK DIAGONAL LOWER MIDDLE LEFT TO LOWER CENTRE															20 (G3)		
	1FB3D LOWER LEFT BLOCK DIAGONAL LOWER MIDDLE LEFT TO LOWER RIGHT															21 (G3)		
	1FB3E LOWER LEFT BLOCK DIAGONAL UPPER MIDDLE LEFT TO LOWER CENTRE															22 (G3)		
	1FB3F LOWER LEFT BLOCK DIAGONAL UPPER MIDDLE LEFT TO LOWER RIGHT															23 (G3)		
	1FB40 LOWER LEFT BLOCK DIAGONAL UPPER LEFT TO LOWER CENTRE															24 (G3)		
	1FB41 LOWER RIGHT BLOCK DIAGONAL UPPER MIDDLE LEFT TO UPPER CENTRE															26 (G3)		
	1FB42 LOWER RIGHT BLOCK DIAGONAL UPPER MIDDLE LEFT TO UPPER RIGHT															27 (G3)		
	1FB43 LOWER RIGHT BLOCK DIAGONAL LOWER MIDDLE LEFT TO UPPER CENTRE															28 (G3)		
	1FB44 LOWER RIGHT BLOCK DIAGONAL LOWER MIDDLE LEFT TO UPPER RIGHT															29 (G3)		
	1FB45 LOWER RIGHT BLOCK DIAGONAL LOWER LEFT TO UPPER CENTRE															2A (G3)		
	1FB46 LOWER RIGHT BLOCK DIAGONAL LOWER MIDDLE LEFT TO UPPER MIDDLE RIGHT															2B (G3)		
	1FB47 LOWER RIGHT BLOCK DIAGONAL LOWER CENTRE TO LOWER MIDDLE RIGHT															30 (G3)		

Representation	Proposed Character Name	Amstrad	Apple	Aquarius	Atari ST	Atari 8-Bit	CoCo	Minitel	MSX	Oric	PET/VIC20	C64/C128	RISC OS	Sinclair	Teletext	TI-99/4a	TRS-80
 1FB48	LOWER RIGHT BLOCK DIAGONAL LOWER LEFT TO LOWER MIDDLE RIGHT														 31 (G3)		
 1FB49	LOWER RIGHT BLOCK DIAGONAL LOWER CENTRE TO UPPER MIDDLE RIGHT														 32 (G3)		
 1FB4A	LOWER RIGHT BLOCK DIAGONAL LOWER LEFT TO UPPER MIDDLE RIGHT														 33 (G3)		
 1FB4B	LOWER RIGHT BLOCK DIAGONAL LOWER CENTRE TO UPPER RIGHT														 34 (G3)		
 1FB4C	LOWER LEFT BLOCK DIAGONAL UPPER CENTRE TO UPPER MIDDLE RIGHT														 36 (G3)		
 1FB4D	LOWER LEFT BLOCK DIAGONAL UPPER LEFT TO UPPER MIDDLE RIGHT														 37 (G3)		
 1FB4E	LOWER LEFT BLOCK DIAGONAL UPPER CENTRE TO LOWER MIDDLE RIGHT														 38 (G3)		
 1FB4F	LOWER LEFT BLOCK DIAGONAL UPPER LEFT TO LOWER MIDDLE RIGHT														 39 (G3)		
 1FB50	LOWER LEFT BLOCK DIAGONAL UPPER CENTRE TO LOWER RIGHT														 3A (G3)		
 1FB51	LOWER LEFT BLOCK DIAGONAL UPPER MIDDLE LEFT TO LOWER MIDDLE RIGHT														 3B (G3)		
 1FB52	UPPER RIGHT BLOCK DIAGONAL LOWER MIDDLE LEFT TO LOWER CENTRE														 60 (G3)		
 1FB53	UPPER RIGHT BLOCK DIAGONAL LOWER MIDDLE LEFT TO LOWER RIGHT														 61 (G3)		
 1FB54	UPPER RIGHT BLOCK DIAGONAL UPPER MIDDLE LEFT TO LOWER CENTRE														 62 (G3)		
 1FB55	UPPER RIGHT BLOCK DIAGONAL UPPER MIDDLE LEFT TO LOWER RIGHT														 63 (G3)		
 1FB56	UPPER RIGHT BLOCK DIAGONAL UPPER LEFT TO LOWER CENTRE														 64 (G3)		
 1FB57	UPPER LEFT BLOCK DIAGONAL UPPER MIDDLE LEFT TO UPPER CENTRE														 66 (G3)		
 1FB58	UPPER LEFT BLOCK DIAGONAL UPPER MIDDLE LEFT TO UPPER RIGHT														 67 (G3)		
 1FB59	UPPER LEFT BLOCK DIAGONAL LOWER MIDDLE LEFT TO UPPER CENTRE														 68 (G3)		
 1FB5A	UPPER LEFT BLOCK DIAGONAL LOWER MIDDLE LEFT TO UPPER RIGHT														 69 (G3)		
 1FB5B	UPPER LEFT BLOCK DIAGONAL LOWER LEFT TO UPPER CENTRE														 6A (G3)		
 1FB5C	UPPER LEFT BLOCK DIAGONAL LOWER MIDDLE LEFT TO UPPER MIDDLE RIGHT														 6B (G3)		

Representation	Proposed Character Name	Amstrad	Apple	Aquarius	Atari ST	Atari 8-Bit	CoCo	Minitel	MSX	Oric	PET/VIC20	C64/C128	RISC OS	Sinclair	Teletext	TI-99/4a	TRS-80			
	1FB5D	UPPER LEFT BLOCK DIAGONAL LOWER CENTRE TO LOWER MIDDLE RIGHT															70 (G3)			
	1FB5E	UPPER LEFT BLOCK DIAGONAL LOWER LEFT TO LOWER MIDDLE RIGHT															71 (G3)			
	1FB5F	UPPER LEFT BLOCK DIAGONAL LOWER CENTRE TO UPPER MIDDLE RIGHT															72 (G3)			
	1FB60	UPPER LEFT BLOCK DIAGONAL LOWER LEFT TO UPPER MIDDLE RIGHT															73 (G3)			
	1FB61	UPPER LEFT BLOCK DIAGONAL LOWER CENTRE TO UPPER RIGHT															74 (G3)			
	1FB62	UPPER RIGHT BLOCK DIAGONAL UPPER CENTRE TO UPPER MIDDLE RIGHT															76 (G3)			
	1FB63	UPPER RIGHT BLOCK DIAGONAL UPPER LEFT TO UPPER MIDDLE RIGHT															77 (G3)			
	1FB64	UPPER RIGHT BLOCK DIAGONAL UPPER CENTRE TO LOWER MIDDLE RIGHT															78 (G3)			
	1FB65	UPPER RIGHT BLOCK DIAGONAL UPPER LEFT TO LOWER MIDDLE RIGHT															79 (G3)			
	1FB66	UPPER RIGHT BLOCK DIAGONAL UPPER CENTRE TO LOWER RIGHT															7A (G3)			
	1FB67	UPPER RIGHT BLOCK DIAGONAL UPPER MIDDLE LEFT TO LOWER MIDDLE RIGHT															7B (G3)			
	1FB68	UPPER AND RIGHT AND LOWER TRIANGULAR THREE QUARTERS BLOCK															2C (G3)			
	1FB69	LEFT AND LOWER AND RIGHT TRIANGULAR THREE QUARTERS BLOCK															2D (G3)			
	1FB6A	UPPER AND LEFT AND LOWER TRIANGULAR THREE QUARTERS BLOCK															3C (G3)			
	1FB6B	LEFT AND UPPER AND RIGHT TRIANGULAR THREE QUARTERS BLOCK															3D (G3)			
	1FB6C	LEFT TRIANGULAR ONE QUARTER BLOCK															6C (G3)			
	1FB6D	UPPER TRIANGULAR ONE QUARTER BLOCK															6D (G3)			
	1FB6E	RIGHT TRIANGULAR ONE QUARTER BLOCK															7C (G3)			
	1FB6F	LOWER TRIANGULAR ONE QUARTER BLOCK															7D (G3)			
	1FB70	VERTICAL ONE EIGHTH BLOCK-2															2E (G3)			
	1FB71	VERTICAL ONE EIGHTH BLOCK-3																		
	1FB72	VERTICAL ONE EIGHTH BLOCK-4																		
	1FB73	VERTICAL ONE EIGHTH BLOCK-5																		
	1FB74	VERTICAL ONE EIGHTH BLOCK-6																		
	1FB75	VERTICAL ONE EIGHTH BLOCK-7															3E (G3)			

Representation	Proposed Character Name	Amstrad	Apple	Aquarius	Atari ST	Atari 8-Bit	CoCo	Minitel	MSX	Oric	PET/VIC20	C64/C128	RISC OS	Sinclair	Teletext	TI-99/4a	TRS-80
— 1FB76	HORIZONTAL ONE EIGHTH BLOCK-2										— 45 (G0)	— 45 (G0)					
— 1FB77	HORIZONTAL ONE EIGHTH BLOCK-3										— 44 (G0)	— 44 (G0)					
— 1FB78	HORIZONTAL ONE EIGHTH BLOCK-4										— 43 (G0)	— 43 (G0)					
— 1FB79	HORIZONTAL ONE EIGHTH BLOCK-5										— 40 (G0)	— 40 (G0)					
— 1FB7A	HORIZONTAL ONE EIGHTH BLOCK-6										— 46 (G0)	— 46 (G0)					
— 1FB7B	HORIZONTAL ONE EIGHTH BLOCK-7										— 52 (G0)	— 52 (G0)					
└ 1FB7C	LEFT AND LOWER ONE EIGHTH BLOCK		└ 54								└ 4C (G0)	└ 4C (G0)					
┐ 1FB7D	LEFT AND UPPER ONE EIGHTH BLOCK										┐ 4F (G0)	┐ 4F (G0)					
┐ 1FB7E	RIGHT AND UPPER ONE EIGHTH BLOCK										┐ 50 (G0)	┐ 50 (G0)					
└ 1FB7F	RIGHT AND LOWER ONE EIGHTH BLOCK										└ 7A (G0)	└ 7A (G0)					
— 1FB80	UPPER AND LOWER ONE EIGHTH BLOCK		— 5C														
≡ 1FB81	HORIZONTAL ONE EIGHTH BLOCK-1358		≡ 47 (llgs)														
▀ 1FB82	UPPER ONE QUARTER BLOCK								▀ C3		▀ 77	▀ 77					
▀ 1FB83	UPPER THREE EIGHTHS BLOCK										▀ 78	▀ 78					
▀ 1FB84	UPPER FIVE EIGHTHS BLOCK										▀ F9	▀ F9					
▀ 1FB85	UPPER THREE QUARTERS BLOCK								▀ C5		▀ EF	▀ EF					
▀ 1FB86	UPPER SEVEN EIGHTHS BLOCK										▀ E4	▀ E4					
▮ 1FB87	RIGHT ONE QUARTER BLOCK								▮ C9		▮ 6A	▮ 6A					
▮ 1FB88	RIGHT THREE EIGHTHS BLOCK										▮ 76	▮ 76					
▮ 1FB89	RIGHT FIVE EIGHTHS BLOCK										▮ F5	▮ F5					
▮ 1FB8A	RIGHT THREE QUARTERS BLOCK								▮ CA		▮ F4	▮ F4					▮ 9A (M4b)
▮ 1FB8B	RIGHT SEVEN EIGHTHS BLOCK										▮ E5	▮ E5					
▧ 1FB8C	LEFT HALF MEDIUM SHADE	▧ DB		▧ 85							▧ 5C	▧ 5C					
▧ 1FB8D	RIGHT HALF MEDIUM SHADE	▧ D9		▧ 95													
▧ 1FB8E	UPPER HALF MEDIUM SHADE	▧ D8		▧ 94										▧ 0B ('80), 0A ('81)			
▧ 1FB8F	LOWER HALF MEDIUM SHADE	▧ DA		▧ 84							▧ 68	▧ 68		▧ 0A ('80), 09 ('81)			
▩ 1FB90	INVERSE MEDIUM SHADE		▩ 57								▩ E6	▩ E6		▩ 89 ('80), 88 ('81)			
▩ 1FB91	UPPER HALF BLOCK AND LOWER HALF INVERSE MEDIUM SHADE										▩ E8	▩ E8		▩ 8A ('80), 89 ('81)			
▩ 1FB92	UPPER HALF INVERSE MEDIUM SHADE AND LOWER HALF BLOCK													▩ 8B ('80), 8A ('81)			
▩ 1FB94	LEFT HALF INVERSE MEDIUM SHADE AND RIGHT HALF BLOCK										▩ DC	▩ DC					
▩ 1FB95	CHECKER BOARD FILL	▩ CE									▩ 5E (G1)	▩ DE (G1)					
▩ 1FB96	INVERSE CHECKER BOARD FILL								▩ D7		▩ DE (G1)	▩ 5E (G1)					

Representation	Proposed Character Name	Amstrad	Apple	Aquarius	Atari ST	Atari 8-Bit	CoCo	Minitel	MSX	Oric	PET/VIC20	C64/C128	RISC OS	Sinclair	Teletext	TI-99/4a	TRS-80
1FBF1	SEGMENTED DIGIT ONE				11												
1FBF2	SEGMENTED DIGIT TWO				12												
1FBF3	SEGMENTED DIGIT THREE				13												
1FBF4	SEGMENTED DIGIT FOUR				14												
1FBF5	SEGMENTED DIGIT FIVE				15												
1FBF6	SEGMENTED DIGIT SIX				16												
1FBF7	SEGMENTED DIGIT SEVEN				17												
1FBF8	SEGMENTED DIGIT EIGHT				18												
1FBF9	SEGMENTED DIGIT NINE				19												

Representation	Character Not Proposed	Amstrad	Apple	Aquarius	Atari ST	Atari 8-Bit	CoCo	Minitel	MSX	Oric	PET/VIC20	C64/C128	RISC OS	Sinclair	Teletext	TI-99/4a	TRS-80
	Atari logo, left half				0E												
	Atari logo, right half				0F												
	Bob Dobbs, top left				1C												
	Bob Dobbs, top right				1D												
	Bob Dobbs, bottom left				1E												
	Bob Dobbs, bottom right				1F												
	Apple logo, outline		41														
	Apple logo, solid		40														
87	symbol for hex value 87												87				
	unidentified character																EE
	unidentified character																FB
	unidentified character																1D (M4b)
	unidentified character	EF															
	unidentified character	FC															
	unidentified character	FD															

Representation	Existing Character Name	Amstrad	Apple	Aquarius	Atari ST	Atari 8-Bit	CoCo	Minitel	MSX	Oric	PET/VIC20	C64/C128	RISC OS	Sinclair	Teletext	TI-99/4a	TRS-80
	(below U+2000 omitted)																
2013	EN DASH												97				
2014	EM DASH												98				
2016	DOUBLE VERTICAL LINE														7C (G0)		
2018	LEFT SINGLE QUOTATION MARK	A7											90		29 (G2)		60
2019	RIGHT SINGLE QUOTATION MARK	27											91		39 (G2)		
201C	LEFT DOUBLE QUOTATION MARK												94		2A (G2)		
201D	RIGHT DOUBLE QUOTATION MARK												95		3A (G2)		
201E	DOUBLE LOW-9 QUOTATION MARK												96				
2020	DAGGER				BB								9C				C8 (M4b)
2021	DOUBLE DAGGER								D9				9D				
2022	BULLET					14			0147		51 (G0)	51 (G0)	8F		4D (G3)		
2026	HORIZONTAL ELLIPSIS		49										8C				
2030	PER MILLE SIGN								BD				8E		57 (G2)		

Representation	Existing Character Name	Amstrad	Apple	Aquarius	Atari ST	Atari 8-Bit	CoCo	Minitel	MSX	Oric	PET/VIC20	C64/C128	RISC OS	Sinclair	Teletext	TI-99/4a	TRS-80
≡ 2261	IDENTICAL TO				≡ F0				≡ F0								
≤ 2264	LESS-THAN OR EQUAL TO				≤ F3				≤ F3								≤ C6
≥ 2265	GREATER-THAN OR EQUAL TO				≥ F2				≥ F2								≥ C7
∅ 2300	DIAMETER SIGN								∅ ED								
↻ 2301	ELECTRIC ARROW																↻ E8
♠ 2302	HOUSE				♠ 7F												
⋈ 2307	WAVY LINE																⋈ E6
¬ 2310	REVERSED NOT SIGN				¬ A9				¬ A9								
⌚ 231B	HOURLASS		⌚ 43														
∫ 2320	TOP HALF INTEGRAL				∫ F4				∫ F4								
∫ 2321	BOTTOM HALF INTEGRAL				∫ F5				∫ F5								
🔔 237E	BELL SYMBOL																🔔 EA
▮ 23B8	LEFT VERTICAL BOX LINE	▮ D3				▮ 16		▮ 7B									
▮ 23B9	RIGHT VERTICAL BOX LINE	▮ D1				▮ 02		▮ 7D									
▬ 23BA	HORIZONTAL SCAN LINE-1	▬ D0				▬ 0D		▬ 7E									
▬ 23BD	HORIZONTAL SCAN LINE-9	▬ D2				▬ 0E		▬ 5F									
␣ 240C	SYMBOL FOR FORM FEED				␣ 0C												
␣ 240D	SYMBOL FOR CARRIAGE RETURN				␣ 0D												␣ 0D (MIII)
␣ 241B	SYMBOL FOR ESCAPE				␣ 1B	␣ 1B											
⌘ 2425	SYMBOL FOR DELETE FORM TWO		⌘ FF														⌘ 7F (MI)
▬ 2500	BOX DRAWINGS LIGHT HORIZONTAL	▬ 9A	▬ 53	▬ AC		▬ 12		▬ 60	▬ 0157		▬ 40	▬ 40			▬ 51 (G3)		
▮ 2502	BOX DRAWINGS LIGHT VERTICAL	▮ 95		▮ D6		▮ 7C		▮ 7C	▮ 0156		▮ 5D	▮ 5D			▮ 50 (G3)		
└ 250C	BOX DRAWINGS LIGHT DOWN AND RIGHT	└ 96		└ DE		└ 11			└ 0158		└ 70	└ 70			└ 52 (G3)		
└ 2510	BOX DRAWINGS LIGHT DOWN AND LEFT	└ 9C		└ CE		└ 05			└ 0159		└ 6E	└ 6E			└ 53 (G3)		
└ 2514	BOX DRAWINGS LIGHT UP AND RIGHT	└ 93		└ CF		└ 1A			└ 015A		└ 6D	└ 6D			└ 54 (G3)		
└ 2518	BOX DRAWINGS LIGHT UP AND LEFT	└ 99		└ DF		└ 03			└ 015B		└ 7D	└ 7D			└ 55 (G3)		
└ 251C	BOX DRAWINGS LIGHT VERTICAL AND RIGHT	└ 97		└ CD		└ 01			└ 0154		└ 6B	└ 6B			└ 56 (G3)		
└ 251D	BOX DRAWINGS VERTICAL LIGHT AND RIGHT HEAVY														└ 42 (G3)		
└ 2524	BOX DRAWINGS LIGHT VERTICAL AND LEFT	└ 9D		└ DD		└ 04			└ 0153		└ 73	└ 73			└ 57 (G3)		
└ 2525	BOX DRAWINGS VERTICAL LIGHT AND LEFT HEAVY														└ 43 (G3)		
└ 252C	BOX DRAWINGS LIGHT DOWN AND HORIZONTAL	└ 9E		└ DC		└ 17			└ 0152		└ 72	└ 72			└ 58 (G3)		
└ 252F	BOX DRAWINGS DOWN LIGHT AND HORIZONTAL HEAVY														└ 41 (G3)		
└ 2534	BOX DRAWINGS LIGHT UP AND HORIZONTAL	└ 9B		└ CC		└ 18			└ 0151		└ 71	└ 71			└ 59 (G3)		
└ 2537	BOX DRAWINGS UP LIGHT AND HORIZONTAL HEAVY														└ 40 (G3)		
⊕ 253C	BOX DRAWINGS LIGHT VERTICAL AND HORIZONTAL	⊕ 9F		⊕ C8		⊕ 13			⊕ 0155		⊕ 5B	⊕ 5B			⊕ 5A (G3)		
⊕ 253F	BOX DRAWINGS VERTICAL LIGHT AND HORIZONTAL HEAVY														⊕ 4C (G3)		

Representation	Existing Character Name	Amstrad	Apple	Aquarius	Atari ST	Atari 8-Bit	CoCo	Minitel	MSX	Oric	PET/VIC20	C64/C128	RISC OS	Sinclair	Teletext	TI-99/4a	TRS-80
	256D BOX DRAWINGS LIGHT ARC DOWN AND RIGHT										 55 (G0)	 55 (G0)					
	256E BOX DRAWINGS LIGHT ARC DOWN AND LEFT										 49 (G0)	 49 (G0)					
	256F BOX DRAWINGS LIGHT ARC UP AND LEFT										 4B (G0)	 4B (G0)					
	2570 BOX DRAWINGS LIGHT ARC UP AND RIGHT										 4A (G0)	 4A (G0)					
	2571 BOX DRAWINGS LIGHT DIAGONAL UPPER RIGHT TO LOWER LEFT	 CC		 CA		 06			 015D		 4E (G0)	 4E (G0)					
	2572 BOX DRAWINGS LIGHT DIAGONAL UPPER LEFT TO LOWER RIGHT	 CD		 DA		 07			 015E		 4D (G0)	 4D (G0)					
	2573 BOX DRAWINGS LIGHT DIAGONAL CROSS	 CB		 D8					 015C		 56 (G0)	 56 (G0)					
	2574 BOX DRAWINGS LIGHT LEFT	 98															
	2575 BOX DRAWINGS LIGHT UP	 91															
	2576 BOX DRAWINGS LIGHT RIGHT	 92															
	2577 BOX DRAWINGS LIGHT DOWN	 94															
	2580 UPPER HALF BLOCK	 83				 95	 [8-F]C		 DF		 E2	 E2			 83 ('80), 03 ('81)		
	2581 LOWER ONE EIGHTH BLOCK			 90							 64	 64					
	2582 LOWER ONE QUARTER BLOCK			 88					 C0		 6F	 6F					
	2583 LOWER THREE EIGHTHS BLOCK										 79	 79					
	2584 LOWER HALF BLOCK	 8C		 1F		 15	 [8-F]3		 DC		 62	 62			 03 ('80), 83 ('81)		
	2585 LOWER FIVE EIGHTHS BLOCK										 F8	 F8					
	2586 LOWER THREE QUARTERS BLOCK			 89					 C2		 F7	 F7					
	2587 LOWER SEVEN EIGHTHS BLOCK			 80							 E3	 E3					
	2588 FULL BLOCK	 8F		 7F, FF		 A0	 [8-F]F, BF, FF	 7F (G1)	 DB, FF	 7F (G0), 5F (G1)	 A0, E0	 A0, E0		 80	 7F (G1), 3F (G3)	 1E	 BF
	2589 LEFT SEVEN EIGHTHS BLOCK		 4E	 91							 E7	 E7					
	258A LEFT THREE QUARTERS BLOCK			 C3					 C8		 EA	 EA					
	258B LEFT FIVE EIGHTHS BLOCK										 F6	 F6					
	258C LEFT HALF BLOCK	 85		 99, B5		 19	 [8-F]A, AA, EA	 35 (G1)	 DD	 35 (G1)	 61	 61		 02 ('80), 05 ('81)	 35 (G1)		 95
	258D LEFT THREE EIGHTHS BLOCK			 98							 75	 75					
	258E LEFT ONE QUARTER BLOCK			 97					 C6		 74	 74					 1A (M4b)
	258F LEFT ONE EIGHTH BLOCK		 5F	 81							 65	 65					
	2590 RIGHT HALF BLOCK	 8A		 EA		 99	 [8-F]5, 95, D5	 6A (G1)	 DE	 4A (G1)	 E1	 E1		 82 ('80), 85 ('81)	 6A (G1)		 AA
	2592 MEDIUM SHADE	 CF	 56	 86						 7E (G0)	 66	 66		 09 ('80), 08 ('81)	 2F (G3)		
	2594 UPPER ONE EIGHTH BLOCK		 4C								 63	 63					
	2595 RIGHT ONE EIGHTH BLOCK		 5A								 67	 67					
	2596 QUADRANT LOWER LEFT	 84		 1C		 0F	 [8-F]2		 D6		 7B	 7B		 06 ('80), 04 ('81)			
	2597 QUADRANT LOWER RIGHT	 88		 1A		 09	 [8-F]1		 D4		 6C	 6C		 07 ('80), 87 ('81)			
	2598 QUADRANT UPPER LEFT	81		1D		0C	[8-F]8		D3		7E	7E		04 ('80), 01 ('81)			

Representation	Existing Character Name	Amstrad	Apple	Aquarius	Atari ST	Atari 8-Bit	CoCo	Minitel	MSX	Oric	PET/VIC20	C64/C128	RISC OS	Sinclair	Teletext	TI-99/4a	TRS-80	
	2599	QUADRANT UPPER LEFT AND LOWER LEFT AND LOWER RIGHT	 8D				 8B	 [8-F]B			 FC	 FC		 85 ('80), 82 ('81)				
	259A	QUADRANT UPPER LEFT AND LOWER RIGHT	 89		 1E			 [8-F]9		 C1		 7F	 7F		 88 ('80), 86 ('81)			
	259B	QUADRANT UPPER LEFT AND UPPER RIGHT AND LOWER LEFT	 87				 89	 [8-F]E			 EC	 EC		 87 ('80), 07 ('81)				
	259C	QUADRANT UPPER LEFT AND UPPER RIGHT AND LOWER RIGHT	 8B				 8F	 [8-F]D			 FB	 FB		 86 ('80), 84 ('81)				
	259D	QUADRANT UPPER RIGHT	 82		 1B		 0B	 [8-F]4		 D5		 7C	 7C		 05 ('80), 02 ('81)			
	259E	QUADRANT UPPER RIGHT AND LOWER LEFT	 86					 [8-F]6		 C7		 FF	 FF		 08 ('80), 06 ('81)			
	259F	QUADRANT UPPER RIGHT AND LOWER LEFT AND LOWER RIGHT	 8E				 8C	 [8-F]7				 FE	 FE		 84 ('80), 81 ('81)			
	25A0	BLACK SQUARE	 E9						 FE							 7F (G0)		
	25A1	WHITE SQUARE	 E8															
	25AC	BLACK RECTANGLE							 C4									
	25AD	WHITE RECTANGLE															 17 (M4b)	
	25B2	BLACK UP-POINTING TRIANGLE	 F4		 8F													
	25B6	BLACK RIGHT-POINTING TRIANGLE	 F6		 8E		 7F											
	25BC	BLACK DOWN-POINTING TRIANGLE	 F5		 9F													
	25C0	BLACK LEFT-POINTING TRIANGLE	 F7		 9E		 7E											
	25C6	BLACK DIAMOND		 5B														
	25CA	LOZENGE							 BC									
	25CB	WHITE CIRCLE	 E6						 0149		 57 (G0)	 57 (G0)			 4F (G3)			
	25CF	BLACK CIRCLE	 E7												 4E (G3)			
	25D8	INVERSE BULLET					 94		 0148		 D1 (G0)	 D1 (G0)						
	25D9	INVERSE WHITE CIRCLE							 014A		 D7 (G0)	 D7 (G0)						
	25E2	BLACK LOWER RIGHT TRIANGLE	 D6		 C0		 08				 E9 (G0)	 E9 (G0)			 35 (G3)			
	25E3	BLACK LOWER LEFT TRIANGLE	 D7		 C1		 0A				 DF (G0)	 DF (G0)			 25 (G3)		 1B (M4b)	
	25E4	BLACK UPPER LEFT TRIANGLE	 D4				 88				 69 (G0)	 69 (G0)			 75 (G3)			
	25E5	BLACK UPPER RIGHT TRIANGLE	 D5				 8A				 5F (G0)	 5F (G0)			 65 (G3)		 9B (M4b)	
	25F0	WHITE SQUARE WITH UPPER LEFT QUADRANT											83					
	2639	WHITE FROWNING FACE	E1														C5	
	263A	WHITE SMILING FACE	E0						0141								C4	
	263B	BLACK SMILING FACE							0142									
	263C	WHITE SUN WITH RAYS	EE						014F									
	2640	FEMALE SIGN	EB						014C								FA	
	2642	MALE SIGN	EA						014B								F9	
	2660	BLACK SPADE SUIT	E5		8A		7B		0146		41 (G0)	41 (G0)					C0	
	2663	BLACK CLUB SUIT	E2		D5		10		0145		58 (G0)	58 (G0)					C3	
	2665	BLACK HEART SUIT	E4		D4		00		0143		53 (G0)	53 (G0)					C1	

[illegible]